

# Exam Winter Semester 2022

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

- Exam Winter Semester 2022** ..... 2
- Additional permitted Aids ..... 2
- Hits ..... 2
- Only EEE1-relevant Part ..... 2
- Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022) ..... 2
- Exercise E3 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022) ..... 3
- Exercise E1 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022) ..... 3
- Exercise E2 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022) ..... 5
- Full Exam ..... 9
- Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022) ..... 9
- Exercise E3 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022) ..... 10
- Exercise E1 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022) ..... 10
- Exercise E2 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022) ..... 12
- Exercise E1 Charging Capacitors (written test, approx. 16 % of a 60-minute written test, WS2022) ..... 16
- Exercise E1 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022) ..... 17
- Exercise E9 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022) ..... 17
- Exercise E1 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022) ..... 18

# Exam Winter Semester 2022

## Additional permitted Aids

- non-programmable calculator,
- formulary (2 DIN A4 pages)

## Hits

- The duration of the exam is 60 min.
- Attempts to cheat will lead to exclusion and failure of the exam.
- Withdrawal is no longer possible after these exam has been handed out.
- Please write down intermediate calculations and results on the assignment sheet. (when more space is needed also on the reverse side. In this case: Mark it clearly).
- Always use units in the calculation.
- Use a document-proof, non-red pen.

## Only EEE1-relevant Part

**This part is only for about 25 minutes !**

### Exercise E1 Resistance of a Wire by Resistivity

(written test, approx. 6 % of a 60-minute written test, WS2022)

2. Heating elements are used to heat wire with a temperature of  $180^\circ\text{C}$ . Electric power dissipation (= heat flow) of  $P=40\text{ W}$  is necessary.

Determine the current  $I$  needed to operate for heating elements.

The Nichrome wire has a resistivity of  $1.10 \cdot 10^{-6}\ \Omega\text{m}$ .

The heating element is  $3\text{ m}$  long and has a diameter of  $3.57\text{ mm}$ .

∴ Calculate the resistance  $R$  of the heating element.

Solution

$$\begin{aligned} P &= U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \\ &= \sqrt{\frac{P}{R}} = \sqrt{\frac{40\text{ W}}{0.33\ \Omega}} \end{aligned}$$

$$\begin{aligned} R &= \rho \cdot \frac{l}{A} \quad \text{with } A = r^2 \cdot \pi = \\ &= \frac{1}{4} d^2 \cdot \pi \quad \text{and } R = \rho \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad \text{and } R = \\ &= 1.10 \cdot 10^{-6}\ \Omega\text{m} \cdot \frac{4 \cdot 3\text{ m}}{(3.57 \cdot 10^{-3}\text{ m})^2 \cdot \pi} \end{aligned}$$

**Exercise E3 Temperature-dependent Resistance**  
**(written test, approx. 6 % of a 60-minute written test, WS2022)**

2. The diagram explains why the effect of constant resistance on refrigeration system structure is not as significant as it seems. The circuit has a resistor of  $10 \text{ k}\Omega$  at  $25^\circ\text{C}$ . Its temperature coefficients are:  $\alpha = 0.01 \text{ } \frac{1}{\text{K}}$  and  $\beta = 71 \cdot 10^{-6} \text{ } \frac{1}{\text{K}^2}$ .

Result: The temperature inside the refrigeration system can reach down to  $-40^\circ\text{C}$ .

Calculate the resistance of the thermistor at  $-40^\circ\text{C}$ .

$$R = 6.5 \text{ k}\Omega$$

The power transfered to the load is  $P = \frac{U^2}{R}$ . Therefore, a solution is to increase the resistance.

Therefore, with constant  $U$  and increasing  $R$  the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

Therefore, with constant  $U$  and increasing  $R$  the power decreases. Ten times more resistance decreases the heat flow to one-tenth.


```
\begin{align*} R &= R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2) && | \\ \text{with } \Delta T &= T_{\text{end}} - T_{\text{start}} && \\ R &= 10 \text{ k}\Omega \cdot \left(1 + 0.01 \frac{1}{\text{K}} \cdot (-40^\circ\text{C} - 25^\circ\text{C}) + 71 \cdot 10^{-6} \frac{1}{\text{K}^2} \cdot (-40^\circ\text{C} - 25^\circ\text{C})^2\right) && \\ &&& \end{align*}
```

**Exercise E1 Pure Resistor Network Simplification**  
**(written test, approx. 13 % of a 60-minute written test, WS2022)**

The following shall be solved:  $R_1 = 20 \text{ }\Omega$ ,  $R_2 = 10 \text{ }\Omega$ ,  $R_3 = 10 \text{ }\Omega$ ,  $R_4 = 10 \text{ }\Omega$  and the voltage  $U = 10 \text{ V}$ .  
 Result:  $R_{\text{eq}} = 13.8 \text{ }\Omega$ .

```
Solution
\begin{align*} R_{\text{eq}} &= 13.8 \text{ }\Omega && \end{align*}
```

Now a wye-delta transformation is necessary.




Since  $R_2=R_3$  and based on the equations for the transformation, the transformed  $R_Y$  is given as: 
$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2 + R_2} = \frac{(100 \Omega)^2}{3 \cdot 100 \Omega} = \frac{1}{3} \cdot 100 \Omega = 33.33 \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series: 
$$R_{eq} = R_Y + (R_Y + R_1 + R_1) \parallel (R_Y + R_2) \parallel R_{eq} = 33.33 \Omega + (33.33 \Omega + 400 \Omega) \parallel (33.33 \Omega + 100 \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance  $R_{eq}$  between A and B.

Solution




The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = (R_2 + R_1 + R_1) \parallel (R_2 + R_2) \parallel R_{\text{eq}} = (100 \Omega + 200 \Omega + 200 \Omega) \parallel (100 \Omega + 100 \Omega) \parallel R_{\text{eq}} = (500 \Omega) \parallel (200 \Omega) \parallel R_{\text{eq}} = \frac{500 \Omega \cdot 200 \Omega}{500 \Omega + 200 \Omega} \parallel$$

**Exercise E2 Equivalent linear Source  
(written test, approx. 14 % of a 60-minute written test, WS2022)**

The circuit in the following has to be simplified.  
Result


$$U_{\text{s}} = U_{\text{AB}} = 4.5 \text{ V} \quad R_{\text{i}} = R_{\text{AB}} = 6 \Omega$$




Calculate the internal resistance  $R_i$  and the source voltage  $U_s$  of an equivalent linear voltage source on the connectors  $A$  and  $B$ .  $R_1=5.0 \Omega$ ,  $U_2=6.0 \text{ V}$ ,  $R_3=10 \Omega$ ,  $I_4=4.2 \text{ A}$ ,  $R_5=10 \Omega$ ,  $R_6=7.5 \Omega$ ,  $R_7=15 \Omega$ . Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of  $U_2$  and  $R_1$  can be transformed into a current source  $I_2 = \frac{U_2}{R_1}$  and  $R_1$ :



Now a lot of them can be combined. The resistors  $R_1$ ,  $R_3$ ,  $R_5$  are in parallel, like also  $I_2$  and  $I_4$ :

$$R_{135} = R_1 || R_3 || R_5$$

$$I_{24} = I_2 - I_4 = \frac{U_{24}}{R_1} - I_4$$

The resulting circuit can again be transformed:



Here, the  $U_{24}$  is calculated by  $I_{24}$  as the following:

$$U_{24}$$

$$I = R_{135} \cdot I_{24} \quad I = \left( \frac{U_2}{R_1} - I_4 \right) \cdot R_1 \parallel R_3 \parallel R_5$$

On the right side of the last circuit, there is a voltage divider given by  $R_{135}$ ,  $R_6$ , and  $R_7$ .

Therefore the voltage between  $A$  and  $B$  is given as:

$$U_{AB} = U_{24} \cdot \left\{ \frac{R_7}{R_6 + R_7 + R_1 \parallel R_3 \parallel R_5} \right\} = \left( \frac{U_2}{R_1} - I_4 \right) \cdot \left\{ \frac{R_7 \cdot R_1 \parallel R_3 \parallel R_5}{R_6 + R_7 + R_1 \parallel R_3 \parallel R_5} \right\}$$

For the internal resistance  $R_i$  the ideal voltage source is substituted by its resistance ( $=0\Omega$ , so a short-circuit):

$$R_{AB} = R_7 \parallel (R_6 + R_1 \parallel R_3 \parallel R_5)$$

with  $R_1 \parallel R_3 \parallel R_5 = 5\Omega \parallel 10\Omega \parallel 10\Omega = 5\Omega \parallel 5\Omega = 2.5\Omega$ :

$$U_{AB} = \left( \frac{6.0\text{V}}{5.0\Omega} - 4.2\Omega \right) \cdot \left\{ \frac{15\Omega \cdot 2.5\Omega}{7.5\Omega + 15\Omega + 2.5\Omega} \right\} \quad R_{AB} = 15\Omega \parallel (7.5\Omega + 2.5\Omega)$$

### Full Exam

These is the full exam

Full exam

### Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)

The heating element made of nichrome wire with a cross-section of  $1.80\text{mm}^2$ . Each second, a power dissipation (= heat flow) of  $P=40\text{W}$  is necessary. Determine the current  $I$  needed to operate for heating elements. The Nichrome wire has a resistivity of  $1.10 \cdot 10^{-6}\Omega\text{m}$ . The heating element is  $3\text{m}$  long and has a diameter of  $3.57\text{mm}$ . Calculate the resistance  $R$  of the heating element.

Solution

$$P = U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \sqrt{\frac{P}{R}} = \sqrt{\frac{40\text{W}}{0.33\Omega}}$$

$$R = \rho \cdot \frac{l}{A} \quad | \quad \text{with } A = r^2 \cdot \pi = \frac{1}{4} d^2 \cdot \pi \quad R = \rho \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad R = 1.10 \cdot 10^{-6}\Omega\text{m} \cdot \frac{4 \cdot 3\text{m}}{d^2 \cdot \pi}$$

$$3 \cdot 10^{-3} \cdot \pi \cdot R^2$$

[electrical\\_engineering\\_and\\_electronics:task\\_rj0r6j4apumukrj6\\_with\\_calculation](#)  
[resistivity, power, exam ee1 ws2022](#)

**Exercise E3 Temperature-dependent Resistance**  
**(written test, approx. 6 % of a 60-minute written test, WS2022)**

A refrigerator is explained with the effect of temperature on the resistance of a resistor. The resistance of a resistor is given by  $R = R_0 (1 + \alpha \Delta T + \beta \Delta T^2)$  for  $\Delta T$  in  $^{\circ}\text{C}$ . Its temperature coefficients are:  $\alpha = 0.01 \text{ K}^{-1}$  and  $\beta = 71 \cdot 10^{-6} \text{ K}^{-2}$ .

The temperature inside the refrigeration system can reach down to  $-40^{\circ}\text{C}$ .

Result  
 Calculate the resistance of the thermistor at  $-40^{\circ}\text{C}$ .

The power transferred to the resistor  $P = U \cdot I$  and the heat  $Q = P \cdot t$  is solution for resistive flow might heat up the refrigeration system. Therefore, with constant  $U$  and increasing  $R$  the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 (1 + \alpha \Delta T + \beta \Delta T^2) \quad | \text{with } \Delta T = T_{\text{end}} - T_{\text{start}}$$


$$R = 10 \cdot 10^3 \cdot (1 + 0.01 \cdot (-40 - 25) + 71 \cdot 10^{-6} \cdot (-40 - 25)^2)$$

[electrical\\_engineering\\_and\\_electronics:task\\_70jg4yzznocarsq\\_with\\_calculation](#)  
[temperature dependent resistance, power, heat, exam ee1 ws2022](#)

**Exercise E1 Pure Resistor Network Simplification**  
**(written test, approx. 13 % of a 60-minute written test, WS2022)**

The following shall hold:  $R_1 = 20 \text{ } \Omega$ ,  $R_2 = 10 \text{ } \Omega$ ,  $R_3 = 10 \text{ } \Omega$ ,  $R_4 = 10 \text{ } \Omega$ ,  $R_5 = 10 \text{ } \Omega$ ,  $R_6 = 10 \text{ } \Omega$ ,  $R_7 = 10 \text{ } \Omega$ ,  $R_8 = 10 \text{ } \Omega$ ,  $R_9 = 10 \text{ } \Omega$ ,  $R_{10} = 10 \text{ } \Omega$ ,  $R_{11} = 10 \text{ } \Omega$ ,  $R_{12} = 10 \text{ } \Omega$ ,  $R_{13} = 10 \text{ } \Omega$ ,  $R_{14} = 10 \text{ } \Omega$ ,  $R_{15} = 10 \text{ } \Omega$ ,  $R_{16} = 10 \text{ } \Omega$ ,  $R_{17} = 10 \text{ } \Omega$ ,  $R_{18} = 10 \text{ } \Omega$ ,  $R_{19} = 10 \text{ } \Omega$ ,  $R_{20} = 10 \text{ } \Omega$ .

Solution  
 $R_{\text{eq}} = 132.8 \text{ } \Omega$   
 Now a wye-delta transformation is necessary.




Since  $R_2=R_3$  and based on the equations for the transformation, the transformed  $R_Y$  is given as: 
$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2 + R_2} = \frac{(100 \Omega)^2}{3 \cdot 100 \Omega} = \frac{1}{3} \cdot 100 \Omega = 33.33 \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series: 
$$R_{eq} = R_Y + (R_Y + R_1 + R_1) \parallel (R_Y + R_2) \parallel R_{eq} = 33.33 \Omega + (33.33 \Omega + 400 \Omega) \parallel (33.33 \Omega + 100 \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance  $R_{eq}$  between  $A$  and  $B$ .

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:


$$R_{\text{eq}} = (R_2 + R_1) \parallel (R_2 + R_2) \parallel R_{\text{eq}} = (100 \Omega + 200 \Omega + 200 \Omega) \parallel (100 \Omega + 100 \Omega) \parallel R_{\text{eq}} = (500 \Omega) \parallel (200 \Omega) \parallel R_{\text{eq}} = \frac{500 \Omega \cdot 200 \Omega}{500 \Omega + 200 \Omega}$$

[electrical\\_engineering\\_and\\_electronics:task\\_x357drkaqv84jnsc\\_with\\_calculation\\_network\\_simplification,\\_exam\\_ee1\\_ws2022](#)

**Exercise E2 Equivalent linear Source  
(written test, approx. 14 % of a 60-minute written test, WS2022)**

The circuit in the following has to be simplified.  
Result

$$U_{\text{S}} = U_{\text{AB}} = 4.5 \text{ V} \parallel R_{\text{i}} = R_{\text{AB}} = 6 \Omega$$




Calculate the internal resistance  $R_i$  and the source voltage  $U_s$  of an equivalent linear voltage source on the connectors A and B.

$R_1=5.0 \Omega$ ,  $U_2=6.0 \text{ V}$ ,  $R_3= 10 \Omega$ ,  $I_4=4.2 \text{ A}$ ,  
 $R_5=10 \Omega$ ,  $R_6=7.5 \Omega$ ,  $R_7=15 \Omega$


Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:




The linear voltage source of  $U_2$  and  $R_1$  can be transformed into a current source  $I_2 = \frac{U_2}{R_1}$  and  $R_1$ :



Now a lot of them can be combined. The resistors  $R_1, R_3, R_5$  are in

parallel, like also  $I_2$  and  $I_4$ : 
$$R_{135} = R_1 || R_3 || R_5$$
 
$$I_{24} = I_2 - I_4 = \left\{ \frac{U_2}{R_1} \right\} - I_4$$
 The resulting circuit can again be transformed:



Here, the  $U_{24}$  is calculated by  $I_{24}$  as the following: 
$$U_{24} = R_{135} \cdot I_{24} = \left( \frac{U_2}{R_1} - I_4 \right) \cdot R_1 || R_3 || R_5$$

On the right side of the last circuit, there is a voltage divider given by  $R_{135}$ ,  $R_6$ , and  $R_7$ . Therefore the voltage between  $A$  and  $B$  is given as: 
$$U_{\text{AB}} = U_{24} \cdot \left\{ \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right\} = \left( \frac{U_2}{R_1} - I_4 \right) \cdot \left\{ \frac{R_7 \cdot R_1 || R_3 || R_5}{R_6 + R_7 + R_1 || R_3 || R_5} \right\}$$

For the internal resistance  $R_i$  the ideal voltage source is substituted by its resistance ( $=0\Omega$ , so a short-circuit): 
$$R_{\text{AB}} = R_7 || (R_6 + R_1 || R_3 || R_5)$$

with  $R_1 || R_3 || R_5 = 5 \Omega || 10 \Omega || 10 \Omega = 5 \Omega || 5 \Omega = 2.5 \Omega$ :

$$U_{\text{AB}} = \left\{ \frac{6.0 \text{ V}}{5.0 \Omega} - 4.2 \Omega \right\} \cdot \left\{ \frac{15 \Omega \cdot 2.5 \Omega}{7.5 \Omega + 15 \Omega + 2.5 \Omega} \right\} || R_{\text{AB}} = 15 \Omega || (7.5 \Omega + 2.5 \Omega)$$


[electrical\\_engineering\\_and\\_electronics:task\\_6tqtqtue1e2nf2c7\\_with\\_calculation](#)  
 dc network analysis, pure resistor network simplification, delta wye transformation, exam ee1 ws2022

### Exercise E1 Charging Capacitors (written test, approx. 16 % of a 60-minute written test, WS2022)

The capacitor becomes fully charged (voltage across the capacitor is  $U$ ) again. The voltage across the capacitor is again  $0$  V at the moment  $t_0=0$  s when the switch  $S_1$  is closed. Calculate the voltage  $u_c(t_2)$  across the capacitor at  $t_2=1$  ms after closing the switch.

Hint! To solve this, first create an equivalent linear voltage source from  $U$ ,  $R_1$ , and  $R_B$ .


The internal voltage of the equivalent source is  $U_{eq} = U \cdot \frac{R_B}{R_1 + R_B}$  and the internal resistance is  $R_{eq} = R_1 \parallel R_B = \frac{R_1 \cdot R_B}{R_1 + R_B}$ .  
 On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting  $R_2$ .



The circuit contains a voltage source  $U=12$  V, a switch  $S_1$ , a resistor of  $R_1=20$   $\Omega$  and a capacitor of  $C=100$   $\mu$ F. The switch  $S_2$  to an additional consumer  $R_2$  will be considered to be open for the first tasks. At the moment  $t_0=0$  s the switch  $S_1$  is closed, the voltage across the capacitor is  $u_c(t_0)=0$  V.

... First do not consider the light bulb - it is not connected to the RC circuit. Calculate the point of time  $t_1$  when  $u_c(t_1)=0.5 \cdot U$ .

Solution



An equivalent linear voltage source can be given with  $U$ ,  $R_1$ , and  $R_B$  as seen in yellow.

Therefore, the voltage of the equivalent instant source is  $U_{eq} = U \cdot \frac{R_B}{R_1 + R_B} = 1/2 \cdot U$ . The internal resistance is given by  $R_{eq} = R_1 \parallel R_B = 10$   $\Omega$ . The following formula describes the time course of  $u_c(t)$  which has to be  $u_c(t) = U_{eq} \cdot (1 - e^{-t/\tau})$  with  $\tau = R_{eq} \cdot C = 100$   $\mu$ s. It has to be rearranged to  $(1 - e^{-t/\tau}) = 0.5$   $\Rightarrow e^{-t/\tau} = 0.5$   $\Rightarrow -t/\tau = \ln(0.5)$   $\Rightarrow t = \tau \cdot \ln(2) = 100 \mu$ s  $\cdot \ln(2) \approx 69.3$   $\mu$ s.



**(written test, approx. 18 % of a 60-minute written test, WS2022)**

2. A series circuit contains a resistor with  $R = 100 \Omega$  and a capacitor with  $C = 40 \text{ nF}$ . The voltage source is  $v(t) = 3.0 \sin(2\pi \cdot 15 \text{ kHz} \cdot t)$  V. The current through the resistor is  $i(t) = I_m \sin(2\pi \cdot 15 \text{ kHz} \cdot t + \phi)$  A. Determine the magnitude of the current  $I_m$  and the phase angle  $\phi$ .

Solution

$$R = 100 \Omega$$

$$C = 40 \text{ nF}$$

A series circuit means that the current is constant on every component. The equivalent impedance for  $R$  and  $C$  combined is given by

$$Z = R - jX_C = 100 - j \frac{1}{2\pi \cdot 15 \cdot 10^3 \cdot 40 \cdot 10^{-9}} = 100 - j26.5 \Omega$$

Back to the first formula:

$$I_m = \frac{U_m}{|Z|} = \frac{3.0}{\sqrt{100^2 + 26.5^2}} = 0.0273 \text{ A} = 27.3 \text{ mA}$$

$$\phi = \arctan\left(\frac{-X_C}{R}\right) = \arctan\left(\frac{-26.5}{100}\right) = -14.5^\circ$$

Therefore, the resulting current of the parallel circuit is given as:

$$i(t) = 27.3 \text{ mA} \cdot \sin(2\pi \cdot 15 \text{ kHz} \cdot t - 14.5^\circ)$$

[electrical\\_engineering\\_and\\_electronics:task\\_pdkgtyexxy1ktu3\\_with\\_calculation](#)  
[complex impedance, exam ee1 ws2022](#)

**Exercise E1 Complex Impedance Circuit**

**(written test, approx. 15 % of a 60-minute written test, WS2022)**

1. Consider the circuit below. The voltage source is  $v(t) = 3.0 \sin(2\pi \cdot 15 \text{ kHz} \cdot t)$  V. The current through the resistor is  $i(t) = I_m \sin(2\pi \cdot 15 \text{ kHz} \cdot t + \phi)$  A. Determine the magnitude of the current  $I_m$  and the phase angle  $\phi$ .

Solution

Result

$$I_m = 19.8 \text{ mA}$$

$$\phi = 48.2^\circ$$

Draw the circuit diagram of the given circuit. Label all components, voltages, and currents.

$$Z = \frac{U}{I} = \frac{3.0 \text{ V}}{0.0198 \text{ A}} = 151.5 \Omega$$

$$\phi = \arctan\left(\frac{X_C}{R}\right) = \arctan\left(\frac{1}{2\pi \cdot 15 \cdot 10^3 \cdot 0.22 \cdot 10^{-6}}}\right) = 48.2^\circ$$


Result

$$I_m = \frac{U_m}{|Z|} = \frac{3.0}{151.5} = 0.0198 \text{ A} = 19.8 \text{ mA}$$

$$\phi = \arctan\left(\frac{X_C}{R}\right) = \arctan\left(\frac{1}{2\pi \cdot 15 \cdot 10^3 \cdot 0.22 \cdot 10^{-6}}}\right) = 48.2^\circ$$







electrical\_engineering\_and\_electronics:task\_kricv9fh7haauo6q\_with\_calculation  
complex impedance, exam ee1 ws2022

From:

<https://wiki.mexle.org/> - **MEXLE Wiki**

Permanent link:

[https://wiki.mexle.org/electrical\\_engineering\\_and\\_electronics\\_1/ws2022\\_exam](https://wiki.mexle.org/electrical_engineering_and_electronics_1/ws2022_exam)

Last update: **2026/01/12 00:24**

