

dummy

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E1 Machine-Vision Strobe: Capacitor Charging and Safe Discharge	2
Exercise E2 Industrial Sensor Interface: Buffered Measurement Node	2
Exercise E3 Hall-Sensor Test Bench: Air-Core Calibration Coil	3

Exercise E1 Machine-Vision Strobe: Capacitor Charging and Safe Discharge

A. The capacitor charging circuit is shown in Figure 1. The capacitor is charged by a pulse generator. The pulse generator is a square wave with a period of 100 μs and a duty cycle of 10%. The capacitor is charged to a voltage of 447.2 V. After the pulse, the capacitor is discharged through a resistor. The discharge time constant is 4.47 ms. The capacitor must be safely discharged before maintenance.

Solution

```

\begin{align*} C &= 1 \mu\text{F} \quad W = 0.1 \text{ J} \quad I_{\text{max}} = 100 \text{ A} \\
\begin{align*} U_0 &= \sqrt{\frac{2W}{C}} = \sqrt{\frac{2 \cdot 0.1 \text{ J}}{1 \cdot 10^{-6} \text{ F}}} = 447.2 \text{ V} \\
\end{align*} \\
\begin{align*} \tau &= RC = 4.47 \text{ ms} \\
\end{align*} \\
\begin{align*} u_C(t) &= U_0 e^{-t/\tau} \\
\end{align*} \\
\begin{align*} \tau &= RC = 4.47 \text{ ms} \\
\end{align*} \\
\begin{align*} W(t) &= \frac{1}{2} C u_C^2(t) \\
\end{align*} \\
\begin{align*} W(0) &= \frac{1}{2} C U_0^2 = 0.1 \text{ J} \\
\end{align*} \\
\begin{align*} W(\tau) &= \frac{1}{2} C U_0^2 e^{-2} \approx 0.135 \text{ J} \\
\end{align*} \\
\begin{align*} W(2\tau) &= \frac{1}{2} C U_0^2 e^{-4} \approx 0.018 \text{ J} \\
\end{align*} \\
\begin{align*} W(3\tau) &= \frac{1}{2} C U_0^2 e^{-6} \approx 0.0025 \text{ J} \\
\end{align*} \\
\begin{align*} W(4\tau) &= \frac{1}{2} C U_0^2 e^{-8} \approx 0.0003 \text{ J} \\
\end{align*} \\
\begin{align*} W(5\tau) &= \frac{1}{2} C U_0^2 e^{-10} \approx 4 \cdot 10^{-5} \text{ J} \\
\end{align*} \\
\begin{align*} W(6\tau) &= \frac{1}{2} C U_0^2 e^{-12} \approx 5 \cdot 10^{-6} \text{ J} \\
\end{align*} \\
\begin{align*} W(7\tau) &= \frac{1}{2} C U_0^2 e^{-14} \approx 7 \cdot 10^{-7} \text{ J} \\
\end{align*} \\
\begin{align*} W(8\tau) &= \frac{1}{2} C U_0^2 e^{-16} \approx 1 \cdot 10^{-7} \text{ J} \\
\end{align*} \\
\begin{align*} W(9\tau) &= \frac{1}{2} C U_0^2 e^{-18} \approx 1.5 \cdot 10^{-8} \text{ J} \\
\end{align*} \\
\begin{align*} W(10\tau) &= \frac{1}{2} C U_0^2 e^{-20} \approx 2 \cdot 10^{-9} \text{ J} \\
\end{align*} \\
\end{pre}

```

Exercise E2 Industrial Sensor Interface: Buffered Measurement Node

A. Draw the circuit diagram for a buffered measurement node. The load resistor is 100 Ω and the capacitor is 10 μF. The input voltage is 5 V. The output voltage is 2.5 V.

Result: The capacitor is used to smooth the signal and to provide a stable voltage for a short measurement cycle. At first, the measurement electronics are disconnected. Once the capacitor is fully charged, a switch closes and the measurement load is connected.

Solution

$$U_{out} = U_{in} \frac{R_{load}}{R_{load} + R_{buffer}} = 5 \text{ V} \cdot \frac{100 \Omega}{100 \Omega + 100 \Omega} = 2.5 \text{ V}$$

```

\begin{align*} U &= 12 \sim \{\rm V\} \quad R_1 = 2 \sim \{\rm k\Omega\} \quad R_2 = 10 \sim \{\rm k\Omega\} \\ R_3 &= 10 \sim \{\rm k\Omega\} \quad C = 1 \sim \{\rm \mu F\} \end{align*}
\begin{align*} R_{\text{eq}} &= R_1 + R_2 + R_3 = 20 \sim \{\rm k\Omega\} \\ \tau &= R_{\text{eq}} C = 20 \sim \{\rm k\Omega\} \cdot 1 \sim \{\rm \mu F\} = 20 \sim \{\rm ms\} \end{align*}
\begin{align*} u_C(t) &= U \left( 1 - e^{-t/\tau} \right) = 12 \left( 1 - e^{-t/20} \right) \end{align*}
\end{pre>

```

Exercise E3 Hall-Sensor Test Bench: Air-Core Calibration Coil

Result A 100 mA current is fed. Current density is high because it avoids hysteresis and remanence effects of iron cores. The coil is wound as a short, single-layer cylindrical coil.

Solution

```

\begin{align*} I &= 22 \sim \{\rm mm\} \quad d = 20 \sim \{\rm mm\} \quad d_{\text{Cu}} = 0.8 \sim \{\rm mm\} \\ \rho_{\text{Cu}} &= 1.72 \sim \{\rm \mu\Omega\cdot\text{cm}\} \end{align*}
\begin{align*} R &= \frac{4 \rho_{\text{Cu}} l}{\pi d^2} = \frac{4 \cdot 1.72 \cdot 10^{-8} \cdot 0.022}{\pi \cdot (0.0008)^2} \approx 3.7 \sim \{\rm \Omega\} \\ \tau &= \frac{L}{R} = \frac{0.0001}{3.7} \approx 2.7 \sim \{\rm \mu s\} \end{align*}
\begin{align*} i(t) &= I \left( 1 - e^{-t/\tau} \right) \end{align*}
\end{pre>

```

First, determine the copper cross-sectional area:

$$\begin{aligned} A_{\text{Cu}} &= \frac{\pi}{4} d_{\text{Cu}}^2 = \frac{\pi}{4} (0.8 \text{ mm})^2 \\ &= 0.503 \text{ mm}^2 \end{aligned}$$

The mean length of one turn is approximately the circumference:

$$l_{\text{turn}} \approx \pi d = \pi \cdot 20 \text{ mm} = 62.83 \text{ mm}$$

Thus, the total wire length is

$$\begin{aligned} l_{\text{Cu}} &= N \cdot l_{\text{turn}} = 25 \cdot 62.83 \text{ mm} \\ &= 1570.8 \text{ mm} = 1.571 \text{ m} \end{aligned}$$

Now calculate the resistance:

$$\begin{aligned} R &= \rho_{\text{Cu}} \frac{l_{\text{Cu}}}{A_{\text{Cu}}} \\ &= 0.0178 \text{ } \Omega \cdot \text{m} \cdot \frac{1.571 \text{ m}}{0.503 \text{ mm}^2} \approx 0.0556 \text{ } \Omega \end{aligned}$$

From:

<https://wiki.mexle.org/> - **MEXLE Wiki**

Permanent link:

<https://wiki.mexle.org/dummy?rev=1774572386>

Last update: **2026/03/27 01:46**

