

# dummy

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

<b>Exercises</b> .....	2
Exercise E1 Quick check: ideal transformer voltage and current ratio .....	2
Exercise E2 Quick check: mutual inductance from reluctance .....	4
Exercise E3 Mutual inductance and leakage from a magnetic path .....	6
Exercise E4 Quick check: referring secondary quantities to the primary side .....	9
Exercise E5 Quick check: short-circuit voltage and fault current .....	10
Exercise E6 Longer exercise: transformer equivalent circuit for an actuator supply .....	11
Exercise E7 Short-circuit voltage from the transformer impedance .....	14
Exercise E8 Voltage drop under load using the Kapp approximation .....	17
Exercise E9 Why the magnetizing branch can be neglected in the short-circuit test .....	19
Exercise E10 Why the short-circuit equivalent circuit is often sufficient under load .....	22
Exercise E11 Ideal transformer versus real transformer .....	25

## Exercises

### Exercise E1 Quick check: ideal transformer voltage and current ratio

A transformer has  $N_1=1200$  turns and  $N_2=300$  turns. The primary RMS voltage is  $U_1=230\text{ V}$ . The secondary side supplies a load current  $I_2=2.0\text{ A}$ .

1. Calculate the turns ratio  $n$ .

#### SolutionResult

The turns ratio of an ideal transformer is defined as:

$$n = \frac{N_1}{N_2}$$

Insert the given values:

$$n = \frac{1200}{300} = 4$$

$$n = 4$$

2. Calculate the ideal secondary voltage  $U_2$ .

#### SolutionResult

For an ideal transformer, the voltage ratio follows the turns ratio:

$$n = \frac{U_1}{U_2}$$

Therefore:

$$U_2 = \frac{U_1}{n} = \frac{230\text{ V}}{4} = 57.5\text{ V}$$

$$U_2 = 57.5\text{ V}$$

3. Calculate the magnitude of the ideal primary current  $I_1$ .

#### SolutionResult

For the ideal transformer, the current ratio is inverse to the voltage ratio:

$$I_1 = \frac{I_2}{n}$$

Insert the values:  $I_1 = \frac{2.0 \text{ A}}{4} = 0.50 \text{ A}$

$$I_1 = 0.50 \text{ A}$$

4. State whether this is a step-up or step-down transformer.

#### SolutionResult

Compare the primary and secondary voltages:  $U_1 = 230 \text{ V}$   $U_2 = 57.5 \text{ V}$

Since  $U_2 < U_1$

the transformer reduces the voltage.

The transformer is a step-down transformer.

## Exercise E2 Quick check: mutual inductance from reluctance

Two coils are wound on the same ideal magnetic core. The main magnetic reluctance is

$$R_{\text{mH}} = 2.0 \cdot 10^6 \frac{1}{\text{H}}$$

The number of turns is  $N_1 = 500$  and  $N_2 = 100$ .

1. Calculate  $L_{1\text{H}}$ .

### SolutionResult

The main-flux inductance of coil 1 is:

$$L_{1\text{H}} = \frac{N_1^2}{R_{\text{mH}}}$$

Insert the values:

$$L_{1\text{H}} = \frac{500^2}{2.0 \cdot 10^6 \frac{1}{\text{H}}} = 0.125 \text{ H}$$

$$L_{1\text{H}} = 0.125 \text{ H}$$

2. Calculate  $L_{2\text{H}}$ .

### SolutionResult

The main-flux inductance of coil 2 is:

$$L_{2\text{H}} = \frac{N_2^2}{R_{\text{mH}}}$$

Insert the values:

$$L_{2\text{H}} = \frac{100^2}{2.0 \cdot 10^6 \frac{1}{\text{H}}} = 0.0050 \text{ H} = 5.0 \text{ mH}$$

$$L_{2\text{H}} = 0.0050 \text{ H} = 5.0 \text{ mH}$$

3. Calculate  $M$ .

### SolutionResult

The mutual inductance is:

$$M = \frac{N_1 N_2}{R_{\text{mH}}}$$

Insert the values:

$$M = \frac{500 \cdot 100}{2.0 \cdot 10^6 \cdot 1/\text{H}} = 0.025 \text{ H} = 25 \text{ mH}$$

$$M = 0.025 \text{ H} = 25 \text{ mH}$$

4. Check whether the units are correct.

### SolutionResult

The reluctance is given in:

$$R_{\text{mH}} = \frac{1}{\text{H}}$$

The number of turns is dimensionless.

$$\left[ \frac{N^2}{R_{\text{mH}}} \right] = \frac{1}{1/\text{H}} = \text{H}$$

The same argument applies to the mutual inductance:

$$\left[ \frac{N_1 N_2}{R_{\text{mH}}} \right] = \text{H}$$

The unit is correct because

$$\frac{1}{1/\text{H}} = \text{H}$$

### Exercise E3 Mutual inductance and leakage from a magnetic path

Two coils are wound on the same magnetic core. The shared main magnetic path has the reluctance

$$\begin{aligned} R_{\text{mH}} = 1.6 \cdot 10^6 \sim \frac{1}{\text{H}}. \end{aligned}$$

The numbers of turns are

$$\begin{aligned} N_1 = 400, \quad N_2 = 100. \end{aligned}$$

The leakage inductances are

$$\begin{aligned} L_{1\sigma} = 4.0 \sim \text{mH}, \quad L_{2\sigma} = 0.30 \sim \text{mH}. \end{aligned}$$

Calculate:

- $L_{1\text{H}}$
- $L_{2\text{H}}$
- $M$
- the total self-inductances  $L_1$  and  $L_2$
- the coupling coefficient  $k = \frac{M}{\sqrt{L_1 L_2}}$

1. Calculate  $L_{1\text{H}}$ .

#### SolutionResult

The main-flux self-inductance of coil 1 is: 
$$\begin{aligned} L_{1\text{H}} = \frac{N_1^2}{R_{\text{mH}}} \end{aligned}$$

Insert the values: 
$$\begin{aligned} L_{1\text{H}} &= \frac{400^2}{1.6 \cdot 10^6 \sim 1/\text{H}} \\ &= 0.100 \sim \text{H} \end{aligned}$$

$$\begin{aligned} L_{1\text{H}} = 0.100 \sim \text{H} = 100 \sim \text{mH} \end{aligned}$$

2. Calculate  $L_{2\text{H}}$ .

## SolutionResult

The main-flux self-inductance of coil 2 is: 
$$\begin{aligned} L_{2\text{ (H)}} &= \frac{N_2^2}{R_{\text{mH}}} \\ \end{aligned}$$

Insert the values: 
$$\begin{aligned} L_{2\text{ (H)}} &= \frac{100^2}{1.6 \cdot 10^6} \\ &= 0.00625\text{ (H)} \\ &= 6.25\text{ (mH)} \end{aligned}$$

$$\begin{aligned} L_{2\text{ (H)}} &= 0.00625\text{ (H)} = 6.25\text{ (mH)} \\ \end{aligned}$$

3. Calculate \$M\$.

## SolutionResult

The mutual inductance is: 
$$\begin{aligned} M &= \frac{N_1 N_2}{R_{\text{mH}}} \\ \end{aligned}$$

Insert the values: 
$$\begin{aligned} M &= \frac{400 \cdot 100}{1.6 \cdot 10^6} \\ &= 0.025\text{ (H)} \\ &= 25\text{ (mH)} \end{aligned}$$

$$\begin{aligned} M &= 0.025\text{ (H)} = 25\text{ (mH)} \\ \end{aligned}$$

4. Calculate the total self-inductances \$L\_1\$ and \$L\_2\$.

## SolutionResult

$$\begin{aligned} L_1 &= 104\text{ (H)} \end{aligned}$$

The total self-inductance is the sum of main-flux inductance and leakage inductance.

For coil 1: 
$$L_1 = L_{1\text{H}} + L_{1\text{sigma}} = 100\text{ mH} + 4.0\text{ mH} = 104\text{ mH}$$

For coil 2: 
$$L_2 = L_{2\text{H}} + L_{2\text{sigma}} = 6.25\text{ mH} + 0.30\text{ mH} = 6.55\text{ mH}$$

$$L_2 = 6.55\text{ mH}$$

5. Calculate the coupling coefficient  $k = \frac{M}{\sqrt{L_1 L_2}}$ .

### SolutionResult

The coupling coefficient is:

$$k = \frac{M}{\sqrt{L_1 L_2}}$$

Insert the values in henry:

$$k = \frac{0.025\text{ H}}{\sqrt{0.104\text{ H} \cdot 0.00655\text{ H}}} \approx 0.96$$

The coupling is strong, but not ideal, because leakage inductances are present.

$$k \approx 0.96$$

The coupling is strong, but not ideal.

### Exercise E4 Quick check: referring secondary quantities to the primary side

A transformer has  $n=5$ . The secondary winding resistance is  $R_2=0.20\ \Omega$  and the secondary leakage reactance is  $X_{2\sigma}=0.35\ \Omega$ .

Calculate the values  $R'_2$  and  $X'_{2\sigma}$  referred to the primary side.

1. Calculate  $R'_2$ .

#### SolutionResult

When a resistance is referred from the secondary side to the primary side, it is multiplied by  $n^2$ :

$$\begin{aligned} R'_2 &= n^2 R_2 \end{aligned}$$

Insert the values:  $\begin{aligned} R'_2 &= 5^2 \cdot 0.20\ \Omega \\ &= 25 \cdot 0.20\ \Omega \\ &= 5.0\ \Omega \end{aligned}$

$$\begin{aligned} R'_2 &= 5.0\ \Omega \end{aligned}$$

2. Calculate  $X'_{2\sigma}$ .

#### SolutionResult

The secondary leakage reactance is also referred to the primary side by multiplying with  $n^2$ :

$$\begin{aligned} X'_{2\sigma} &= n^2 X_{2\sigma} \end{aligned}$$

Insert the values:  $\begin{aligned} X'_{2\sigma} &= 5^2 \cdot 0.35\ \Omega \\ &= 25 \cdot 0.35\ \Omega \\ &= 8.75\ \Omega \end{aligned}$

$$\begin{aligned} X'_{2\sigma} &= 8.75\ \Omega \end{aligned}$$

3. Check the unit.

### SolutionResult

The turns ratio  $n$  is dimensionless:  

$$[n] = 1$$

Therefore, multiplying by  $n^2$  does not change the unit:  

$$[R'_2] = \Omega \quad [X'_{2\sigma}] = \Omega$$

The unit remains  $\Omega$ , because  $n$  is dimensionless.

### Exercise E5 Quick check: short-circuit voltage and fault current

A transformer has a rated primary current  $I_{1\text{N}} = 10 \text{ A}$  and a short-circuit voltage  $u_{\text{k}} = 5\%$ .

1. Calculate the continuous short-circuit current  $I_{1\text{k}}$  when rated primary voltage is applied.

### SolutionResult

The short-circuit current can be estimated from the rated current and the relative short-circuit voltage:  

$$I_{1\text{k}} = I_{1\text{N}} \cdot \frac{100\%}{u_{\text{k}}}$$

Insert the values:  

$$I_{1\text{k}} = 10 \text{ A} \cdot \frac{100\%}{5\%} = 200 \text{ A}$$

$$I_{1\text{k}} = 200 \text{ A}$$

```

I_{1{\rm k}} \&= 10~{\rm A}\cdot
\frac{100~\%}{5~\%} \ \&=
200~{\rm A} \ \end{align*}

```

2. Estimate the initial peak short-circuit current  $i_{\rm p}$  using  $i_{\rm p} \approx 2.54 I_{1{\rm k}}$ .

### SolutionResult

The initial peak current is estimated by: 
$$i_{\rm p} \approx 2.54 \cdot I_{1{\rm k}}$$

Insert the continuous short-circuit current: 
$$i_{\rm p} \approx 2.54 \cdot 200~{\rm A} \ \&= 508~{\rm A}$$

The short-circuit current is much larger than the rated current. Protection devices must be selected accordingly.

```

\begin{align*} i_{\rm p} \approx
508~{\rm A} \ \end{align*}

```

Protection devices must be selected accordingly.

### Exercise E6 Longer exercise: transformer equivalent circuit for an actuator supply

A single-phase transformer supplies an actuator driver. Rated data and equivalent circuit data are:

```

\begin{align*} U_{1{\rm N}} \&= 230~{\rm V}, \ \& U_{2{\rm N}} \&= 23~{\rm V}, \ \& I_{2{\rm N}} \&= 5.0~{\rm A}, \ \& R_1 \&= 1.2~\Omega, \ \& X_{1\sigma} \&= 1.8~\Omega, \ \& R_2 \&= 0.012~\Omega, \ \& X_{2\sigma} \&= 0.018~\Omega. \ \end{align*}

```

Assume  $n = \frac{U_{1{\rm N}}}{U_{2{\rm N}}}$ . The magnetizing branch is neglected for the loaded operating point.

1. Calculate  $n$ .

### SolutionResult

The turns ratio is estimated from the rated voltages: 
$$n = \frac{U_{1(\text{rm N})}}{U_{2(\text{rm N})}}$$

Insert the values: 
$$n = \frac{230 \text{ V}}{23 \text{ V}} = 10$$

$$n = 10$$

2. Refer  $R_2$  and  $X_{2\sigma}$  to the primary side.

### SolutionResult

Secondary quantities are referred to the primary side by multiplying them with  $n^2$ : 
$$R'_2 = n^2 R_2 \quad X'_{2\sigma} = n^2 X_{2\sigma}$$

With  $n=10$ : 
$$R'_2 = 10^2 \cdot 0.012 \Omega = 1.2 \Omega$$
  

$$X'_{2\sigma} = 10^2 \cdot 0.018 \Omega = 1.8 \Omega$$

$$R'_2 = 1.2 \Omega$$
  

$$X'_{2\sigma} = 1.8 \Omega$$

3. Calculate  $R_{\text{k}}$  and  $X_{\text{k}}$ .

### SolutionResult

The short-circuit equivalent values are the sums of the primary quantities and the referred secondary quantities:

$$R_{\text{k}} = R_1 + R'_2 \quad X_{\text{k}} = X_{1\sigma} + X'_{2\sigma}$$

Insert the values:

$$R_{\text{k}} = 1.2\ \Omega + 1.2\ \Omega = 2.4\ \Omega$$

$$X_{\text{k}} = 1.8\ \Omega + 1.8\ \Omega = 3.6\ \Omega$$

$$R_{\text{k}} = 2.4\ \Omega$$

$$X_{\text{k}} = 3.6\ \Omega$$

4. Calculate the primary rated current magnitude  $I_{1\text{N}}$  using the ideal current ratio.

#### SolutionResult

For an ideal transformer, the primary current magnitude is:

$$I_{1\text{N}} = \frac{I_{2\text{N}}}{n}$$

Insert the values:

$$I_{1\text{N}} = \frac{5.0\ \text{A}}{10} = 0.50\ \text{A}$$

$$I_{1\text{N}} = 0.50\ \text{A}$$

5. Estimate the magnitude of the internal voltage drop  $U_{\text{k}} \approx \underline{Z}_{\text{k}} I_{1\text{N}}$ .

#### SolutionResult

First calculate the magnitude of the short-circuit impedance:

$$|Z_k| = \sqrt{R_k^2 + X_k^2}$$

Insert the values:

$$|Z_k| = \sqrt{(2.4\ \Omega)^2 + (3.6\ \Omega)^2} = 4.33\ \Omega$$

Now calculate the internal voltage drop:

$$U_k \approx |Z_k| I_{1N} = 4.33\ \Omega \cdot 0.50\ \text{A} = 2.17\ \text{V}$$

This is a primary-side voltage drop. On the secondary side:

$$\frac{2.17\ \text{V}}{10} = 0.217\ \text{V}$$

For a 23 V actuator supply this is small but not zero.

$$|Z_k| = 4.33\ \Omega \quad U_k \approx 2.17\ \text{V}$$

Secondary-side equivalent:

$$U_{k,2} \approx 0.217\ \text{V}$$

## Exercise E7 Short-circuit voltage from the transformer impedance

A transformer has the rated primary data

$$U_{1N} = 230\ \text{V}, \quad I_{1N} = 2.0\ \text{A}$$

The short-circuit equivalent impedance referred to the primary side is

$$R_k = 1.5\ \Omega, \quad X_k = 4.0\ \Omega$$

Calculate:

- $|Z_k|$
- the rated short-circuit voltage  $U_{k,2}$

- the relative short-circuit voltage  $u_{\text{k}}$
- the prospective continuous short-circuit current  $I_{\text{k}}$  for rated primary voltage
- the approximate first peak current  $i_{\text{peak}} \approx 2.54 I_{\text{k}}$

1. Calculate  $|\underline{Z}_{\text{k}}|$ .

#### SolutionResult

The short-circuit impedance magnitude is: 
$$|\underline{Z}_{\text{k}}| = \sqrt{R_{\text{k}}^2 + X_{\text{k}}^2}$$

Insert the values: 
$$|\underline{Z}_{\text{k}}| = \sqrt{(1.5 \text{ } \Omega)^2 + (4.0 \text{ } \Omega)^2} = 4.27 \text{ } \Omega$$

$$|\underline{Z}_{\text{k}}| = 4.27 \text{ } \Omega$$

2. Calculate the rated short-circuit voltage  $U_{\text{k}}$ .

#### SolutionResult

The primary voltage required to drive rated current through the short-circuited transformer is:

$$U_{\text{k}} = |\underline{Z}_{\text{k}}| I_{\text{N}}$$

Insert the values: 
$$U_{\text{k}} = 4.27 \text{ } \Omega \cdot 2.0 \text{ } \text{A} = 8.54 \text{ } \text{V}$$

$$U_{\text{k}} = 8.54 \text{ } \text{V}$$

3. Calculate the relative short-circuit voltage  $u_{\text{rk}}$ .

#### SolutionResult

The relative short-circuit voltage is:

$$u_{\text{rk}} = \frac{U_{\text{rk}}}{U_{\text{N}}} \cdot 100\%$$

Insert the values:

$$u_{\text{rk}} = \frac{8.54 \text{ V}}{230 \text{ V}} \cdot 100\% \\ = 3.71\%$$

$$u_{\text{rk}} = 3.71\%$$

4. Calculate the prospective continuous short-circuit current  $I_{\text{rk}}$  for rated primary voltage.

#### SolutionResult

The prospective continuous short-circuit current is:

$$I_{\text{rk}} = I_{\text{N}} \cdot \frac{100\%}{u_{\text{rk}}}$$

Insert the values:

$$I_{\text{rk}} = 2.0 \text{ A} \cdot \frac{100}{3.71} \\ = 53.9 \text{ A}$$

$$I_{\text{rk}} = 53.9 \text{ A}$$

5. Calculate the approximate first peak current  $i_{\text{peak}} \approx 2.54 I_{\text{rk}}$ .

## SolutionResult

The approximate first peak current is:

$$\begin{aligned} i_{\text{peak}} &\approx \\ 2.54 I_{1\text{k}} &\end{aligned}$$

Insert the short-circuit current:

$$\begin{aligned} i_{\text{peak}} &\approx \\ 2.54 \cdot 53.9 \text{ A} &= \\ 137 \text{ A} &\end{aligned}$$

Even though the rated current is only  $2.0 \text{ A}$ , a short-circuit fault could lead to a much larger current until protection reacts.

$$\begin{aligned} i_{\text{peak}} &\approx \\ 137 \text{ A} &\end{aligned}$$

### Exercise E8 Voltage drop under load using the Kapp approximation

A transformer has the turns ratio

$$\begin{aligned} n &= 10. \end{aligned}$$

The short-circuit equivalent parameters referred to the primary side are

$$\begin{aligned} R_{\text{k}} &= 2.4 \text{ } \Omega, \quad X_{\text{k}} = 3.6 \text{ } \Omega. \end{aligned}$$

The secondary load current is

$$\begin{aligned} I_2 &= 4.0 \text{ A}. \end{aligned}$$

The load has the power factor

$$\begin{aligned} \cos\varphi &= 0.8 \end{aligned}$$

and is inductive.

Estimate the voltage drop on the secondary side using

$$\begin{aligned} \Delta U_1 &\approx I_1 \left( R_{\text{k}} \cos\varphi + X_{\text{k}} \sin\varphi \right) \\ &\end{aligned}$$

and

$$\Delta U_2 \approx \frac{\Delta U_1}{n}$$

1. Calculate the primary current magnitude  $I_1$ .

#### SolutionResult

The primary current magnitude is approximately: 
$$I_1 = \frac{I_2}{n}$$

Insert the values: 
$$I_1 = \frac{4.0 \text{ A}}{10} \quad \&= \quad 0.40 \text{ A}$$

$$I_1 = 0.40 \text{ A}$$

2. Determine  $\sin\varphi$  for the inductive load.

#### SolutionResult

For an inductive load with  $\cos\varphi = 0.8$ : 
$$\sin\varphi = \sqrt{1 - \cos^2\varphi}$$

Insert the value: 
$$\sin\varphi = \sqrt{1 - 0.8^2} \quad \&= \quad 0.6$$

$$\sin\varphi = 0.6$$

3. Estimate the primary-side voltage drop  $\Delta U_1$ .

#### SolutionResult

Use the Kapp approximation:

$$\Delta U_1 \approx I_1 \left( R_k \cos \varphi + X_k \sin \varphi \right)$$

Insert the values:

$$\Delta U_1 \approx 0.40 \text{ A} \left( 2.4 \Omega \cdot 0.8 + 3.6 \Omega \cdot 0.6 \right) = 0.40 \text{ A} \left( 1.92 \Omega + 2.16 \Omega \right) = 1.63 \text{ V}$$

$$\Delta U_1 \approx 1.63 \text{ V}$$

4. Estimate the secondary-side voltage drop  $\Delta U_2$ .

#### SolutionResult

The secondary-side voltage drop is:

$$\Delta U_2 \approx \frac{\Delta U_1}{n}$$

Insert the values:

$$\Delta U_2 \approx \frac{1.63 \text{ V}}{10} = 0.163 \text{ V}$$

The secondary voltage decreases by approximately  $0.16 \text{ V}$  for this operating point.

$$\Delta U_2 \approx 0.163 \text{ V}$$

The secondary voltage decreases by approximately  $0.16 \text{ V}$ .

### Exercise E9 Why the magnetizing branch can be neglected in the short-circuit test

A transformer has the rated primary voltage

$$U_{1\{\text{N}\}} = 230 \text{ V}$$

Its rated primary current is

$$I_{1\{\text{N}\}} = 3.0 \text{ A}$$

At rated voltage and no-load operation, the magnetizing current is approximately

$$I_{\text{m,N}} = 0.12 \text{ A}$$

The short-circuit voltage is

$$u_{\text{k}} = 6.0 \%$$

Assume that the magnetizing current is approximately proportional to the applied voltage.

1. Calculate the short-circuit test voltage  $U_{1\{\text{k}\}}$ .

#### SolutionResult

The short-circuit test voltage is:

$$U_{1\{\text{k}\}} = \frac{u_{\text{k}}}{100\%} \cdot U_{1\{\text{N}\}}$$

Insert the values:

$$U_{1\{\text{k}\}} = 0.06 \cdot 230 \text{ V} = 13.8 \text{ V}$$

$$U_{1\{\text{k}\}} = 13.8 \text{ V}$$

2. Estimate the magnetizing current  $I_{\text{m,k}}$  during the short-circuit test.

#### SolutionResult

The magnetizing current is assumed to be proportional to the voltage:

$$I_{\text{m,k}} = I_{\text{m,N}} \cdot \frac{U_{1\{\text{k}\}}}{U_{1\{\text{N}\}}}$$

$$I_{\text{m,k}} = 0.0072 \text{ A} = 7.2 \text{ mA}$$

$$m, N) \cdot \frac{U_{1\{\text{rm } k\}}}{U_{1\{\text{rm } N\}}} \end{align*}$$

Insert the values: 
$$\begin{aligned} I_{\text{rm } m, k} &= 0.12 \cdot A \cdot \frac{13.8 \cdot V}{230 \cdot V} \\ I &= 0.0072 \cdot A \\ &= 7.2 \cdot \text{mA} \end{aligned}$$

3. Compare  $I_{\text{rm } m, k}$  with  $I_{1\{\text{rm } N\}}$ .

#### SolutionResult

Compare the short-circuit magnetizing current with the rated current: 
$$\frac{I_{\text{rm } m, k}}{I_{1\{\text{rm } N\}}} = \frac{0.0072 \cdot A}{3.0 \cdot A} \end{align*}$$

Calculate the ratio: 
$$\frac{I_{\text{rm } m, k}}{I_{1\{\text{rm } N\}}} = 0.0024 \quad \text{or} \quad 0.24\% \end{align*}$$

$$\frac{I_{\text{rm } m, k}}{I_{1\{\text{rm } N\}}} = 0.24\% \end{align*}$$

4. Explain why the magnetizing branch can be neglected.

#### SolutionResult

During the short-circuit test, the applied voltage is much smaller than the rated voltage: 
$$U_{1\{\text{rm } k\}} \ll U_{1\{\text{rm } N\}} \end{align*}$$

The magnetizing branch  $R_{\text{Fe}} \parallel jX_{1\{\text{rm } H\}}$  can usually be neglected in the short-circuit test.

Since the magnetizing current is assumed to be approximately proportional to the applied voltage, the magnetizing current is also very small:  $I_{m,k} = 7.2 \sim \text{mA}$

Compared with the rated current:  $I_{N1} = 3.0 \sim \text{A}$

the magnetizing current is only  $0.24\%$ .

So during the short-circuit test, almost all current flows through the short-circuit path consisting of  $R_k$  and  $X_k$ .

### Exercise E10 Why the short-circuit equivalent circuit is often sufficient under load

A transformer has the turns ratio  $n=10$ . The short-circuit equivalent parameters referred to the primary side are  $R_k = 2.0 \sim \Omega$ ,  $X_k = 4.0 \sim \Omega$ .

The secondary load current is  $I_2 = 5.0 \sim \text{A}$ . The load is ohmic-inductive with  $\cos\varphi = 0.8$ .

The no-load current on the primary side is approximately  $I_{10} = 0.03 \sim \text{A}$ .

1. Calculate the load-related primary current  $I'_2$ .

#### SolutionResult

The load-related primary current is:  

$$I'_2 = \frac{I_2}{n}$$

Insert the values: 
$$I'_2 = \frac{5.0 \sim \text{A}}{10} = 0.50 \sim \text{A}$$

$$I'_2 = 0.50 \sim \text{A}$$

$$0.50 \sim \{\rm A\} \end{align*}$$

2. Estimate the primary-side voltage drop.

#### SolutionResult

The voltage drop is estimated with:  

$$\begin{aligned} \Delta U_1 \approx I_2 \\ \left( R_k \cos\varphi + X_k \sin\varphi \right) \end{aligned}$$

For  $\cos\varphi=0.8$ :  

$$\begin{aligned} \sin\varphi &= \sqrt{1-\cos^2\varphi} \\ &= \sqrt{1-0.8^2} \\ &= 0.6 \end{aligned}$$

Insert the values:  

$$\begin{aligned} \Delta U_1 &\approx 0.50 \sim \{\rm A\} \\ \left( 2.0 \sim \Omega \cdot 0.8 + \right. & \\ \left. 4.0 \sim \Omega \cdot 0.6 \right) & \\ &= 0.50 \sim \{\rm A\} \left( \right. \\ \left. 1.6 \sim \Omega + 2.4 \sim \Omega \right) & \\ &= 2.0 \sim \{\rm V\} \end{aligned}$$

$$\begin{aligned} \Delta U_1 \approx \\ 2.0 \sim \{\rm V\} \end{aligned}$$

3. Calculate the secondary-side voltage drop  $\Delta U_2 \approx \frac{\Delta U_1}{n}$ .

#### SolutionResult

The secondary-side voltage drop is:  

$$\Delta U_2 \approx \frac{\Delta U_1}{n}$$

Insert the values:  

$$\Delta U_2 \approx \frac{2.0 \sim \{\rm V\}}{n}$$

$$\begin{aligned} \Delta U_2 \approx \\ 0.20 \sim \{\rm V\} \end{aligned}$$

```
V}}{10} \\ \&= 0.20~{\rm V}
\end{align*}
```

4. Estimate an upper bound for the neglected voltage drop caused by  $I_{10}$ .

SolutionResult

First calculate the magnitude of the short-circuit impedance:

```
\begin{align*} |\underline{Z}_{\rm k}| = \sqrt{R_{\rm k}^2 + X_{\rm k}^2} \end{align*}
```

```
Insert the values: \begin{align*} |\underline{Z}_{\rm k}| \&= \sqrt{(2.0~\Omega)^2 + (4.0~\Omega)^2} \\ \&= 4.47~\Omega \end{align*}
```

The upper bound for the voltage drop caused by the no-load current is:

```
\begin{align*} \Delta U_{1,10} \&\leq |\underline{Z}_{\rm k}| I_{10} \\ \&= 4.47~\Omega \cdot 0.03~{\rm A} \\ \&= 0.134~{\rm V} \end{align*}
```

On the secondary side:

```
\Delta U_{2,10} \&\leq \frac{0.134~{\rm V}}{10} \\ \&= 0.0134~{\rm V} \end{align*}
```

```
\begin{align*} |\underline{Z}_{\rm k}| \&= 4.47~\Omega \\ \Delta U_{1,10} \&\leq 0.134~{\rm V} \\ \Delta U_{2,10} \&\leq 0.0134~{\rm V} \end{align*}
```

5. Decide whether the short-circuit equivalent circuit is sufficient for this load estimate.

SolutionResult

The load-related secondary-side voltage drop is: 
$$\Delta U_2 \approx 0.20 \text{ V}$$

The estimated neglected secondary-side voltage drop caused by the no-load current is at most: 
$$\Delta U_{2,10} \leq 0.0134 \text{ V}$$

This is small compared with the load-related drop of  $0.20 \text{ V}$ .

For this engineering estimate, the short-circuit equivalent circuit is sufficient.

### Exercise E11 Ideal transformer versus real transformer

A transformer has the rated primary voltage of  $U_1 = 230 \text{ V}$  and the turns ratio  $n = 10$ . A resistive load draws  $I_2 = 4.0 \text{ A}$ . For the real transformer, the short-circuit equivalent parameters referred to the primary side are  $R_k = 2.4 \text{ } \Omega$ ,  $X_k = 3.2 \text{ } \Omega$ . The iron loss is approximately  $P_{\text{Fe}} = 1.5 \text{ W}$ . Assume a resistive load with  $\cos \varphi = 1$ .

1. Calculate the ideal secondary voltage  $U_{2,\text{ideal}}$ .

#### SolutionResult

For the ideal transformer: 
$$U_{2,\text{ideal}} = \frac{U_1}{n}$$

Insert the values: 
$$U_{2,\text{ideal}} = \frac{230 \text{ V}}{10} = 23.0 \text{ V}$$

$$U_{2,\text{ideal}} = 23.0 \text{ V}$$

2. Calculate the load-related primary current  $I'_2$ .

### SolutionResult

The load-related primary current is:

$$I'_2 = \frac{I_2}{n}$$

Insert the values:  $I'_2 = \frac{4.0 \text{ A}}{10} = 0.40 \text{ A}$

$$I'_2 = 0.40 \text{ A}$$

3. Estimate the real secondary voltage.

### SolutionResult

For a resistive load, the approximate primary-side voltage drop is:

$$\Delta U_1 \approx I'_2 R_k$$

Insert the values:  $\Delta U_1 \approx 0.40 \text{ A} \cdot 2.4 \Omega = 0.96 \text{ V}$

The corresponding secondary-side voltage drop is:  $\Delta U_2 \approx \frac{\Delta U_1}{n} = \frac{0.96 \text{ V}}{10} = 0.096 \text{ V}$

Thus the real secondary voltage is approximately:  $U_{2, \text{real}} \approx 23.0 \text{ V}$

$$\begin{aligned} \Delta U_1 &\approx 0.96 \text{ V} \\ \Delta U_2 &\approx 0.096 \text{ V} \\ U_{2, \text{real}} &\approx 22.90 \text{ V} \end{aligned}$$

$$V_2 - 0.096 \text{ V} \approx 22.90 \text{ V}$$

4. Estimate the copper losses.

#### SolutionResult

The copper losses are: 
$$P_{\text{Cu}} \approx R_{\text{k}} (I_2')^2$$

Insert the values: 
$$P_{\text{Cu}} \approx 2.4 \text{ } \Omega \cdot (0.40 \text{ A})^2 \approx 0.384 \text{ W}$$

The real transformer also has iron losses: 
$$P_{\text{Fe}} = 1.5 \text{ W}$$

$$P_{\text{Cu}} \approx 0.384 \text{ W}$$

Additionally: 
$$P_{\text{Fe}} = 1.5 \text{ W}$$

5. Compare ideal and real transformer behavior.

#### SolutionResult

For the ideal transformer: 
$$U_{2, \text{ideal}} = 23.0 \text{ V}$$

For the real transformer: 
$$U_{2, \text{real}} \approx 22.90 \text{ V}$$

The real transformer has copper losses and iron losses: 
$$P_{\text{Cu}} + P_{\text{Fe}}$$

The real transformer differs from the ideal transformer by:

- a slightly lower secondary voltage,
- copper and iron losses,
- a load-dependent voltage drop.

For this operating point it is close to ideal, but not exactly ideal.

```
P_{\rm Cu}\approx 0.384~{\rm W}
\\ P_{\rm Fe}\approx 1.5~{\rm W}
\end{align*}
```

So the main differences are:

- the ideal transformer has exactly  $U_2=23.0~{\rm V}$ , the real transformer has a slightly lower voltage,
- the ideal transformer has no losses, the real transformer has copper and iron losses,
- the ideal transformer has no leakage voltage drop, the real transformer has a load-dependent voltage drop.

For this operating point the transformer is close to ideal, but not exactly ideal.

From:

<https://wiki.mexle.org/> - **MEXLE Wiki**

Permanent link:

<https://wiki.mexle.org/dummy?rev=1779065800>

Last update: **2026/05/18 02:56**

