

task_pdkggtyexxy1ktu3_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E1 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022) 2

complex impedance, exam ee1 WS2022

Exercise E1 Impedances at different Frequencies
(written test, approx. 18 % of a 60-minute written test, WS2022)

A series circuit consists of a resistor $R_1 = 1.00 \text{ } \Omega$, an inductor $L = 4.7 \text{ } \mu\text{H}$, and a capacitor $C = 40 \text{ nF}$. The circuit is connected to an AC voltage source $v(t) = 10 \cos(2\pi \cdot 450 \text{ kHz} \cdot t) \text{ V}$. Determine the magnitude of the current I through the circuit.

Solution

$$R_1 = 1.00 \text{ } \Omega$$

$$R_2 = 10.0 \text{ } \Omega$$

A series circuit means that the current is constant on every component.

The equivalent impedance for R and L combined is given by

Parallel circuit means that the voltage is the same on R_2 and C_3

$$\frac{1}{Z_{\text{parallel}}} = \frac{1}{R_2} + \frac{1}{X_{C_3}}$$

$$\frac{1}{Z_{\text{parallel}}} = \frac{1}{10} + \frac{1}{-j \cdot 40 \cdot 10^{-9} \cdot 450 \cdot 10^3}$$

$$\frac{1}{Z_{\text{parallel}}} = \frac{1}{10} + \frac{1}{-j \cdot 18}$$

$$\frac{1}{Z_{\text{parallel}}} = \frac{j + 18}{180}$$

$$Z_{\text{parallel}} = \frac{180}{18 + j}$$

$$Z_{\text{parallel}} = \frac{180(18 - j)}{(18 + j)(18 - j)}$$

$$Z_{\text{parallel}} = \frac{3240 - 180j}{324 - 36}$$

$$Z_{\text{parallel}} = \frac{3240 - 180j}{288}$$

$$Z_{\text{parallel}} = 11.25 - 0.625j \text{ } \Omega$$

Therefore, the resulting current of the parallel circuit is given as:

$$I_{\text{parallel}} = \frac{V_{\text{parallel}}}{Z_{\text{parallel}}} = \frac{10}{11.25 - 0.625j}$$

$$I_{\text{parallel}} = \frac{10(11.25 + 0.625j)}{(11.25 - 0.625j)(11.25 + 0.625j)}$$

$$I_{\text{parallel}} = \frac{112.5 + 6.25j}{126.5625 - 0.390625}$$

$$I_{\text{parallel}} = \frac{112.5 + 6.25j}{126.171875}$$

$$I_{\text{parallel}} = 0.892 + 0.0495j \text{ A}$$

Back to the first formula:

$$I = \frac{V}{Z_{\text{total}}} = \frac{10}{1.00 + j \cdot 20.25 + 11.25 - 0.625j}$$

$$I = \frac{10}{12.25 + j \cdot 19.625}$$

$$I = \frac{10(12.25 - j \cdot 19.625)}{(12.25 + j \cdot 19.625)(12.25 - j \cdot 19.625)}$$

$$I = \frac{122.5 - 196.25j}{150.0625 + 384.375}$$

$$I = \frac{122.5 - 196.25j}{534.4375}$$

$$I = 0.229 - 0.367j \text{ A}$$

From: <https://wiki.mexle.org/> - MEXLE Wiki

Permanent link: https://wiki.mexle.org/electrical_engineering_1/task_pdkggyexxy1ktu3_with_calculation?rev=1680242542

Last update: 2023/03/31 08:02

