

task_pdkggtyexxy1ktu3_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E1 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)	2
--	---

complex impedance, exam ee1 WS2022

Exercise E1 Impedances at different Frequencies
(written test, approx. 18 % of a 60-minute written test, WS2022)

A series circuit consists of a resistor $R_1 = 1.00 \text{ } \Omega$, an inductor $L = 4.7 \text{ } \mu\text{H}$, and a capacitor $C = 40 \text{ nF}$. The circuit is connected to an AC voltage source $v(t) = 10 \cos(2\pi \cdot 450 \text{ kHz} \cdot t) \text{ V}$. Determine the magnitude of the current I through the circuit.

Solution

$$R_1 = 1.00 \text{ } \Omega$$

$$R_2 = 10.0 \text{ } \Omega$$

A series circuit means that the current is constant on every component.

The equivalent impedance for R and L combined is given by

Parallel circuit means that the voltage is the same on R_2 and C_3

$$\frac{1}{Z_{\text{parallel}}} = \frac{1}{R_2} + \frac{1}{X_{C_3}}$$

$$\frac{1}{Z_{\text{parallel}}} = \frac{1}{10} + \frac{1}{-j \cdot 40 \cdot 10^{-9} \cdot 450 \cdot 10^3}$$

$$\frac{1}{Z_{\text{parallel}}} = \frac{1}{10} + \frac{1}{-j \cdot 18}$$

$$\frac{1}{Z_{\text{parallel}}} = \frac{j + 18}{180}$$

$$Z_{\text{parallel}} = \frac{180}{18 + j}$$

$$Z_{\text{parallel}} = \frac{180(18 - j)}{(18 + j)(18 - j)}$$

$$Z_{\text{parallel}} = \frac{3240 - 180j}{324 + 36}$$

$$Z_{\text{parallel}} = \frac{3240 - 180j}{360}$$

$$Z_{\text{parallel}} = 9 - 0.5j \text{ } \Omega$$

Therefore, the resulting current of the parallel circuit is given as:

$$I_{\text{parallel}} = \frac{V}{Z_{\text{parallel}}} = \frac{10}{9 - 0.5j}$$

$$I_{\text{parallel}} = \frac{10(9 + 0.5j)}{(9 - 0.5j)(9 + 0.5j)}$$

$$I_{\text{parallel}} = \frac{90 + 5j}{81 - 0.25}$$

$$I_{\text{parallel}} = \frac{90 + 5j}{80.75}$$

$$I_{\text{parallel}} = 1.11 + 0.06j \text{ A}$$

Back to the first formula:

$$I_{\text{total}} = \frac{V}{R_1 + Z_{\text{parallel}}}$$

$$I_{\text{total}} = \frac{10}{1 + 9 - 0.5j}$$

$$I_{\text{total}} = \frac{10}{10 - 0.5j}$$

$$I_{\text{total}} = \frac{10(10 + 0.5j)}{(10 - 0.5j)(10 + 0.5j)}$$

$$I_{\text{total}} = \frac{100 + 5j}{100 - 0.25}$$

$$I_{\text{total}} = \frac{100 + 5j}{99.75}$$

$$I_{\text{total}} = 1.00 + 0.05j \text{ A}$$

From: <https://wiki.mexle.org/> - MEXLE Wiki

Permanent link: https://wiki.mexle.org/electrical_engineering_1/task_pdkggyexxy1ktu3_with_calculation?rev=1680242542

Last update: 2023/03/31 08:02

