

Exam Winter Semester 2022

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exam Winter Semester 2022	3
Additional permitted Aids	3
Hits	3
Tasks	3
Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)	3
Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)	3
Exercise E2 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)	4
Exercise E1 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)	4
Exercise E3 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)	5
Exercise E2 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)	7
Exercise E1 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022)	9
Exercise E3 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022)	13
Exercise E4 Charging Capacitors (written test, approx. 16 % of a 60-minute written test, WS2022)	17
Exercise E1 Charging Capacitors (written test, approx. 16 % of a 60-minute written test, WS2022)	18
Exercise E5 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)	20
Exercise E4 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)	20
Exercise E6 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute	

written test, WS2022)	21
Exercise E1 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)	21
Exercise E1 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022)	22
Exercise E1 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022)	25

Exam Winter Semester 2022

Additional permitted Aids

- non-programmable calculator,
- formulary (2 DIN A4 pages)

Hits

- The duration of the exam is 60 min.
- Attempts to cheat will lead to exclusion and failure of the exam.
- Withdrawal is no longer possible after these exam has been handed out.
- Please write down intermediate calculations and results on the assignment sheet. (when more space is needed also on the reverse side. In this case: Mark it clearly).
- Always use units in the calculation.
- Use a document-proof, non-red pen.

Tasks

Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)

A heating element made of solid nichrome wire with a temperature coefficient of $1.80 \cdot 10^{-4} \text{ K}^{-1}$ is selected. The power dissipation (= heat flow) of $P=40 \text{ W}$ is necessary. Calculate the current I needed to operate it.

The Nichrome wire has a resistivity of $1.10 \cdot 10^{-6} \text{ } \Omega \text{ m}$.

The heating element is 3 m long and has a diameter of 3.57 mm .

∴ Calculate the resistance R of the heating element.

Solution

$$\begin{aligned} P &= U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \sqrt{\frac{P}{R}} \\ I &= \sqrt{\frac{40 \text{ W}}{0.33 \text{ } \Omega}} \end{aligned}$$

$$\begin{aligned} R &= \rho \cdot \frac{l}{A} \quad \text{with } A = r^2 \cdot \pi = \frac{1}{4} d^2 \cdot \pi \\ R &= \rho \cdot \frac{l}{\frac{1}{4} d^2 \cdot \pi} \quad \text{and } R = 1.10 \cdot 10^{-6} \text{ } \Omega \text{ m} \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi} \end{aligned}$$

Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)

A heating element made of solid nichrome wire with a temperature coefficient of $1.80 \cdot 10^{-4} \text{ K}^{-1}$ is selected.

Result power dissipation (= heat flow) of $P=40 \text{ W}$ is necessary.
 Calculate the current I needed to operate it.
 The Nichrome wire has a resistivity of $1.10 \cdot 10^{-6} \text{ } \Omega \text{ m}$.
 The heating element is 3 m long and has a diameter of 3.57 mm .
Solution $R = \rho \cdot \frac{l}{A} = 10^{-3} \text{ } \Omega$

Solution

$$P = U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \sqrt{\frac{P}{R}} = \sqrt{\frac{40 \text{ W}}{0.33 \text{ } \Omega}}$$

$$R = \rho \cdot \frac{l}{A} \quad | \quad A = r^2 \cdot \pi = \frac{1}{4} d^2 \cdot \pi \quad || \quad R = \rho \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad || \quad R = 1.10 \cdot 10^{-6} \text{ } \Omega \text{ m} \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi}$$

Exercise E2 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)

2. Regulation explains a temperature sensitive component for a refrigerator. The thermistor has a resistance of $10 \text{ k} \Omega$ at 25°C . Its temperature coefficients are: $\alpha=0.01 \text{ } \frac{1}{\text{K}}$ and $\beta=71 \cdot 10^{-6} \text{ } \frac{1}{\text{K}^2}$

Result The temperature inside the refrigeration system can reach down to -40°C .
 Calculate the resistance of the thermistor at -40°C .
Solution The resistance of the thermistor at -40°C is $6.5 \text{ k} \Omega$.
 Therefore, with constant U and increasing R the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2) \quad | \quad \Delta T = T_{\text{end}} - T_{\text{start}} \quad || \quad R = 10 \text{ k} \Omega \cdot \left(1 + 0.01 \cdot (-40^\circ \text{C} - 25^\circ \text{C}) + 71 \cdot 10^{-6} \cdot (-40^\circ \text{C} - 25^\circ \text{C})^2\right)$$

Exercise E1 Temperature-dependent Resistance

(written test, approx. 6 % of a 60-minute written test, WS2022)

2. A resistor exhibits a temperature coefficient of resistance of $\alpha = 0.01 \text{ K}^{-1}$ and a resistance of $R_0 = 10 \text{ k}\Omega$ at $T_0 = 25^\circ\text{C}$. Its temperature coefficients are: $\alpha = 0.01 \text{ K}^{-1}$ and $\beta = 71 \cdot 10^{-6} \text{ K}^{-2}$.
 Result: The temperature inside the refrigeration system can reach down to -40°C .

The temperature inside the refrigeration system can reach down to -40°C .

$$R = R_0 (1 + \alpha \Delta T + \beta \Delta T^2) = 10 \text{ k}\Omega (1 + 0.01 \cdot (-40 - 25) + 71 \cdot 10^{-6} \cdot (-40 - 25)^2) = 6.5 \text{ k}\Omega$$

Resistor transfer resistor R in parallel of the circuit and generate heat. Therefore, a solution is to use the heat up the refrigeration system.

Therefore, with constant U and increasing R the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 (1 + \alpha \Delta T + \beta \Delta T^2) \quad | \quad \Delta T = T_{\text{end}} - T_{\text{start}}$$

$$R = 10 \text{ k}\Omega (1 + 0.01 \cdot (-40^\circ\text{C} - 25^\circ\text{C}) + 71 \cdot 10^{-6} \cdot (-40^\circ\text{C} - 25^\circ\text{C})^2)$$


Exercise E3 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)

The following shall hold: $R_1 = 200 \text{ }\Omega$, $R_2 = R_3 = 100 \text{ }\Omega$, and the voltage $U = 10 \text{ V}$.
 Result: $R_B = 132.8 \text{ }\Omega$.

Solution

$$R_{\text{B}} = 132.8 \text{ }\Omega$$

Now a wye-delta transformation is necessary.




Since $R_2=R_3$ and based on the equations for the transformation, the transformed R_Y is given as:
$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2 + R_2} = \frac{(100 \Omega)^2}{3 \cdot 100 \Omega} = \frac{1}{3} \cdot 100 \Omega = 33.33 \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:
$$R_{eq} = R_Y + (R_Y + R_1 + R_1) \parallel (R_Y + R_2) \parallel R_{eq} = 33.33 \Omega + (33.33 \Omega + 400 \Omega) \parallel (33.33 \Omega + 100 \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance R_{eq} between A and B.

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = (R_2 + R_1 + R_1) \parallel (R_2 + R_2) \parallel (100 \Omega + 200 \Omega + 200 \Omega) \parallel (100 \Omega + 100 \Omega) \parallel (500 \Omega) \parallel (200 \Omega) \parallel R_{\text{eq}} = \frac{500 \Omega \cdot 200 \Omega}{500 \Omega + 200 \Omega}$$


Exercise E2 Pure Resistor Network Simplification
(written test, approx. 13 % of a 60-minute written test, WS2022)

The following shall be solved with $R_1 = 200 \Omega$, $R_2 = R_3 = 100 \Omega$ and the voltage U_{AB} given.

Solution

$$R_{\text{eq}} = 132.8 \Omega$$

Now a wye-delta transformation is necessary.




Since $R_2=R_3$ and based on the equations for the transformation, the transformed R_Y is given as:
$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2 + R_2} = \frac{(100 \Omega)^2}{3 \cdot 100 \Omega} = \frac{1}{3} \cdot 100 \Omega = 33.33 \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:
$$R_{eq} = R_Y + (R_Y + R_1 + R_1) \parallel (R_Y + R_2) \parallel R_{eq} = 33.33 \Omega + (33.33 \Omega + 400 \Omega) \parallel (33.33 \Omega + 100 \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance R_{eq} between A and B.

Solution




The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = (R_2 + R_1 + R_{-1}) \parallel (R_2 + R_2) \parallel R_{\text{eq}} = (100 \Omega + 200 \Omega + 200 \Omega) \parallel (100 \Omega + 100 \Omega) \parallel R_{\text{eq}} = (500 \Omega) \parallel (200 \Omega) \parallel R_{\text{eq}} = \frac{500 \Omega \cdot 200 \Omega}{500 \Omega + 200 \Omega}$$

**Exercise E1 Equivalent linear Source
(written test, approx. 14 % of a 60-minute written test, WS2022)**

The circuit in the following has to be simplified.
Result


$$U_{\text{s}} = U_{\text{AB}} = 4.5 \text{ V} \quad R_{\text{i}} = R_{\text{AB}} = 6 \Omega$$




Calculate the internal resistance R_i and the source voltage U_s of an equivalent linear voltage source on the connectors A and B . $R_1=5.0 \Omega$, $U_2=6.0 \text{ V}$, $R_3= 10 \Omega$, $I_4=4.2 \text{ A}$, $R_5=10 \Omega$, $R_6=7.5 \Omega$, $R_7=15 \Omega$ Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of U_2 and R_1 can be transformed into a current source $I_2 = \frac{U_2}{R_1}$ and R_1 :



Now a lot of them can be combined. The resistors R_1 , R_3 , R_5 are in parallel, like also I_2 and I_4 :

$$R_{135} = R_1 || R_3 || R_5$$

$$I_{24} = I_2 - I_4$$

The resulting circuit can again be transformed:



Here, the U_{24} is calculated by I_{24} as the following:

$$U_{24} = I_{24} \cdot R_{56}$$

$$U_{24} = U_2 \cdot \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} - I_4 \cdot R_1 || R_3 || R_5$$

On the right side of the last circuit, there is a voltage divider given by R_{135} , R_6 , and R_7 .

Therefore the voltage between A and B is given as:

$$U_{AB} = U_{24} \cdot \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} - (U_2 \cdot \frac{R_7}{R_1} - I_4) \cdot \frac{R_7 \cdot R_1 || R_3 || R_5}{R_6 + R_7 + R_1 || R_3 || R_5}$$

For the internal resistance R_i the ideal voltage source is substituted by its resistance ($= 0 \Omega$, so a short-circuit):

$$R_{AB} = R_7 || (R_6 + R_1 || R_3 || R_5)$$

with $R_1 || R_3 || R_5 = 5 \Omega || 10 \Omega || 10 \Omega = 5 \Omega || 5 \Omega = 2.5 \Omega$:


$$U_{AB} = \frac{6.0 \text{ V}}{5.0 \Omega} - 4.2 \Omega \cdot \frac{15 \Omega \cdot 2.5 \Omega}{7.5 \Omega + 15 \Omega + 2.5 \Omega}$$

$$R_{AB} = 15 \Omega || (7.5 \Omega + 2.5 \Omega)$$

**Exercise E3 Equivalent linear Source
(written test, approx. 14 % of a 60-minute written test, WS2022)**

The circuit in the following has to be simplified.
Result


$$U_s = U_{AB} = 4.5 \text{ V} \quad R_i = R_{AB} = 6 \Omega$$




Calculated the internal resistance R_{int} and the source voltage U_{oc} of an equivalent linear voltage source on the connectors A and B . $R_1=5.0 \text{ }\Omega$, $U_2=6.0 \text{ V}$, $R_3= 10 \text{ }\Omega$, $I_4=4.2 \text{ A}$, $R_5=10 \text{ }\Omega$, $R_6=7.5 \text{ }\Omega$, $R_7=15 \text{ }\Omega$ Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of U_2 and R_1 can be transformed into a current source $I_2 = \frac{U_2}{R_1}$ and R_1 :



Now a lot of them can be combined. The resistors R_1 , R_3 , R_5 are in parallel, like also I_2 and I_4 :

$$R_{135} = R_1 || R_3 || R_5$$

$$I_{24} = I_2 - I_4 = \frac{U_{24}}{R_1} - I_4$$

The resulting circuit can again be transformed:



Here, the U_{24} is calculated by I_{24} as the following:

$$U_{24} = I_{24} \cdot R_{135} + I_4 \cdot R_1$$

$$U_{AB} = U_{24} \cdot \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} - I_4 \cdot R_1 || R_3 || R_5$$

On the right side of the last circuit, there is a voltage divider given by R_{135} , R_6 , and R_7 .

Therefore the voltage between A and B is given as:

$$U_{AB} = U_{24} \cdot \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} - (U_2 \over R_1 - I_4) \cdot \frac{R_7 \cdot R_1 || R_3 || R_5}{R_6 + R_7 + R_1 || R_3 || R_5}$$

For the internal resistance R_i the ideal voltage source is substituted by its resistance ($=0 \Omega$, so a short-circuit):

$$R_{AB} = R_7 || (R_6 + R_1 || R_3 || R_5)$$

with $R_1 || R_3 || R_5 = 5 \Omega || 10 \Omega || 10 \Omega = 5 \Omega || 5 \Omega = 2.5 \Omega$:

$$U_{AB} = \frac{6.0 \text{ V}}{5.0 \Omega} - 4.2 \Omega \cdot \frac{15 \Omega \cdot 2.5 \Omega}{7.5 \Omega + 15 \Omega + 2.5 \Omega}$$

$$R_{AB} = 15 \Omega || (7.5 \Omega + 2.5 \Omega)$$


Exercise E4 Charging Capacitors
(written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit below is a battery with an internal resistance of R_1 and a switch S_1 and a capacitor C and a resistor R_2 in parallel. The voltage across the capacitor is again U_0 at the moment $t_0=0$ s when the switch S_1 is closed. Calculate the voltage $u_c(t_2)$ across the capacitor at $t_2=1$ ms after closing the switch.


Solution: To solve this, first create an equivalent linear voltage source from U , R_1 , and R_2 .

$$U_{eq} = \frac{U \cdot R_2}{R_1 + R_2} \quad R_{eq} = R_1 || R_2$$

On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting R_2 .




The circuit contains a voltage source $U=12 \text{ V}$, a switch S_1 , a resistor of $R_1=20 \text{ }\Omega$ and a capacitor of $C=100 \text{ }\mu\text{F}$. The switch S_2 to an additional consumer R_2 will be considered to be open for the first task. At the moment $t_0=0 \text{ s}$ the switch S_1 is closed, the voltage across the capacitor is $u_c(t_0)=0 \text{ V}$.



First do not consider the light bulb - it is not connected to the RC circuit. Calculate the point of time t_1 when $u_c(t_1)=0.5 \cdot U$.

Solution



So, here only R_1 and C gives the time constant: $\tau = R_1 \cdot C$

The following formula describes the time course of $u_C(t)$ which has to be $u_c(t_1)=0.5 \cdot U$:

$$u_c(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$$
 It has to be rearranged to $(1 - e^{-t/\tau}) = 0.5$.
 An equivalent linear voltage source can be given with $U_s = U \cdot \frac{R_B}{R_1 + R_B}$ and $R_i = R_1 \parallel R_B$ as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is: $U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U$. The internal resistance is given by substituting the ideal voltage source with its resistance ($R_i = 0 \text{ }\Omega$, short-circuit).

$$R_i = R_1 \parallel R_B = 10 \text{ }\Omega$$

$$u_c(t_2) = U_s \cdot (1 - e^{-t_2/(R_i \cdot C)}) = \frac{1}{2} \cdot U \cdot (1 - e^{-1 \text{ ms} / (10 \text{ }\Omega \cdot 100 \text{ }\mu\text{F})})$$

Exercise E1 Charging Capacitors
 (written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit (as shown in the figure) consists of a DC voltage source $U=6 \text{ V}$, a resistor $R_1=20 \text{ }\Omega$, a capacitor $C=20 \text{ }\mu\text{F}$ and a light bulb $R_B=20 \text{ }\Omega$. The switch S_1 is open. The voltage across the capacitor is again 0 V at the moment $t_0=0 \text{ s}$ when the switch S_1 is closed. Calculate the voltage $u_c(t_2)$ across the capacitor at $t_2=1 \text{ ms}$ after closing the switch.

Solution To solve this, first create an equivalent linear voltage source from U , R_1 , and R_B .


$$U_s = U \cdot \frac{R_B}{R_1 + R_B} = 2 \text{ V}$$

$$R_i = R_1 \parallel R_B = 10 \text{ }\Omega$$

Solution

The ideal voltage source is $U = 12 \text{ V}$. The internal resistance is $R_1 = 20 \text{ }\Omega$. The voltage across the capacitor is u_C . The voltage across the light bulb is u_B . The voltage across the resistor R_2 is u_{R_2} . The voltage across the capacitor is u_C . The voltage across the light bulb is u_B . The voltage across the resistor R_2 is u_{R_2} .

On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting R_2 .




The circuit contains a voltage source $U = 12 \text{ V}$, a switch S_1 , a resistor of $R_1 = 20 \text{ }\Omega$ and a capacitor of $C = 100 \text{ }\mu\text{F}$.

The switch S_2 to an additional consumer R_2 will be considered to be open for the first asks. At the moment $t_0 = 0$ the switch S_1 is closed, the voltage across the capacitor is $u_C(t_0) = 0$.

First do not consider the light bulb - it is not connected to the RC circuit.

Calculate the point of time t_1 when $u_C(t_1) = 0.5 \cdot U$.



Solution

An equivalent linear voltage source can be given with U , R_1 , and R_B as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is: $U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U$. The internal resistance is given by substituting the ideal voltage source with its resistance ($R = 0 \text{ }\Omega$, short-circuit). $R_i = R_1 \parallel R_B = 10 \text{ }\Omega$.

$$u_C(t_2) = U_s \cdot (1 - e^{-t_2 / (R_i \cdot C)}) = \frac{1}{2} \cdot U \cdot (1 - e^{-t_2 / (10 \text{ }\Omega \cdot 100 \text{ }\mu\text{F})})$$

So, here only R_1 and C gives the time constant: $\tau = R_1 \cdot C$

The following formula describes the time course of $u_C(t)$ which has to be $u_C(t_1) = 0.5 \cdot U$: $u_C(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$. It has to be rearranged to $(1 - e^{-t/\tau}) = 0.5 \implies e^{-t/\tau} = 0.5 \implies -t/\tau = \ln(0.5) \implies t = \tau \cdot \ln(0.5) \implies t = R_1 \cdot C \cdot \ln(0.5)$

Exercise E5 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)

2. Given that the phasor voltage source $\underline{U} = 50 \angle 0^\circ$ V and the admittance $\underline{Y} = 0.24 - j0.2$ S, the current \underline{I} through the components ($\$R\$ and $\$X_L\$) shall be given.$$

After analysis, the full width dimensioned complex impedance values extracted can be given in phasor notation $\underline{Z} = \frac{1}{\underline{Y}} = \frac{1}{0.24 - j0.2} = \frac{0.24 + j0.2}{(0.24)^2 + (0.2)^2} = \frac{0.24 + j0.2}{0.1} = 2.4 + j2$ Ω .

Solution
.. Calculation of physical values of the two components.
Solution $\begin{aligned} R &= \operatorname{Re}\{Z\} = 2.4 \Omega \\ X_L &= \operatorname{Im}\{Z\} = 2 \Omega \end{aligned}$

Solution

$$\underline{I} = \frac{\underline{U}}{\underline{Z}} = \frac{50 \angle 0^\circ}{2.4 + j2} = \frac{50}{\sqrt{2.4^2 + 2^2}} \angle -\arctan\left(\frac{2}{2.4}\right) = 10.41 \angle -39.8^\circ$$

The current \underline{I} through the admittance \underline{Y} is $\underline{I}_Y = \underline{U} \underline{Y} = 50 \angle 0^\circ (0.24 - j0.2) = 12 - j10$ A. The magnitude is $|\underline{I}_Y| = \sqrt{12^2 + 10^2} = 15.62$ A. The phase is $\angle \underline{I}_Y = \arctan\left(\frac{-10}{12}\right) = -39.8^\circ$.

Therefore, the component R has a current $\underline{I}_R = \underline{I}_Y$ and the component X_L has a current $\underline{I}_{X_L} = j \underline{I}_Y$.
$$\underline{I}_R = 12 - j10 \text{ A} \quad \underline{I}_{X_L} = j(12 - j10) = 10 + j12 \text{ A}$$

With the complex part $\underline{Z} = 2.4 + j2 \Omega$, the physical values are $R = 2.4 \Omega$ and $X_L = 2 \Omega$.
$$\underline{I}_R = \frac{\underline{U}}{R} = \frac{50 \angle 0^\circ}{2.4} = 20.83 \angle 0^\circ \text{ A}$$

$$\underline{I}_{X_L} = \frac{\underline{U}}{X_L} = \frac{50 \angle 0^\circ}{2} = 25 \angle 0^\circ \text{ A}$$

The phase φ can be calculated as $\varphi = \arctan\left(\frac{\operatorname{Im}\{Z\}}{\operatorname{Re}\{Z\}}\right) = \arctan\left(\frac{2}{2.4}\right) = 39.8^\circ$.

Exercise E4 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)

2. Given that the phasor voltage source $\underline{U} = 50 \angle 0^\circ$ V and the admittance $\underline{Y} = 0.24 - j0.2$ S, the current \underline{I} through the components ($\$R\$ and $\$X_L\$) shall be given.$$

After analysis, the full width dimensioned complex impedance values extracted can be given in phasor notation $\underline{Z} = \frac{1}{\underline{Y}} = \frac{1}{0.24 - j0.2} = \frac{0.24 + j0.2}{(0.24)^2 + (0.2)^2} = \frac{0.24 + j0.2}{0.1} = 2.4 + j2$ Ω .

Solution
.. Calculation of physical values of the two components.
Solution $\begin{aligned} R &= \operatorname{Re}\{Z\} = 2.4 \Omega \\ X_L &= \operatorname{Im}\{Z\} = 2 \Omega \end{aligned}$

Solution

$$\underline{I} = \frac{\underline{U}}{\underline{Z}} = \frac{50 \angle 0^\circ}{2.4 + j2} = \frac{50}{\sqrt{2.4^2 + 2^2}} \angle -\arctan\left(\frac{2}{2.4}\right) = 10.41 \angle -39.8^\circ$$

The current \underline{I} through the admittance \underline{Y} is $\underline{I}_Y = \underline{U} \underline{Y} = 50 \angle 0^\circ (0.24 - j0.2) = 12 - j10$ A. The magnitude is $|\underline{I}_Y| = \sqrt{12^2 + 10^2} = 15.62$ A. The phase is $\angle \underline{I}_Y = \arctan\left(\frac{-10}{12}\right) = -39.8^\circ$.

The absolute value of the impedance is $|Z| = \sqrt{R^2 + (X_L - X_C)^2}$ and the phase angle is $\phi = \arctan\left(\frac{X_L - X_C}{R}\right)$.
 With the complex part comes the physical value: $X_L = \omega L$ and $X_C = \frac{1}{\omega C}$.
 The phase ϕ is given by $\phi = \arctan\left(\frac{X_L - X_C}{R}\right)$.

Exercise E6 Impedances at different Frequencies
 (written test, approx. 18 % of a 60-minute written test, WS2022)

At a series circuit with a resistor $R = 1.00 \text{ k}\Omega$, a capacitor $C = 40 \text{ nF}$ and an inductor $L = 4.7 \text{ }\mu\text{H}$ in AC with a voltage $U = 10 \text{ V}$ and a frequency $f = 450 \text{ kHz}$.
 Result: $Z = 1.00 \text{ k}\Omega$, $X_L = 0.84 \text{ }\Omega$, $X_C = 99.47 \text{ }\Omega$, $I = 10.0 \text{ mA}$, $\phi = 89.9^\circ$.
 A resistor R_1 shall have the same absolute value of the impedance as a capacitor $C_1 = 40 \text{ nF}$ at $f_1 = 4 \text{ MHz}$.

Solution
 Solution $R_1 = 1.00 \text{ k}\Omega$
 Solution $R_2 = 10.0 \text{ }\Omega$

A series circuit means that the current is constant on every component.
 The equivalent impedance for R and L combined is given by $Z_{RL} = \sqrt{R^2 + X_L^2}$.
 Parallel circuit means that the voltage is the same on R_2 and C_1 .
 $Z_{R_2C_1} = \frac{R_2 \cdot X_{C_1}}{\sqrt{R_2^2 + X_{C_1}^2}}$ since X_{C_1} and R_2 are perpendicular to each other.
 $X_{C_1} = \frac{1}{\omega C_1} = \frac{1}{2\pi \cdot 4 \cdot 10^6 \cdot 40 \cdot 10^{-9}} = 0.9947 \text{ }\Omega$
 $Z_{R_2C_1} = \frac{R_2 \cdot 0.9947}{\sqrt{R_2^2 + 0.9947^2}}$
 This can be simplified to $Z_{R_2C_1} = \frac{R_2}{\sqrt{1 + \left(\frac{R_2}{0.9947}\right)^2}}$ (It has to, since R_2 is perpendicular to X_{C_1}).
 Therefore, the resulting current of the parallel circuit is given as:
 $I = \frac{U}{Z_{R_2C_1}} = \frac{U \cdot \sqrt{1 + \left(\frac{R_2}{0.9947}\right)^2}}{R_2}$
 This can be rearranged to get $R_2 = \frac{U \cdot \sqrt{1 + \left(\frac{R_2}{0.9947}\right)^2}}{I}$
 $R_2^2 = \frac{U^2 \cdot \left(1 + \left(\frac{R_2}{0.9947}\right)^2\right)}{I^2}$
 $R_2^2 \cdot I^2 = U^2 + \frac{U^2 \cdot R_2^2}{0.9947^2}$
 $R_2^2 \cdot I^2 - \frac{U^2 \cdot R_2^2}{0.9947^2} = U^2$
 $R_2^2 \cdot \left(I^2 - \frac{U^2}{0.9947^2}\right) = U^2$
 $R_2 = \frac{U}{\sqrt{I^2 - \frac{U^2}{0.9947^2}}}$
 Back to the first formula: $R_2 \cdot I = X_{C_1} \cdot I$
 $R_2 = X_{C_1} = \frac{1}{\omega C_1} = \frac{1}{2\pi \cdot 4 \cdot 10^6 \cdot 40 \cdot 10^{-9}} = 0.9947 \text{ }\Omega$

Exercise E1 Impedances at different Frequencies
 (written test, approx. 18 % of a 60-minute written test, WS2022)

Resistor values $20 = 450 \text{ kHz}$, $4.7 \text{ } \mu\text{H}$, and a 10 nF capacitor. 3 V AC voltage source of 3 V at 15 kHz .

~\rm X\\$ with $f = 15 \text{ kHz}$, $X_L = 2\pi f L = 2\pi \cdot 15 \cdot 4.7 \cdot 10^{-6} = 0.436 \text{ } \Omega$.
 ~\rm A\\$ through R_1 resistor R_1 shall have the same absolute value of the impedance as a capacitor

$X_C = 40 \text{ } \Omega$ at $f = 4 \text{ MHz}$.

Solution
 $R_1 = 1.00 \text{ } \Omega$
 $R_2 = 10.0 \text{ } \Omega$

Solution

A series circuit means that the current is constant on every component.

The equivalent impedance for R and L combined is given by $Z = R + jX_L$
 Parallel circuit means that the voltage is the same on R_2 and X_C
 $Z_{parallel} = \frac{R_2 \cdot X_C}{R_2 + X_C} = \frac{10 \cdot 40}{10 + 40} = 8 \text{ } \Omega$
 Since X_C is perpendicular to R_2 , this can be simplified to $Z_{parallel} = \frac{R_2 X_C}{\sqrt{R_2^2 + X_C^2}}$
 $Z_{parallel} = \frac{10 \cdot 40}{\sqrt{10^2 + 40^2}} = 8 \text{ } \Omega$ (It has to, since R_2 is perpendicular to X_C)
 Therefore, the resulting current of the parallel circuit is given as:
 $I_{parallel} = I_{R2} + I_{XC}$
 $I_{parallel} = \frac{V}{Z_{parallel}} = \frac{3}{8} = 0.375 \text{ A}$
 Back to the first formula: $R_3 \cdot I_{R3} = X_C \cdot I_{parallel}$
 $R_3 = \frac{X_C \cdot I_{parallel}}{I_{R3}} = \frac{40 \cdot 0.375}{0.1} = 150 \text{ } \Omega$


Exercise E1 Complex Impedance Circuit
 (written test, approx. 15 % of a 60-minute written test, WS2022)


1. Calculate the current $i(t)$ through the $10 \text{ } \Omega$ resistor. $u(t) = 3.0 \text{ V} \cdot \sin(2\pi \cdot 15 \text{ kHz} \cdot t)$

Result
 $Z = 48.2 \text{ } \Omega$, $Z_C = 19.8 \text{ } \Omega$

Draw the circuit diagram of the given circuit with all components, voltages, and currents.

$Z = \frac{U}{I}$, $I = \frac{U}{Z}$
 $Z_C = \frac{1}{2\pi \cdot 15 \cdot 10^{-6}} = 1061 \text{ } \Omega$
 $Z_L = 2\pi \cdot 15 \cdot 330 \cdot 10^{-6} = 3.14 \text{ } \Omega$
 $Z = R + jZ_L - jZ_C = 10 + j3.14 - j1061 = 10 - j1057.86 \text{ } \Omega$
 $|Z| = \sqrt{10^2 + 1057.86^2} = 1058 \text{ } \Omega$
 $I = \frac{3}{1058} = 0.0028 \text{ A}$





From:

<https://wiki.mexle.org/> - **MEXLE Wiki**

Permanent link:

https://wiki.mexle.org/electrical_engineering_1/ws2022_exam

Last update: **2023/08/17 11:43**

