

# task\_cgeyprm6oboukcci\_with\_calculation

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

Exercise E1 Pure Resistor Network Simplification (written test, approx. 12 % of a 60-minute written test, SS2023) .....	2
---	---

## network simplification, exam ee1 SS2023

### Exercise E1 Pure Resistor Network Simplification (written test, approx. 12 % of a 60-minute written test, SS2023)

The circuit below will be given to you. Calculate the voltage at node  $K$ , when switch  $S$  is closed.

Result

The values in the circuit are

Solution

- $R_1 = 60 \text{ } \Omega$

- $R_2 = 40 \text{ } \Omega$

- $R_3 = 10 \text{ } \Omega$

- $R_4 = 10 \text{ } \Omega$

The voltage divider for  $K$  has the same proportionality as the voltage divider for  $A$ .

Therefore, the potential of  $K$  is the same as for  $A$ . There will be no current flow through  $R_3$ . The resistance does not create a voltage drop and therefore does not interfere with the circuit.

1. Calculate the voltage at node  $K$ , when switch  $S$  is open. It might be beneficial to redraw the circuit first.

Solution

Rearranging the circuit one can get:

Once the switch  $S$  is opened, the upper part is a parallel circuit. Therefore,  $R_{\text{eq}}$  is given as:

$$R_{\text{eq}} = (R_1 + R_2) \parallel (R_1 + R_2) + R_4 = \frac{1}{2} \cdot (R_1 + R_2) + R_4 = \frac{1}{2} \cdot (60 \Omega + 40 \Omega) + 100 \Omega$$

From:

<https://wiki.mexle.org/> - **MEXLE Wiki**

Permanent link:

[https://wiki.mexle.org/electrical\\_engineering\\_and\\_electronics/task\\_cgeyprm6oboukcci\\_with\\_calculation](https://wiki.mexle.org/electrical_engineering_and_electronics/task_cgeyprm6oboukcci_with_calculation)

Last update: **2023/07/24 20:24**

