

task_ezrkjzifcegttcpc_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E1 Multiphase systems (written test, approx. 4 % of a 120-minute written test, SS2021)	2
---	---

Multiphase systems, RMS, power, exam ee2 SS2021

Exercise E1 Multiphase systems

(written test, approx. 4 % of a 120-minute written test, SS2021)


a) Specify the RMS value of the phase voltage U_{RMS} and the RMS value of the phase current I_{RMS} . Resulting.

A voltage with the RMS value $U_{\text{RMS}} = 110 \text{ V}$ is applied between the terminals of each winding.

Through each of the windings, there is a current with an RMS value $I_{\text{RMS}} = 5 \text{ A}$ and a phase shift $\varphi = \pm 25^\circ$ compared to the voltage.

b) Draw the circuit diagram. Since $U_{\text{RMS}} = 110 \text{ V}$ is applied between the terminals of each winding, the phase voltage U_{RMS} is the same for all windings. For a three-phase system, the phase voltage U_{RMS} is $U_{\text{RMS}} = 110 \text{ V}$ and the phase current I_{RMS} is $I_{\text{RMS}} = 5 \text{ A}$. The total power P_{tot} is $P_{\text{tot}} = 3 \cdot U_{\text{RMS}} \cdot I_{\text{RMS}} \cdot \cos(\varphi) = 1610.88 \text{ W}$. The total complex power S_{tot} is $S_{\text{tot}} = 3 \cdot U_{\text{RMS}} \cdot I_{\text{RMS}} = 1650 \text{ VA}$. The total reactive power Q_{tot} is $Q_{\text{tot}} = 3 \cdot U_{\text{RMS}} \cdot I_{\text{RMS}} \cdot \sin(\varphi) = 807.75 \text{ var}$. The total real power P_{tot} must be zero: $\sum P_i = 0$.

By this (and showing in the example in the image below), One can see, that $I_{\text{RMS}} = \sqrt{3} \cdot I_{\text{RMS}} = \sqrt{3} \cdot 5 \text{ A}$



one single phase as an example



From:
<https://wiki.mexle.org/> - **MEXLE Wiki**

Permanent link:
https://wiki.mexle.org/electrical_engineering_and_electronics/task_ezrkjzifcegttpc_with_calculation

Last update: **2024/07/04 11:34**

