

Exam Winter Semester 2022

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

- Exam Winter Semester 2022** 2
- Additional permitted Aids 2
- Hits 2
- Tasks 2
- Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022) 2
- Exercise E1 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022) 2
- Exercise E2 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022) 3
- Exercise E3 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022) 5
- Exercise E1 Charging Capacitors (written test, approx. 16 % of a 60-minute written test, WS2022) 9
- Exercise E4 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022) 10
- Exercise E1 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022) 11
- Exercise E1 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022) 12

Exam Winter Semester 2022

Additional permitted Aids

- non-programmable calculator,
- formulary (2 DIN A4 pages)

Hits

- The duration of the exam is 60 min.
- Attempts to cheat will lead to exclusion and failure of the exam.
- Withdrawal is no longer possible after these exam has been handed out.
- Please write down intermediate calculations and results on the assignment sheet. (when more space is needed also on the reverse side. In this case: Mark it clearly).
- Always use units in the calculation.
- Use a document-proof, non-red pen.

Tasks

Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)

A heating element made of a nichrome wire with a temperature coefficient of $1.80 \cdot 10^{-4} \text{ K}^{-1}$ is selected. The power dissipation (= heat flow) of $P=40 \text{ W}$ is necessary. Calculate the current I needed to operate it.

The Nichrome wire has a resistivity of $1.10 \cdot 10^{-6} \text{ } \Omega \text{ m}$.
The heating element is 3 m long and has a diameter of 3.57 mm .
Calculate the resistance R of the heating element.

Solution

$$\begin{aligned} P &= U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \sqrt{\frac{P}{R}} \\ R &= \rho \cdot \frac{l}{A} \quad \text{with } A = r^2 \cdot \pi = \frac{1}{4} d^2 \cdot \pi \\ R &= \rho \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad \Rightarrow \quad R = 1.10 \cdot 10^{-6} \text{ } \Omega \text{ m} \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi} \end{aligned}$$

[resistivity](#), [power](#), [exam ee1 ws2022](#)

Exercise E1 Temperature-dependent Resistance

(written test, approx. 6 % of a 60-minute written test, WS2022)

A. The following exhibits a temperature sensitive component used in a refrigerator. The component has a resistance of $10 \text{ k}\Omega$ at 25°C . Its temperature coefficients are: $\alpha = 0.01 \text{ } \frac{1}{\text{K}}$ and $\beta = 71 \cdot 10^{-6} \text{ } \frac{1}{\text{K}^2}$.

Result: The temperature inside the refrigeration system can reach down to -40°C .

$$R = 10 \text{ k}\Omega \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2)$$

Resistance transfer resistor R is part of the circuit and generates heat. Therefore, a solution is to use a heat sink up the refrigeration system.

Therefore, with constant U and increasing R the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2) \quad | \quad \Delta T = T_{\text{end}} - T_{\text{start}}$$

$$R = 10 \text{ k}\Omega \cdot \left(1 + 0.01 \frac{1}{\text{K}} \cdot (-40^\circ\text{C} - 25^\circ\text{C}) + 71 \cdot 10^{-6} \frac{1}{\text{K}^2} \cdot (-40^\circ\text{C} - 25^\circ\text{C})^2 \right)$$

temperature dependent resistance, power, heat, exam ee1 ws2022


Exercise E2 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)

The following shall be solved. $R_1 = 20 \text{ }\Omega$, $R_2 = 10 \text{ }\Omega$, $R_3 = 15 \text{ }\Omega$, $R_4 = 10 \text{ }\Omega$, $R_5 = 10 \text{ }\Omega$ and the source $U = 10 \text{ V}$. Result: $I = 0.5 \text{ A}$.

Solution

$$R_{\text{eq}} = 13.8 \text{ }\Omega$$

Now a wye-delta transformation is necessary.




Since $R_2=R_3$ and based on the equations for the transformation, the transformed R_Y is given as:
$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2 + R_2} = \frac{(100 \Omega)^2}{3 \cdot 100 \Omega} = \frac{1}{3} \cdot 100 \Omega = 33.33 \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:
$$R_{eq} = R_Y + (R_Y + R_1 + R_1) \parallel (R_Y + R_2) \parallel R_{eq} = 33.33 \Omega + (33.33 \Omega + 400 \Omega) \parallel (33.33 \Omega + 100 \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance R_{eq} between A and B.

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = (R_2 + R_1 + R_1) \parallel (R_2 + R_2)$$

$$R_{\text{eq}} = (100 \Omega + 200 \Omega + 200 \Omega) \parallel (100 \Omega + 100 \Omega)$$

$$R_{\text{eq}} = (500 \Omega) \parallel (200 \Omega)$$

$$R_{\text{eq}} = \frac{500 \Omega \cdot 200 \Omega}{500 \Omega + 200 \Omega}$$


[network simplification, exam ee1 ws2022](#)

**Exercise E3 Equivalent linear Source
(written test, approx. 14 % of a 60-minute written test, WS2022)**

The circuit in the following has to be simplified.
Result

$$U_s = U_{AB} = 4.5 \text{ V}$$


$$R_i = R_{AB} = 6 \Omega$$




Calculated the internal resistance R_{int} and the source voltage U_{oc} of an equivalent linear voltage source on the connectors A and B . $R_1=5.0 \text{ }\Omega$, $U_2=6.0 \text{ V}$, $R_3= 10 \text{ }\Omega$, $I_4=4.2 \text{ A}$, $R_5=10 \text{ }\Omega$, $R_6=7.5 \text{ }\Omega$, $R_7=15 \text{ }\Omega$ Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of U_2 and R_1 can be transformed into a current source $I_2 = \frac{U_2}{R_1}$ and R_1 :



Now a lot of them can be combined. The resistors R_1 , R_3 , R_5 are in parallel, like also I_2 and I_4 :

$$R_{135} = R_1 || R_3 || R_5$$

$$I_{24} = I_2 - I_4$$

The resulting circuit can again be transformed:



Here, the U_{24} is calculated by I_{24} as the following:

$$U_{24} = I_{24} \cdot R_{135}$$

$$U_{24} = U_{23} \cdot \frac{R_6}{R_6 + R_7 + R_1 || R_3 || R_5}$$

On the right side of the last circuit, there is a voltage divider given by R_{135} , R_6 , and R_7 .

Therefore the voltage between A and B is given as:

$$U_{AB} = U_{24} \cdot \left(\frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) = \left(\frac{U_{23}}{R_1} - I_4 \right) \cdot \left(\frac{R_7 \cdot R_1 || R_3 || R_5}{R_6 + R_7 + R_1 || R_3 || R_5} \right)$$

For the internal resistance R_i the ideal voltage source is substituted by its resistance ($=0 \Omega$, so a short-circuit):

$$R_{AB} = R_7 || (R_6 + R_1 || R_3 || R_5)$$

with $R_1 || R_3 || R_5 = 5 \Omega || 10 \Omega || 10 \Omega = 5 \Omega || 5 \Omega = 2.5 \Omega$:

$$U_{AB} = \left(\frac{6.0 \text{ V}}{5.0 \Omega} - 4.2 \text{ A} \right) \cdot \frac{15 \Omega \cdot 2.5 \Omega}{7.5 \Omega + 15 \Omega + 2.5 \Omega} \quad R_{AB} = 15 \Omega || (7.5 \Omega + 2.5 \Omega)$$

dc network analysis, pure resistor network simplification, delta wye transformation, exam ee1 ws2022


Exercise E1 Charging Capacitors
(written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit below (realization) consists of a DC voltage source U , a switch S_1 , a capacitor C , and a resistor R_2 . The voltage across the capacitor is again U at the moment $t_0=0 \text{ s}$ when the switch S_1 is closed. Calculate the voltage $u_c(t_2)$ across the capacitor at $t_2=1 \text{ ms}$ after closing the switch.


Solution: To solve this, first create an equivalent linear voltage source from U , R_1 , and R_2 .

$$U_{eq} = U \cdot \frac{R_2}{R_1 + R_2} \quad R_{eq} = \frac{R_1 \cdot R_2}{R_1 + R_2}$$

On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting R_2 .




The circuit contains a voltage source $U=12\text{ V}$, a switch S_1 , a resistor of $R_1=20\text{ }\Omega$ and a capacitor of $C=100\text{ }\mu\text{F}$. The switch S_2 to an additional consumer R_2 will be considered to be open for the first task. At the moment $t_0=0\text{ s}$ the switch S_1 is closed, the voltage across the capacitor is $u_c(t_0)=0\text{ V}$.



First do not consider the light bulb - it is not connected to the RC circuit. Calculate the point of time t_1 when $u_c(t_1)=0.5 \cdot U$.

Solution



So, here only R_1 and C gives the time constant: $\tau = R_1 \cdot C$

The following formula describes the time course of $u_c(t)$ which has to be $u_c(t_1)=0.5 \cdot U$:

$$u_c(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$$

It has to be rearranged to $(1 - e^{-t/\tau}) = 0.5$. An equivalent linear voltage source can be given with $U_s = \frac{U \cdot R_B}{R_1 + R_B}$ and $R_i = R_1 \parallel R_B$ as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is: $U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U$. The internal resistance is given by substituting the ideal voltage source with its resistance ($R_i = 0\text{ }\Omega$, short-circuit).

$$R_i = R_1 \parallel R_B = 10\text{ }\Omega$$

$$u_c(t_2) = U_s \cdot (1 - e^{-t_2/(R_i \cdot C)}) = \frac{1}{2} \cdot U \cdot (1 - e^{-1\text{ ms}/(10\text{ }\Omega \cdot 100\text{ }\mu\text{F})})$$

charging capacitors, dc network analysis, pure resistor network simplification, delta wye transformation, exam ee1 ws2022

Exercise E4 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)

1. Calculate the open-circuit voltage U_{OC} and the short-circuit current I_{SC} of the circuit shown in the figure. (R and X_1) shall be given.

After analysis, the full bi-dimensional complex impedance Z shall be extracted and given in polar form $Z = |Z| \cdot e^{j\phi}$ where ϕ is the phase angle in degrees. $Z = (2 + j4) \parallel (3 + j5) + 5j\text{ }\Omega$

Solution Calculate the physical values of the two components.

$$C = 103 \text{ } \mu\text{F}$$

$$R = 10 \text{ } \Omega$$

Solution

The current and voltage are in phase once there is only a pure ohmic (= pure real) impedance Z .

Therefore, $\omega C = \frac{1}{\omega L}$ with the same ω . The value of L is $L = \frac{1}{\omega^2 C} = \frac{1}{(4.68 \times 10^3)^2 \cdot 103 \times 10^{-6}} = 0.24 \text{ } \mu\text{H}$

$$Z = R + j(\omega L - \frac{1}{\omega C}) = 10 + j(4.68 \times 10^3 \cdot 0.24 \times 10^{-6} - \frac{1}{4.68 \times 10^3 \cdot 103 \times 10^{-6}})$$

$$Z = 10 + j(1.1232 - 4.68 \times 10^3 \cdot 103 \times 10^{-6}) = 10 + j(1.1232 - 488.04) = 10 - j486.9168 \text{ } \Omega$$

$$|Z| = \sqrt{10^2 + (-486.9168)^2} = 486.92 \text{ } \Omega$$

$$\varphi = \arctan\left(\frac{-486.9168}{10}\right) = -88.54^\circ$$

The absolute value $|Z| = 486.92 \text{ } \Omega$ can be calculated as:

$$|Z| = \frac{U}{I} = \frac{50 \text{ V}}{0.1 \text{ A}} = 500 \text{ } \Omega$$

With the complex part comes the physical value: $L = \frac{1}{\omega^2 C} = \frac{1}{(4.68 \times 10^3)^2 \cdot 103 \times 10^{-6}} = 0.24 \text{ } \mu\text{H}$

$$C = \frac{1}{\omega^2 L} = \frac{1}{(4.68 \times 10^3)^2 \cdot 0.24 \times 10^{-6}} = 103 \text{ } \mu\text{F}$$

The phase φ can be calculated as:

$$\varphi = \arctan\left(\frac{\text{Im}(Z)}{\text{Re}(Z)}\right) = \arctan\left(\frac{-486.9168}{10}\right) = -88.54^\circ$$

complex impedance, exam ee1 ws2022

Exercise E1 Impedances at different Frequencies
 (written test, approx. 18 % of a 60-minute written test, WS2022)

Exercise E1 A series circuit consists of a resistor R_1 and a capacitor C_1 in series. A voltage $U = 50 \text{ V}$ is applied across the circuit. The current $I = 0.1 \text{ A}$ flows through the circuit. The resistor R_1 shall have the same absolute value of the impedance as a capacitor $C_1 = 40 \text{ nF}$ at $f_1 = 4 \text{ MHz}$.

Solution

$$R_1 = 1.00 \text{ } \Omega$$

$$R_2 = 10.0 \text{ } \Omega$$

A series circuit means that the current is constant on every component.

The equivalent impedance for R and L combined is given by:

$$Z = R + j\omega L$$

Parallel circuit means that the voltage is the same on R_1 and C_1 :

$$U = I R_1 = I \frac{1}{j\omega C_1} \Rightarrow R_1 = \frac{1}{j\omega C_1} \Rightarrow R_1 = -j \frac{1}{\omega C_1}$$

Since R_1 and C_1 are in parallel, the resulting current of the parallel circuit is given as:


$$I_{\text{total}} = I_{R_1} + I_{C_1}$$

This circuit is a parallel circuit. The resulting current of the parallel circuit is given as:

$$I_{\text{total}} = I_{R_1} + I_{C_1} = \frac{U}{R_1} + \frac{U}{\frac{1}{j\omega C_1}} = U \left(\frac{1}{R_1} + j\omega C_1 \right)$$

Back to the first formula:

$$R_3 \cdot I_{\text{total}} = U \Rightarrow R_3 = \frac{U}{I_{\text{total}}} = \frac{U}{U \left(\frac{1}{R_1} + j\omega C_1 \right)} = \frac{1}{\frac{1}{R_1} + j\omega C_1}$$



complex impedance, exam ee1 ws2022

From:

<https://wiki.mexle.org/> - **MEXLE Wiki**

Permanent link:

https://wiki.mexle.org/electrical_engineering_and_electronics_1/ws2022_exam?rev=1768172507

Last update: **2026/01/12 00:01**

