

rechnung_betragundphase_umkehrintegrator

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

$U_A = -\int_0^t \frac{1}{R \cdot C} \cdot \frac{dU_E(t)}{dt} + U_{A0} dt$	insert sine function	$U_E(t) = \hat{U}_E \cdot \sin(\omega \cdot t)$
$U_A = -\int_0^t \frac{1}{R \cdot C} \cdot \sin(\omega \cdot t) \cdot \hat{U}_E dt + U_{A0}$	insert root function with limits	$\int_0^t \sin(a \cdot x) dx = [-\frac{1}{a} \cos(a \cdot x)]_0^t$
$U_A = -\frac{1}{R \cdot C} \cdot \hat{U}_E \cdot \int_0^t \cos(\omega \cdot t) dt + U_{A0}$	put constant before integral	
$U_A = \frac{1}{R \cdot C} \cdot \hat{U}_E \cdot \cos(\omega \cdot t) \Big _0^t + U_{A0}$	insert limits	$t_0=0, t_1=t$
$U_A = \frac{\hat{U}_E}{R \cdot C} \cdot (\cos(\omega \cdot t) - \cos(0)) + U_{A0}$		$\cos(0) = 1$
$U_A = \frac{\hat{U}_E}{R \cdot C} \cdot \cos(\omega \cdot t) - \frac{\hat{U}_E}{R \cdot C} + U_{A0}$	multiply	
$U_A = \frac{\hat{U}_E}{R \cdot C} \cdot \cos(\omega \cdot t) - \frac{\hat{U}_E}{R \cdot C} + U_{A0}$	consider the non-cosine terms	
$U_A = \frac{\hat{U}_E}{R \cdot C} \cdot \cos(\omega \cdot t) - \frac{\hat{U}_E}{R \cdot C} + U_{A0}$	This part is independent in time. Since we assume purely sinusoidal quantities, the for the initial voltage of the capacitor must be:	$U_{A0} = \frac{\hat{U}_E}{R \cdot C}$
$U_A = \frac{\hat{U}_E}{R \cdot C} \cdot \cos(\omega \cdot t)$		

From: <https://wiki.mexle.org/> - MEXLE Wiki

Permanent link: https://wiki.mexle.org/circuit_design/rechnung_betragundphase_umkehrintegrator?rev=1632676778

Last update: 2021/09/26 19:19

