

# rechnung\_betragundphase\_umkehrintegrator

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

\$\;\$ \$\;\$	$U_A = -\frac{1}{R \cdot C} \int_0^t U_E(t) dt + U_{A0}$
\$\;\$ \$\;\$	insert sine function: $U_E(t) = \hat{U}_E \sin(\omega t)$
\$\;\$ \$\;\$	$U_A = -\frac{1}{R \cdot C} \int_0^t \hat{U}_E \sin(\omega t) dt + U_{A0}$
\$\;\$ \$\;\$	insert root function with limits $\int_{x_0}^{x_1} \sin(a \cdot x) dx = [-\frac{1}{a} \cos(a \cdot x)]_{x_0}^{x_1}$
\$\;\$ \$\;\$	$U_A = -\frac{1}{R \cdot C} [-\frac{\hat{U}_E}{\omega} \cos(\omega t)]_0^t + U_{A0}$
\$\;\$ \$\;\$	put constant before integral
\$\;\$ \$\;\$	$U_A = \frac{\hat{U}_E}{\omega R \cdot C} [\cos(\omega t)]_0^t + U_{A0}$
\$\;\$ \$\;\$	insert limits: $t_0=0, t_1=t$
\$\;\$ \$\;\$	$U_A = \frac{\hat{U}_E}{\omega R \cdot C} (\cos(\omega t) - \cos(0)) + U_{A0}$
\$\;\$ \$\;\$	$\cos(0) = 1$
\$\;\$ \$\;\$	$U_A = \frac{\hat{U}_E}{\omega R \cdot C} (\cos(\omega t) - 1) + U_{A0}$
\$\;\$ \$\;\$	multiply
\$\;\$ \$\;\$	$U_A = \frac{\hat{U}_E}{\omega R \cdot C} \cos(\omega t) - \frac{\hat{U}_E}{\omega R \cdot C} + U_{A0}$
\$\;\$ \$\;\$	consider the non-cosine terms
\$\;\$ \$\;\$	$U_A = \frac{\hat{U}_E}{\omega R \cdot C} \cos(\omega t) - \frac{\hat{U}_E}{\omega R \cdot C} + U_{A0}$
\$\;\$ \$\;\$	This part is independent in time. Since we assume purely sinusoidal quantities, the initial voltage of the capacitor must be: $U_{C0} = U_{A0} = \frac{\hat{U}_E}{\omega R \cdot C}$
\$\;\$ \$\;\$	$U_A = \frac{\hat{U}_E}{\omega R \cdot C} \cos(\omega t)$
\$\;\$ \$\;\$	
\$\;\$ \$\;\$	

From: <https://wiki.mexle.org/> - MEXLE Wiki

Permanent link: [https://wiki.mexle.org/circuit\\_design/rechnung\\_betragundphase\\_umkehrintegrator?rev=1641770290](https://wiki.mexle.org/circuit_design/rechnung_betragundphase_umkehrintegrator?rev=1641770290)

Last update: 2022/01/10 00:18

