

rechnung_betragundphase_umkehrintegrator

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

\$\;\$ \$\;\$ \$\;\$	$U_A = -\frac{1}{R \cdot C} \int_{t_0}^{t_1} U_E(t) dt + U_{A0}$
\$\;\$ \$\;\$ \$\;\$	insert sine function: $U_E(t) = U_E \cdot \sin(\omega \cdot t)$
\$\;\$ \$\;\$ \$\;\$	$U_A = -\frac{1}{R \cdot C} \int_{t_0}^{t_1} U_E \cdot \sin(\omega \cdot t) dt + U_{A0}$
\$\;\$ \$\;\$ \$\;\$	insert root function with limits $\int_{x_0}^{x_1} \sin(a \cdot x) dx = [-\frac{1}{a} \cdot \cos(a \cdot x)]_{x_0}^{x_1}$
\$\;\$ \$\;\$ \$\;\$	$U_A = -\frac{1}{R \cdot C} \cdot [-\frac{U_E}{\omega} \cdot \cos(\omega \cdot t)]_{t_0}^{t_1} + U_{A0}$
\$\;\$ \$\;\$ \$\;\$	put constant before integral $U_A = \frac{U_E}{\omega \cdot R \cdot C} \cdot \{ \cos(\omega \cdot t) - \cos(0) \} + U_{A0}$
\$\;\$ \$\;\$ \$\;\$	$U_A = \frac{U_E}{\omega \cdot R \cdot C} \cdot \{ \cos(\omega \cdot t) - 1 \} + U_{A0}$
\$\;\$ \$\;\$ \$\;\$	multiply $U_A = \frac{U_E}{\omega \cdot R \cdot C} \cdot \cos(\omega \cdot t) \cdot \{-\frac{U_E}{\omega \cdot R \cdot C}\} + U_{A0}$
\$\;\$ \$\;\$ \$\;\$	consider the non-cosine terms: The blue part is independent in time. We assume purely sinusoidal quantities!
\$\;\$ \$\;\$ \$\;\$	$U_A = \frac{U_E}{\omega \cdot R \cdot C} \cdot \cos(\omega \cdot t) \cdot \{-\frac{U_E}{\omega \cdot R \cdot C}\} + U_{A0}$
\$\;\$ \$\;\$ \$\;\$	$U_{C0} = U_{A0} = \frac{U_E}{\omega \cdot R \cdot C}$
\$\;\$ \$\;\$ \$\;\$	$U_A = \frac{U_E}{\omega \cdot R \cdot C} \cdot \cos(\omega \cdot t)$

From:

<https://wiki.mexle.org/> - **MEXLE Wiki**

Permanent link:

https://wiki.mexle.org/circuit_design/rechnung_betragundphase_umkehrintegrator?rev=1641770698

Last update: **2022/01/10 00:24**

