

rechnung_nichtinvertierender_verstaerker

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

I. Analysis of the Currents

by (2)+(3)	$I_p = I_m = 0$
	therefore, I_p and I_m are defined
by (6)	$I_0 = I_1$
	I_0 is defined, when I_1 is defined
by (7)+(3)	$I_1 - I_2 - 0 = 0$
	$I_1 = I_2 = I_0$
	$I_1 = I_2 = I_0$
	with (8) and (9): $I_{\boxed{}} = \frac{U_{\boxed{}}}{R_{\boxed{}}}$ and (5)
	$\frac{U_1}{R_1} = \frac{U_2}{R_2} = \frac{U_0}{R_1 + R_2}$
	Voltage divider, $I = \text{const.}$
(10)	$U_2 = U_0 \cdot \frac{R_2}{R_1 + R_2}$
	Voltage divider

II. Analysis if the Voltage Amplification

by (0)	$A_V = \frac{U_0}{U_I}$
	$A_V = \frac{U_0}{U_I}$
	with (4): $U_I = U_2 + U_D$
	$A_V = \frac{U_0}{U_2 + U_D}$
	$A_V = \frac{U_0}{U_2 + U_D}$
	with (10): $U_2 = U_0 \cdot \frac{R_2}{R_1 + R_2}$
	$A_V = \frac{U_0}{U_0 \cdot \frac{R_2}{R_1 + R_2} + U_D}$
	$A_V = \frac{U_0}{U_0 \cdot \frac{R_2}{R_1 + R_2} + U_D}$
	with (1)
	$A_V = \frac{U_0}{U_0 \cdot \frac{R_2}{R_1 + R_2} + \frac{U_0}{A_D}}$

	\quad
$\quad\quad\quad$	$\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad$
\quad	$A_V = \frac{U_O}{U_O \cdot \frac{R_2}{R_1 + R_2} + \frac{U_O}{A_D}}$
	\quad
$\quad\quad\quad$	$\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad$
\quad	$A_V = \frac{\text{color{blue}}{U_O}}{\text{color{blue}}{U_O} \cdot \frac{R_2}{R_1 + R_2} + \frac{\text{color{blue}}{U_O}}{A_D}}$
	Expand with $\frac{1}{U_O}$
$\quad\quad\quad$	$\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad$
\quad	$A_V = \frac{1}{\frac{R_2}{R_1 + R_2} + \frac{1}{A_D}}$
	\quad
$\quad\quad\quad$	$\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad$
\quad	$A_V = \frac{1}{\frac{R_2}{R_1 + R_2} + \text{color{blue}}{\frac{1}{A_D}}}$
	with $\frac{1}{A_D} \xrightarrow{A_D \rightarrow \infty} 0$
$\quad\quad\quad$	$\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad$
\quad	$A_V = \frac{1}{\frac{R_2}{R_1 + R_2}}$
	reshaping the fraction
$\quad\quad\quad$	$\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad$
\quad	$A_V = \frac{R_1 + R_2}{R_2}$
	\quad
$\quad\quad\quad$	$\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad\quad$

From: <https://wiki.mexle.org/> - MEXLE Wiki

Permanent link: https://wiki.mexle.org/circuit_design/rechnung_nichtinvertierender_verstaerker?rev=1651877983

Last update: 2022/05/07 00:59

