

# rechnung\_signalzeitverlauf\_umkehrintegrator

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

\$I.\quad\$ At the point \$t\_1\$

$U_{\text{O}}(t_1) = \frac{1}{\tau} \cdot \int_{t_0}^{t_1} U_{\text{I}}(t) dt + U_{\text{O}}(t_0)$	
$U_{\text{O}}(t_1) = -\frac{1}{5 \text{ ms}} \cdot 1 \text{ V} \cdot 10 \text{ ms} + 0 \text{ V}$	
$U_{\text{O}}(t_1) = -\frac{1}{5 \text{ ms}} \cdot 1 \text{ V} \cdot 10 \text{ ms} = -2 \text{ V}$	

\$I.\quad\$ At the point \$t\_2\$

$U_{\text{O}}(t_1) = \frac{1}{\tau} \cdot \int_{t_0}^{t_1} U_{\text{I}}(t) dt + U_{\text{O}}(t_0)$	
$U_{\text{O}}(t_1) = -\frac{1}{5 \text{ ms}} \cdot (-1 \text{ V}) \cdot 10 \text{ ms} + 2 \text{ V} = 0 \text{ V}$	

\$I.\quad\$ At the point \$t\_3\$

$U_{\text{O}}(t_1) = \frac{1}{\tau} \cdot \int_{t_0}^{t_1} U_{\text{I}}(t) dt + U_{\text{O}}(t_0)$	
$U_{\text{O}}(t_1) = -\frac{1}{5 \text{ ms}} \cdot (-2 \text{ V}) \cdot 10 \text{ ms} + 0 \text{ V} = -2 \text{ V}$	

From: <https://wiki.mexle.org/> - **MEXLE Wiki**

Permanent link: [https://wiki.mexle.org/circuit\\_design/rechnung\\_signalzeitverlauf\\_umkehrintegrator](https://wiki.mexle.org/circuit_design/rechnung_signalzeitverlauf_umkehrintegrator)

Last update: **2023/03/28 14:49**

