

rechnung_spannungsfolger

Student Group

| First Name | Surname | Matrikel Nr. |
|------------|---------|--------------|
| | | |
| | | |
| | | |

Table of Contents

I. Analysis of the Currents

| | | |
|-----------------|-----------------|--|
| aus (2+3) | $I_p = I_m = 0$ | Therefore, I_p and I_m are defined |
| aus (3) und (5) | $I_o = I_m = 0$ | By this, I_o is defined |

II. Analysis of the Voltage Amplification

| | | |
|---------|---|---------------------------------------|
| aus (0) | $A_V = \frac{U_A}{U_E}$ | |
| | $A_V = \frac{U_A}{U_A + U_D}$ | mit (4) |
| | $A_V = \frac{U_A}{U_A + U_D}$ | |
| | $A_V = \frac{U_A}{U_A + U_D}$ | with (1) |
| | $A_V = \frac{A_D \cdot U_D}{A_D \cdot U_D + U_D}$ | |
| | $A_V = \frac{A_D \cdot U_D}{A_D \cdot U_D + U_D}$ | |
| | $A_V = \frac{A_D \cdot U_D}{A_D \cdot U_D + U_D}$ | Expand with $\frac{1}{A_D \cdot U_D}$ |
| | $A_V = \frac{A_D \cdot U_D}{A_D \cdot U_D + U_D} \cdot \frac{1}{A_D \cdot U_D}$ | |
| | $A_V = \frac{1}{1 + \frac{1}{A_D}}$ | |
| | $A_V = \frac{1}{1 + \frac{1}{A_D}}$ | with $\frac{1}{A_D} \rightarrow 0$ |
| | $A_V = \frac{1}{1 + 0}$ | |
| | $A_V = \frac{1}{1} = 1$ | |

From:
<https://wiki.mexle.org/> - **MEXLE Wiki**

Permanent link:
https://wiki.mexle.org/circuit_design/rechnung_spannungsfolger?rev=1636906127

Last update: **2021/11/14 17:08**

