

# rechnung\_umkehrintegrator

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

\$\;\$ \$\;\$	$U_A = f(U_E)$
\$\;\$ \$\;\$	with III.
	$\frac{d}{dt} U_A = -\frac{1}{A_D} U_A + \frac{1}{A_D} U_C$
\$\;\$ \$\;\$	$U_A = \frac{1}{A_D} U_C - U_C$
\$\;\$ \$\;\$	with II. and I.: $\frac{1}{A_D} U_C = \frac{1}{A_D} U_C + \frac{1}{A_D} U_C - U_C \rightarrow \infty \rightarrow 0$
	$\frac{d}{dt} U_A = -\frac{1}{A_D} U_A + \frac{1}{A_D} U_C$
\$\;\$ \$\;\$	$U_A = 0 - U_C$
\$\;\$ \$\;\$	with V.: $U_C = \frac{1}{C} \int_{t_0}^{t_1} I_C dt + Q_0(t_0)$
	$\frac{d}{dt} U_A = -\frac{1}{C} \int_{t_0}^{t_1} I_C dt + Q_0(t_0)$
\$\;\$ \$\;\$	$U_A = -\frac{1}{C} \int_{t_0}^{t_1} I_C dt + Q_0(t_0)$
\$\;\$ \$\;\$	with IV.: $I_C = I_R$
	$\frac{d}{dt} U_A = -\frac{1}{C} \int_{t_0}^{t_1} I_R dt + Q_0(t_0)$
\$\;\$ \$\;\$	$U_A = -\frac{1}{C} \int_{t_0}^{t_1} I_R dt + Q_0(t_0)$
\$\;\$ \$\;\$	Factor out
	$\frac{d}{dt} U_A = -\frac{1}{C} \int_{t_0}^{t_1} I_R dt - \frac{Q_0(t_0)}{C}$
\$\;\$ \$\;\$	$U_A = -\frac{1}{C} \int_{t_0}^{t_1} I_R dt - \frac{Q_0(t_0)}{C}$
\$\;\$ \$\;\$	consider the integration constant: $\frac{Q_0(t_0)}{C} = U_C(t_0) = -U_{A0}$
	$\frac{d}{dt} U_A = -\frac{1}{C} \int_{t_0}^{t_1} I_R dt + U_{A0}$
\$\;\$ \$\;\$	$U_A = -\frac{1}{C} \int_{t_0}^{t_1} I_R dt + U_{A0}$
\$\;\$ \$\;\$	with VI. and II.: $I_R = \frac{U_R}{R} = \frac{U_E}{R}$
	$\frac{d}{dt} U_A = -\frac{1}{C} \int_{t_0}^{t_1} \frac{U_E}{R} dt + U_{A0}$
\$\;\$ \$\;\$	$U_A = -\frac{1}{R \cdot C} \int_{t_0}^{t_1} U_E dt + U_{A0}$
\$\;\$ \$\;\$	move constant ahead
	$\frac{d}{dt} U_A = -\frac{1}{R \cdot C} \int_{t_0}^{t_1} U_E dt + U_{A0}$
\$\;\$ \$\;\$	$U_A = -\frac{1}{R \cdot C} \int_{t_0}^{t_1} U_E dt + U_{A0}$
\$\;\$ \$\;\$	insert time constant $\tau = R \cdot C$
	$\frac{d}{dt} U_A = -\frac{1}{\tau} \int_{t_0}^{t_1} U_E dt + U_{A0}$
\$\;\$ \$\;\$	$U_A = -\frac{1}{\tau} \int_{t_0}^{t_1} U_E dt + U_{A0}$
\$\;\$ \$\;\$	

