

# rechnung\_umkehrintegrator

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

\$\;\$ \$\;\$	$U_A = f(U_E)$
\$\;\$ \$\;\$	with III.
	$\dots$
\$\;\$ \$\;\$	$U_A = \text{color{blue}\{-U_D\}} - U_C$
\$\;\$ \$\;\$	with II. and I.: $\text{color{blue}\{U_D\}} = \{ 1 \over A_D \} \cdot U_A \overset{A_D \rightarrow}{\infty} \rightarrow 0$
	$\dots$
\$\;\$ \$\;\$	$U_A = 0 - \text{color{blue}\{U_C\}}$
\$\;\$ \$\;\$	with V.: $\text{color{blue}\{U_C\}} = \{ 1 \over C \} \cdot (\int_{t_0}^{t_1} I_C \, dt + Q_0(t_0))$
	$\dots$
\$\;\$ \$\;\$	$U_A = -\{ 1 \over C \} \cdot (\int_{t_0}^{t_1} \text{color{blue}\{I_C\}} \, dt + Q_0(t_0))$
\$\;\$ \$\;\$	with IV.: $\text{color{blue}\{I_C\}} = I_R$
	$\dots$
\$\;\$ \$\;\$	$U_A = \text{color{blue}\{-\{ 1 \over C \} \cdot (\int_{t_0}^{t_1} I_R \, dt + Q_0(t_0))\}}$
\$\;\$ \$\;\$	Factor out
	$\dots$
\$\;\$ \$\;\$	$U_A = -\{ 1 \over C \} \cdot \int_{t_0}^{t_1} I_R \, dt - \text{color{blue}\{ Q_0(t_0) \over C \}}$
\$\;\$ \$\;\$	integration constant: $\text{color{blue}\{ Q_0(t_0) \over C \}} = U_C(t_0) = -U_{A0}$
	$\dots$
\$\;\$ \$\;\$	$U_A = -\{ 1 \over C \} \cdot \int_{t_0}^{t_1} \text{color{blue}\{I_R\}} \, dt + U_{A0}$
\$\;\$ \$\;\$	with VI. and II.: $\text{color{blue}\{I_R\}} = \{ U_R \over R \} = \{ U_E \over R \}$
	$\dots$
\$\;\$ \$\;\$	$U_A = -\{ 1 \over C \} \cdot \int_{t_0}^{t_1} \text{color{blue}\{1 \over R\}} \cdot U_E \, dt + U_{A0}$
\$\;\$ \$\;\$	move constant ahead
	$\dots$
\$\;\$ \$\;\$	$U_A = -\{ 1 \over \{R \cdot C\}} \cdot \int_{t_0}^{t_1} U_E \, dt + U_{A0}$
\$\;\$ \$\;\$	insert time constant $\tau = R \cdot C$
	$\dots$
\$\;\$ \$\;\$	$U_A = -\{ 1 \over \tau \} \cdot \int_{t_0}^{t_1} U_E \, dt + U_{A0}$
\$\;\$ \$\;\$	

