

# rechnung\_nichtinvertierender\_verstaerker

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

$\text{I.}$  Analysis of the Currents

by (2)+(3)	$I_p = I_m = 0$
	therefore, $I_p$ and $I_m$ are defined
by (6)	$I_O = I_1$
	$I_O$ is defined, when $I_1$ is defined
by (7)+(3)	$I_1 - I_2 - 0 = 0$
	$I_1 = I_2 = I_O$
	$I_1 = I_2 = I_O$
	$I_1 = I_2 = I_O$
	with (8) and (9): $I_{\boxed{}} = \frac{U_{\boxed{}}}{R_{\boxed{}}}$ and (5)
	$\frac{U_1}{R_1} = \frac{U_2}{R_2} = \frac{U_O}{R_1 + R_2}$
	Voltage divider, $I = \text{const.}$
(10)	$U_2 = U_O \cdot \frac{R_2}{R_1 + R_2}$
	Voltage divider

$\text{II.}$  Analysis of the Voltage Amplification

by (0)	$A_V = \frac{U_O}{U_I}$
	$A_V = \frac{U_O}{U_I}$
	with (4): $U_I = U_2 + U_D$
	$A_V = \frac{U_O}{U_2 + U_D}$
	$A_V = \frac{U_O}{U_2 + U_D}$
	with (10): $U_2 = U_O \cdot \frac{R_2}{R_1 + R_2}$
	$A_V = \frac{U_O}{U_O \cdot \frac{R_2}{R_1 + R_2} + U_D}$
	$A_V = \frac{U_O}{U_O \cdot \frac{R_2}{R_1 + R_2} + U_D}$
	$A_V = \frac{U_O}{U_O \cdot \frac{R_2}{R_1 + R_2} + U_D}$
	with (1)

$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$	$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$
$\$ \backslash \text{quad} \$$	$\$ A_{\text{V}} = \frac{U_{\text{O}}}{O} \cdot \frac{R_2}{R_1 + R_2} + \text{color}\{\text{blue}\}\{\frac{U_{\text{O}}}{A_{\text{D}}}\} \$$
	$\$ \backslash \text{quad} \$$
$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$	$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$
$\$ \backslash \text{quad} \$$	$\$ A_{\text{V}} = \frac{U_{\text{O}}}{O} \cdot \frac{R_2}{R_1 + R_2} + \frac{U_{\text{O}}}{A_{\text{D}}} \$$
	$\$ \backslash \text{quad} \$$
$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$	$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$
$\$ \backslash \text{quad} \$$	$\$ A_{\text{V}} = \frac{\text{color}\{\text{blue}\} U_{\text{O}}}{O} \cdot \frac{R_2}{R_1 + R_2} + \frac{\text{color}\{\text{blue}\} U_{\text{O}}}{A_{\text{D}}} \$$
	Expand with $\frac{1}{U_{\text{O}}}$
$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$	$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$
$\$ \backslash \text{quad} \$$	$\$ A_{\text{V}} = \frac{1}{\frac{R_2}{R_1 + R_2} + \frac{1}{A_{\text{D}}}} \$$
	$\$ \backslash \text{quad} \$$
$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$	$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$
$\$ \backslash \text{quad} \$$	$\$ A_{\text{V}} = \frac{1}{\frac{R_2}{R_1 + R_2} + \text{color}\{\text{blue}\} \frac{1}{A_{\text{D}}}} \$$
	with $\frac{1}{A_{\text{D}}} \rightarrow 0$
$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$	$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$
$\$ \backslash \text{quad} \$$	$\$ A_{\text{V}} = \frac{1}{\frac{R_2}{R_1 + R_2}} \$$
	reshaping the fraction
$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$	$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$
$\$ \backslash \text{quad} \$$	$\$ A_{\text{V}} = \frac{R_1 + R_2}{R_2} \$$
	$\$ \backslash \text{quad} \$$
$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$	$\$ \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \backslash \text{quad} \$$

From: <https://wiki.mexle.org/> - **MEXLE Wiki**

Permanent link: [https://wiki.mexle.org/circuit\\_design/rechnung\\_nichtinvertierender\\_verstaerker](https://wiki.mexle.org/circuit_design/rechnung_nichtinvertierender_verstaerker)

Last update: **2025/12/13 21:54**

