

task_pdkggtyexxy1ktu3_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E6 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022) 2

complex impedance, exam ee1 WS2022

Exercise E6 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)

Exercise E6: A series circuit consists of a resistor \$R_1\$ with \$R_1 = 1.00 \text{ } \Omega\$, a capacitor \$C_1\$ with \$C_1 = 40 \text{ nF}\$, and an AC voltage source \$U_0 = 4.7 \text{ } \mu\text{V}\$ at \$f = 450 \text{ kHz}\$. The current \$I\$ through the resistor \$R_1\$ shall have the same absolute value of the impedance as a capacitor \$C_2\$ with \$C_2 = 1.0 \text{ nF}\$ at \$f = 4 \text{ MHz}\$. Determine the value of \$C_2\$.

Solution

$R_1 = 1.00 \text{ } \Omega$

$R_2 = 10.0 \text{ } \Omega$

A series circuit means that the current is constant on every component.

The equivalent impedance for \$R\$ and \$L\$ combined is given by $Z = R + j\omega L$

Parallel circuit means that the voltage is the same on \$R_2\$ and \$C_2\$

$\frac{1}{Z} = \frac{1}{R_2} + \frac{1}{j\omega C_2}$

$Z = \frac{R_2 \cdot j\omega C_2}{j\omega C_2 R_2 + 1}$

$|Z| = \frac{R_2 \cdot \omega C_2}{\sqrt{1 - (R_2 \omega C_2)^2}}$

$|Z| = \frac{10 \cdot 40 \cdot 10^{-9} \cdot 4 \cdot 10^6}{\sqrt{1 - (10 \cdot 40 \cdot 10^{-9} \cdot 4 \cdot 10^6)^2}}$

$|Z| = \frac{1.6}{\sqrt{1 - 0.256}}$

$|Z| = \frac{1.6}{\sqrt{0.744}}$

$|Z| = 1.87 \text{ } \Omega$

Therefore, the resulting current of the parallel circuit is given as:

$I = \frac{U_0}{|Z|} = \frac{4.7 \cdot 10^{-6}}{1.87} = 2.51 \text{ mA}$

Back to the first formula: $R_3 \cdot |I| = |Z| \cdot |I|$

$R_3 = |Z| = 1.87 \text{ } \Omega$

$R_3 = \frac{1}{\omega C_2} = \frac{1}{2\pi \cdot 4 \cdot 10^6 \cdot C_2}$

$C_2 = \frac{1}{2\pi \cdot 4 \cdot 10^6 \cdot 1.87} = 21.1 \text{ nF}$

From: <https://wiki.mexle.org/> - MEXLE Wiki

Permanent link: https://wiki.mexle.org/ee1/task_pdkggyexxy1ktu3_with_calculation

Last update: 2023/04/02 00:27

