

# task\_yh4srwxu1bo1rddy4\_with\_calculation

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

Exercise E11 Magnetic Circuit (written test, approx. 10 % of a 120-minute written test, SS2024) .....	2
---	---

resonance, impedance, resonant circuit, exam ee2 SS2024

**Exercise E11 Magnetic Circuit**

(written test, approx. 10 % of a 120-minute written test, SS2024)

2. For a series RLC circuit with a voltage source  $U_C = 100 \text{ V}$ , a resistor  $R = 5 \text{ }\Omega$ , an inductor  $L = 1.6 \text{ nH}$ , and a capacitor  $C = 10 \text{ nF}$ . What is the resonance frequency  $f_r$  and the impedance  $Z_{RLC}$  at resonance? (Phase and magnitude)

Path

- $U_C = 100 \text{ V}$
- $f_r = 9.17 \text{ MHz}$
- $Z_{RLC}(f_r) = 83.9 \text{ }\Omega$
- $Z_{RLC}(f_r) = 83.9 \text{ }\Omega$

The formula for the resonance frequency  $f_r$  is:  $f_r = \frac{1}{2\pi\sqrt{LC}}$

The voltage across the ideal capacitor is  $U_C = U \cdot Q = 100 \text{ V} \cdot 10 = 1000 \text{ V}$

The impedance at resonance is  $Z_{RLC} = R = 5 \text{ }\Omega$

A given capacitor shall have the following values:

- $C = 10 \text{ nF}$
- $R = 20 \text{ m}\Omega$
- $L = 1.6 \text{ nH}$

1. What is the impedance  $Z_{RLC}$  of this real capacitor for  $f_0 = 44 \text{ MHz}$ ? (Phase and magnitude)

Path

The impedance is based on the resistance  $R$  and the reactance  $X_{LC} = j(X_L - X_C)$ :

$$\underline{Z}_{RLC} = R + j(\omega L - \frac{1}{\omega C}) = R + j(2\pi f \cdot L - \frac{1}{2\pi f \cdot C})$$

The reactive part is  $X_{LC} = 2\pi f \cdot L - \frac{1}{2\pi f \cdot C}$

$$C) \quad \omega = 2\pi \cdot 44 \cdot 10^6 \text{ MHz} \cdot 1.6 \cdot 10^{-9} \text{ H} - \frac{1}{2\pi \cdot 10^6 \text{ MHz} \cdot 10 \cdot 10^{-9} \text{ F}} \quad \omega = +0.08062... \omega$$

To get the magnitude of the impedance  $|Z_{RLC}|$  one can use the Pythagorean Theorem: 
$$|Z_{RLC}| = \sqrt{R^2 + X_{LC}^2} = \sqrt{(0.020 \omega)^2 + (0.08062... \omega)^2} = 0.0830... \omega$$

For the phase  $\varphi$  the  $\arctan$  can be applied: 
$$\varphi = \arctan\left(\frac{X_{LC}}{R}\right) = \arctan\left(\frac{0.08062... \omega}{0.020 \omega}\right) = 1.3276... \hat{=} +76^\circ$$

From:

<https://wiki.mexle.org/> - **MEXLE Wiki**

Permanent link:

[https://wiki.mexle.org/ee2/task\\_yh4srwxu1bo1rdy4\\_with\\_calculation](https://wiki.mexle.org/ee2/task_yh4srwxu1bo1rdy4_with_calculation)

Last update: **2024/07/15 23:54**

