

task_abh4vhlgczdbni37_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E22 Signal Analysis (written test, approx. 6 % of a 120-minute written test, SS2021)
..... 2

signal analysis, RMS, exam ee2 SS2021

Exercise E22 Signal Analysis**(written test, approx. 6 % of a 120-minute written test, SS2021)**

A) Determine the effective value of the signal $i(t)$ and the phase angle φ (in degrees) (independent quantities are available in the consumer arrow system. (hard)

- $u(t) = 50 \sqrt{2} \cos(6000 t + 4)$ V

- $i(t) = 30 \sqrt{2} \sin(6000 t + 5)$ A

Result

a) Determine the amplitude values \hat{U} , \hat{I} and the RMS values U , I

- $f = 955$ Hz

- $\hat{U} = 50 \sqrt{2}$ V

The frequency can be derived by the term in the sine function: $\omega = 6000$ rad/s

- $\hat{I} = 30 \sqrt{2}$ A

- $f = \frac{\omega}{2\pi} = \frac{6000}{2\pi} = 954.93 \dots$ Hz

RMS values:

For the phase φ , we have to subtract φ_i from φ_u .

But to get these values, both the $u(t)$ and $i(t)$ need to have the same sinusoidal function! Therefore:

- For the RMS values of sinusoidal functions the amplitudes have to be multiplied with $\frac{1}{\sqrt{2}}$

- $U = \frac{\hat{U}}{\sqrt{2}} = 35.4$ V

By this we get for φ
$$\varphi = \varphi_u - \varphi_i = 4 - 5 = -1$$

Converted in degree:
$$\varphi = -1 \cdot \frac{360^\circ}{2\pi} = -32.7042 \dots^\circ$$

From:

<https://wiki.mexle.org/> - MEXLE Wiki

Permanent link:

https://wiki.mexle.org/electrical_engineering_and_electronics/task_abh4vhlgczbni37_with_calculation

Last update: 2024/07/04 02:36

