

task_pdkggtyexxy1ktu3_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E6 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022) 2

complex impedance, exam ee1 WS2022

Exercise E6 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)

Exercise E6: A series circuit consists of a resistor \$R_1\$ with \$R_1 = 100 \text{ } \Omega\$, a capacitor \$C_1\$ with \$C_1 = 40 \text{ nF}\$, and an AC voltage source \$U_1\$ with \$U_1 = 10 \text{ V}\$ and \$f = 4 \text{ MHz}\$. A parallel circuit consists of a resistor \$R_2\$ with \$R_2 = 470 \text{ } \Omega\$, a capacitor \$C_2\$ with \$C_2 = 4.7 \text{ } \mu\text{H}\$, and an AC voltage source \$U_2\$ with \$U_2 = 10 \text{ V}\$ and \$f = 450 \text{ kHz}\$. The current \$I_1\$ through \$R_1\$ shall have the same absolute value of the impedance as a capacitor \$C_3\$ with \$C_3 = 40 \text{ nF}\$ at \$f_1 = 4 \text{ MHz}\$.

Solution

$$R_1 = 100 \text{ } \Omega$$

$$R_2 = 470 \text{ } \Omega$$

A series circuit means that the current is constant on every component.
 The equivalent impedance for \$R\$ and \$L\$ combined is given by
$$Z = R + j\omega L$$

 Parallel circuit means that the voltage is the same on \$R_2\$ and \$C_2\$
$$Z = \frac{R_2 \cdot X_{C2}}{R_2 + X_{C2}}$$

 Since \$X_{C2}\$ is perpendicular to \$R_2\$, this can be simplified to
$$Z = \frac{R_2 \cdot X_{C2}}{\sqrt{R_2^2 + X_{C2}^2}}$$

 The resulting current of the parallel circuit is given as:
$$I_2 = \frac{U_2}{Z}$$

 This can be rearranged to
$$I_2 = \frac{U_2 \cdot \sqrt{R_2^2 + X_{C2}^2}}{R_2 \cdot X_{C2}}$$

 Back to the first formula:
$$I_1 \cdot Z = I_2 \cdot Z$$

$$I_1 \cdot (R_1 + j\omega L) = I_2 \cdot \frac{R_2 \cdot X_{C2}}{\sqrt{R_2^2 + X_{C2}^2}}$$

From: <https://wiki.mexle.org/> - MEXLE Wiki

Permanent link: https://wiki.mexle.org/electrical_engineering_and_electronics/task_pdkggyexxy1ktu3_with_calculation

Last update: 2023/04/02 00:27

