

Mesh set

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Mesh set

Set of nodes

2

3

Mesh set

In every closed circuit and every mesh of the network, the sum of all voltages is zero!
Set the voltage on the power supply to 12 V and measure this voltage precisely using a multimeter. Set up the measuring circuit shown in [figure 1](#).




Fig. 1: Mesh-set Add the voltage arrows and measure U , U_{1} und U_{2} :

U	U_{1}	U_{2}

Tab. 1: Mesh set voltage measurement

What is the mesh set here?

Check the formula with the measured values:

The resistors R_1 and R_2 connected in series form a voltage divider. What is the ratio between the voltages U_1 and U_2 ? $\frac{U_1}{U_2} =$

Set of nodes

At each junction point, the sum of all incoming and outgoing currents is equal to zero!

Set the voltage on the power supply to 12 V and measure the voltage accurately with a multimeter. In the first step, set up the measuring circuit shown in [figure 2](#):




Fig. 2: Node-set circuit 1 Draw the arrows for the directions of currents I_1 and I_2 in [figure 3](#). The DC current measurement range must be set on both multimeter using the rotary switch. Then measure currents I_1 and I_2 and enter the measured values in [table 2](#).




Fig. 3: Node-set circuit 2 What is the relationship between currents I_1 and I_2 ? $\frac{I_1}{I_2} =$ Switch the power supply back on and measure the current I . Enter its value in [table 2](#).

\$\$\$	$I_{\rm 1}$	$I_{\rm 2}$

Tab. 2: Node set current measurement

Determine the node set for node K and check its validity.

Using the measured values for resistors $R_{\rm 1}$, $R_{\rm 2}$, and $R_{\rm 3}$, calculate the total resistance $R_{\rm KP}$:

Using the calculated value $R_{\rm KP}$, check the measured value of the total current:
 $I=\frac{U}{R_{\rm KP}} =$

From:
<https://wiki.mexle.org/> - **MEXLE Wiki**

Permanent link:
https://wiki.mexle.org/mexlefirst_public/mesh-set

Last update: **2026/07/31 16:19**

