

# task\_pdkggtyexxy1ktu3\_with\_calculation

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

Exercise E8 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022) .....	2
--	---

complex impedance, exam ee1 WS2022

Exercise E8 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)

Exercise E8: A series circuit contains a resistor \$R\_1\$ with \$R\_1 = 1.00 \text{ } \Omega\$, a capacitor \$C\_1\$ with \$C\_1 = 40 \text{ nF}\$, and an AC voltage source \$U\_0 = 4.7 \text{ } \mu\text{V}\$ with a frequency \$f = 450 \text{ kHz}\$. The magnitude of the impedance of the resistor \$R\_1\$ shall have the same absolute value of the impedance as a capacitor \$C\_2\$ with \$C\_2 = 1.0 \text{ nF}\$ at \$f\_2 = 4 \text{ MHz}\$. Determine the absolute value of the impedance of the capacitor \$C\_2\$ at \$f\_2 = 4 \text{ MHz}\$.

Solution

$R_1 = 1.00 \text{ } \Omega$

$R_2 = 10.0 \text{ } \Omega$

A series circuit means that the current is constant on every component.

The equivalent impedance for \$R\$ and \$L\$ combined is given by  $Z = R + j\omega L$

Parallel circuit means that the voltage is the same on \$R\_2\$ and \$C\_2\$

$\frac{1}{Z} = \frac{1}{R_2} + \frac{1}{j\omega C_2}$

$Z = \frac{R_2 \cdot j\omega C_2}{j\omega C_2 R_2 + 1}$

$|Z| = \frac{R_2 \cdot \omega C_2}{\sqrt{1 - (R_2 \omega C_2)^2}}$

$|Z| = \frac{R_2 \cdot \omega C_2}{\sqrt{1 - (R_2 \omega C_2)^2}}$

Therefore the resulting current of the parallel circuit is given as:

$I = \frac{U_0}{|Z|} = \frac{U_0 \sqrt{1 - (R_2 \omega C_2)^2}}{R_2 \cdot \omega C_2}$

This can be rearranged to  $R_2 \cdot \omega C_2 = \frac{U_0}{I \sqrt{1 - (R_2 \omega C_2)^2}}$

$(R_2 \cdot \omega C_2)^2 = \frac{U_0^2}{I^2 (1 - (R_2 \omega C_2)^2)}$

Back to the first formula:  $R_3 \cdot |Z| = |X_C| \cdot |Z|$

$R_3 = |X_C| = \frac{1}{\omega C_2} = \frac{1}{2\pi \cdot 4 \cdot 10^6 \cdot C_2}$

From: <https://wiki.mexle.org/> - MEXLE Wiki

Permanent link: [https://wiki.mexle.org/ee1/task\\_pdkggyexxy1ktu3\\_with\\_calculation](https://wiki.mexle.org/ee1/task_pdkggyexxy1ktu3_with_calculation)

Last update: 2023/04/02 00:27

