

# task\_0j7accfimmemytq9\_with\_calculation

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

Exercise E7 Cylindrical Coil (written test, approx. 6 % of a 120-minute written test, SS2021)	2
-----------------------------------------------------------------------------------------------	---

magnetostatic, flux density, magnetic field strength, coil, flux, exam ee2 SS2021

### Exercise E7 Cylindrical Coil (written test, approx. 6 % of a 120-minute written test, SS2021)

A) The magnetic flux (2 points) information is given:

Result

- Length  $l = 30 \text{ cm}$ ,

Path Winding diameter  $d = 390 \text{ mm}$ ,

- Number of windings  $N = 240$ ,
- Current in the conductor  $I = 500 \text{ mA}$ .

Material inside: Air

$$\mu_0 = 4\pi \cdot 10^{-7} \text{ Vs/Am}$$

The magnetic field strength  $H = \mu_r \mu_0^{-1} \cdot B$

The proportion of the magnetic voltage outside the coil can be neglected. Determine the following for the inside of the coil:

$$\Phi = B \cdot A = \mu_0 \cdot N \cdot I \cdot \frac{l}{d}$$

a) the magnetic field strength (2 points)

$$H = \frac{N \cdot I}{l} = \frac{240 \cdot 0.5 \text{ A}}{0.3 \text{ m}} = 400 \text{ A/m} \quad \mu = 0.0005026 \text{ Vs/m}^2$$

$$A = \pi r^2 = \pi \left( \frac{d}{2} \right)^2$$

path

$$\Phi = B \cdot A = \mu_0 \cdot N \cdot I \cdot \frac{l}{d} \cdot \pi \left( \frac{d}{2} \right)^2$$

$$\Phi = 0.0005026 \text{ Vs/m}^2 \cdot \pi \left( \frac{0.39 \text{ m}}{2} \right)^2 \cdot 400 \text{ A/m} = 0.0006004 \text{ Vs}$$

$$H = \frac{240 \cdot 0.5 \text{ A}}{0.3 \text{ m}} = 400 \text{ A/m}$$

From:

<https://wiki.mexle.org/> - MEXLE Wiki

Permanent link:

[https://wiki.mexle.org/ee2/task\\_0j7accfimmemytq9\\_with\\_calculation](https://wiki.mexle.org/ee2/task_0j7accfimmemytq9_with_calculation)

Last update: 2024/07/03 08:55

