

task_7el8zljglaazxtw_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E1 Series Resonant Circuit (written test, approx. 10 % of a 120-minute written test, SS2022)	2
---	---

resonant circuit, exam ee2 SS2022

Exercise E1 Series Resonant Circuit
(written test, approx. 10 % of a 120-minute written test, SS2022)

2. What is the resonance frequency of a series resonant circuit with an inductor of inductance L and a capacitor of capacitance C ?


At this resonance frequency, the impedance of the circuit would be X_{RLC} .

Which value would C have for the given f_0 ?

- Path
- $C = 10 \text{ nF}$
 - $R = 10 \text{ } \Omega$
 - $X_{RLC} = 250 \text{ } \Omega$
 - $L = 60 \text{ } \mu\text{H}$
 - $R = 10 \text{ } \Omega$

The resonance frequency is given as $f_0 = \frac{1}{2\pi\sqrt{LC}}$
 $f_0 = \frac{1}{2\pi\sqrt{60 \cdot 10^{-12} \cdot C}}$
 That is, the impedance of the circuit X_{RLC} has to be set equal to X_{RLC}
 $X_{RLC} = R + j\omega L - \frac{j}{\omega C}$
 At resonance, the impedance is purely real.

With values $C = \frac{1}{2\pi \cdot 100 \cdot 10^6 \cdot 10.6 \cdot 10^{-9}}$



1. What is the impedance Z_{RLC} of this real capacitor for $f_0 = 100 \text{ MHz}$? (Phase and magnitude)

Path

The impedance Z_{RLC} is given by: $Z_{RLC} = R + j\omega L - \frac{j}{\omega C}$
 $Z_{RLC} = R + j\omega L - \frac{j}{\omega C}$
 $Z_{RLC} = R + j\omega L - \frac{j}{\omega C}$
 Putting in the numbers, only for the reactive part X_{LC} :
 $X_{LC} = 2\pi \cdot 100 \cdot 10^6 \cdot 60 \cdot 10^{-12} - \frac{1}{2\pi \cdot 100 \cdot 10^6 \cdot 10 \cdot 10^{-9}}$
 $X_{LC} = -121.45 \text{ m}\Omega$

With the real and imaginary parts, we can derive the magnitude and phase:

$$X_{RLC} = \sqrt{R^2 + X_{LC}^2} \quad \text{and} \quad \sqrt{(88 \text{ m}\Omega)^2 + (-121.45 \text{ m}\Omega)^2} = 150.0... \text{ m}\Omega$$

$$\varphi = \arctan\left(\frac{X_{LC}}{R}\right) = \arctan\left(\frac{-121.45 \text{ m}\Omega}{88 \text{ m}\Omega}\right) = -0.9437... = -54.07...^\circ$$

From:
<https://wiki.mexle.org/> - MEXLE Wiki

Permanent link:
https://wiki.mexle.org/ee2/task_7e18zljglaazxtw_with_calculation?rev=1720138686

Last update: **2024/07/05 02:18**

