

# task\_9xy69axg3gi3nr26\_with\_calculation

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

Exercise E1 Complex series circuit (written test, approx. 8 % of a 120-minute written test, SS2021) ..... 2

## complex voltage divider, exam ee2 SS2021

### Exercise E1 Complex series circuit (written test, approx. 8 % of a 120-minute written test, SS2021)

A) Determine the complex impedance  $\underline{Z}_C$  of the series circuit (beginning at  $\omega = 40 \text{krad/s}$ ) shall be given. Pay attention to the correct dimensioning.

a) Determine the complex impedance  $\underline{Z}_C$ .

Result

$$\underline{Z}_C = -j \cdot 804 \text{ } \Omega$$

Path

The complex impedance  $\underline{Z}_C$  is given as

$$\underline{Z}_C = \frac{1}{j \cdot 2\pi \cdot f \cdot C} = \frac{-j}{2\pi \cdot 40 \cdot 10^3 \text{ Hz} \cdot 4.95 \cdot 10^{-9} \text{ F}} = -j \cdot 803.81... \text{ } \Omega$$

From:

<https://wiki.mexle.org/> - MEXLE Wiki

Permanent link:

[https://wiki.mexle.org/ee2/task\\_9xy69axg3gi3nr26\\_with\\_calculation?rev=1720046030](https://wiki.mexle.org/ee2/task_9xy69axg3gi3nr26_with_calculation?rev=1720046030)

Last update: 2024/07/04 00:33

