

task_9xy69axg3gi3nr26_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E1 Complex series circuit (written test, approx. 8 % of a 120-minute written test, SS2021)	2
---	---

complex voltage divider, exam ee2 SS2021

**Exercise E1 Complex series circuit
(written test, approx. 8 % of a 120-minute written test, SS2021)**

A) Determine the complex impedance \underline{Z} of the series circuit (beginning at $\omega = 40$ rad/s) shall be given. Pay attention to the correct dimensioning.

a) Determine the complex impedance \underline{Z}_C .

Result

$$\underline{Z}_C = -j \cdot 804 \text{ } \Omega$$

Path

The complex impedance \underline{Z}_C is given as
$$\underline{Z}_C = \frac{1}{j \cdot 2\pi \cdot f \cdot C} = \frac{-j}{2\pi \cdot 40 \cdot 10^3 \text{ Hz} \cdot 4.95 \cdot 10^{-9} \text{ F}} = -j \cdot 803.81... \text{ } \Omega$$

Based on the diagram: $\underline{Z} = 828 \text{ } \Omega$

From:

<https://wiki.mexle.org/> - MEXLE Wiki

Permanent link:

https://wiki.mexle.org/ee2/task_9xy69axg3gi3nr26_with_calculation?rev=1720046737

Last update: 2024/07/04 00:45

