

task_ljxf80q7vxywehqf_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E13 Self-Induction (written test, approx. 8 % of a 120-minute written test, SS2024)	2
--	---

induction, exam ee2 SS2024

Exercise E13 Self-Induction

(written test, approx. 8 % of a 120-minute written test, SS2024)

2. Determine the time of a 30 voltagerms the coil radius of 2 cm and 500 turns.
 Result: The current through the coil changes linearly from 0 A to 3 A in 0.02 ms.
 The arrangement is located in air ($\mu_r=1$).
 Path

$$\mu_0 = 4\pi \cdot 10^{-7} \text{ Vs/Am}$$

$$U_{\text{ind}} = -L \cdot \frac{\Delta I}{\Delta t} \approx -1.32 \text{ V}$$

.. Calculate the (self-)inductance of the coil.

For the linear change of the current the formula of the induced voltage can also be linearized:
$$u_{\text{ind}} = -L \cdot \frac{\Delta I}{\Delta t} \approx -1.32 \cdot 10^{-3} \cdot \frac{3 \text{ A}}{0.02 \cdot 10^{-3} \text{ s}}$$

The formula for the induction of a long coil is:
$$L = \mu_0 \mu_r \cdot N^2 \cdot \frac{A}{l} = 4\pi \cdot 10^{-7} \text{ Vs/Am} \cdot (500)^2 \cdot \frac{\pi \cdot (2 \cdot 10^{-2} \text{ m})^2}{2 \cdot 10^{-2} \text{ m}}$$

From:

<https://wiki.mexle.org/> - MEXLE Wiki

Permanent link:

https://wiki.mexle.org/ee2/task_ljxf80q7vxywehqf_with_calculation

Last update: **2024/07/15 22:23**

