

# task\_70jg4yzznocarsq\_with\_calculation

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

Exercise E1.1 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022) .....	2
--	---

temperature dependent resistance, power, heat, exam ee1 WS2022

**Exercise E1.1 Temperature-dependent Resistance  
(written test, approx. 6 % of a 60-minute written test, WS2022)**

A refrigerator exhibits a temperature sensitive temperature coefficient of resistance. The circuit has a resistance of  $10 \text{ k}\Omega$  at  $25^\circ\text{C}$ . Its temperature coefficients are:  $\alpha = 0.01 \text{ } \frac{1}{\text{K}}$  and  $\beta = 71 \cdot 10^{-6} \text{ } \frac{1}{\text{K}^2}$

**Result**  
The temperature inside the refrigeration system can reach down to  $-40^\circ\text{C}$ .

Calculate the resistance of the thermostat at  $-40^\circ\text{C}$ .

**Resistance of the resistor**  $P = U \cdot I$  and  $P = \frac{U^2}{R}$  and  $Q = P \cdot t$ . Therefore, a solution is to **light heat** up the refrigeration system.  
Therefore, with constant  $U$  and increasing  $R$  the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2)$$

with  $\Delta T = T_{\text{end}} - T_{\text{start}}$

$$R = 10 \text{ k}\Omega \cdot (1 + 0.01 \cdot (-40^\circ\text{C} - 25^\circ\text{C}) + 71 \cdot 10^{-6} \cdot (-40^\circ\text{C} - 25^\circ\text{C})^2)$$

From: <https://wiki.mexle.org/> - MEXLE Wiki

Permanent link: [https://wiki.mexle.org/electrical\\_engineering\\_1/task\\_70jig4yzznocarsq\\_with\\_calculation?rev=1680093916](https://wiki.mexle.org/electrical_engineering_1/task_70jig4yzznocarsq_with_calculation?rev=1680093916)

Last update: 2023/03/29 14:45

