

task_70jgg4yzznocarsq_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E1.1 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)	2
--	---

temperature dependent resistance, power, heat, exam ee1 WS2022

**Exercise E1.1 Temperature-dependent Resistance
(written test, approx. 6 % of a 60-minute written test, WS2022)**

A refrigerator exhibits a temperature sensitive temperature coefficient of resistance. The filament has a resistance of $10 \text{ k}\Omega$ at 25°C . Its temperature coefficients are: $\alpha = 0.01 \text{ } ^\circ\text{C}^{-1}$ and $\beta = 71 \times 10^{-6} \text{ } ^\circ\text{C}^{-2}$.

Calculate the resistance of the filament at -40°C .

Result: The temperature inside the refrigeration system can reach down to -40°C .

Calculate the resistance of the filament at -40°C .

Resistance of the resistor R depends on the current I and generated heat. Therefore, a solution is to heat up the refrigeration system.

Therefore, with constant U and increasing R the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2)$$

$$R = 10 \text{ k}\Omega \cdot (1 + 0.01 \cdot (-40 - 25) + 71 \cdot 10^{-6} \cdot (-40 - 25)^2)$$

From: <https://wiki.mexle.org/> - MEXLE Wiki

Permanent link: https://wiki.mexle.org/electrical_engineering_1/task_70jig4yzznocarsq_with_calculation?rev=1680105730

Last update: 2023/03/29 18:02

