

task_bln2sqhr55mlxrj3_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E1 Conversion: Vacuum Cleaner	2
--	---

[conversion](#), [power](#), [energy](#), [chapter1](#) 1

Exercise E1 Conversion: Vacuum Cleaner

Your $18\text{~}\{\text{V}\}$ vacuum cleaner is equipped with a $4.0\text{~}\{\text{Ah}\}$ battery, it runs $15\text{~}\{\text{min}\}$.

How much electrical power is consumed by the motor during this time on average?

Solution: $288\text{~}\{\text{W}\}$

$$W = 18\text{~}\{\text{V}\} \cdot 4.0\text{~}\{\text{Ah}\} = 72\text{~}\{\text{Wh}\} \\ t = 15\text{~}\{\text{min}\} = 0.25\text{~}\{\text{h}\} \\ P = \frac{W}{t} = \frac{72\text{~}\{\text{Wh}\}}{0.25\text{~}\{\text{h}\}} = 288\text{~}\{\text{W}\}$$

From:
<https://wiki.mexle.org/> - MEXLE Wiki

Permanent link:
https://wiki.mexle.org/electrical_engineering_1/task_bln2sqhr55mlxjr3_with_calculation?rev=1680517559

Last update: 2023/04/03 12:25

