

task_jti0uzudcmg4u22t_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E1.1 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)	2
---	---

complex impedance, exam ee1 WS2022

Exercise E1.1 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)

2. Calculate the phasor voltage \underline{U} and the current \underline{I} in the circuit shown in the figure. The components (R and X_L) shall be given.

After analysis, the full width dimensioned phasor voltage \underline{U} and current \underline{I} in phasor notation shall be given. $\underline{U} = \sqrt{2} \cdot U_{eff} \cdot e^{j(\varphi_U - \omega t)}$ and $\underline{I} = \sqrt{2} \cdot I_{eff} \cdot e^{j(\varphi_I - \omega t)}$

Solution
.. Calculation of physical values of the components.
Solution $R = 10 \Omega$, $X_L = 20 \Omega$

Solution
$$\underline{I} = \frac{\underline{U}}{\underline{Z}} = \frac{50 \angle 0^\circ}{10 + j20} = 2.5 \angle -63.4^\circ$$

The current \underline{I} and voltage \underline{U} are in phase with the source voltage $\underline{U}_s = 50 \angle 0^\circ$ resulting in $\underline{U} = 50 \angle 0^\circ$ and $\underline{I} = 2.5 \angle -63.4^\circ$.
The voltage across the capacitor is $\underline{U}_C = \underline{I} \cdot (-j20) = -j50 \angle -63.4^\circ = 50 \angle -153.4^\circ$ and the voltage across the inductor is $\underline{U}_L = \underline{I} \cdot j20 = j50 \angle -63.4^\circ = 50 \angle 26.6^\circ$.
The phase φ can be calculated as $\varphi = \arctan\left(\frac{\text{Im}(\underline{I})}{\text{Re}(\underline{I})}\right) = \arctan\left(\frac{-1.96}{0.96}\right) = -63.4^\circ$.
With the complex exponent $e^{j\varphi}$ we can write $\underline{I} = 2.5 \sqrt{2} \cos(\omega t - 63.4^\circ)$ and $\underline{U} = 50 \sqrt{2} \cos(\omega t)$.

From: <https://wiki.mexle.org/> - MEXLE Wiki
Permanent link: https://wiki.mexle.org/electrical_engineering_1/task_jti0uzudcmg4u22t_with_calculation?rev=1680105719
Last update: 2023/03/29 18:01

