

task_pdkggtyexxy1ktu3_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

complex impedance, exam ee1 WS2022

1 test

Exercise 2 : Impedances at Frequencies

(written test, approx. 18% of a 60-minute written test, WS2022)

Calculate the **resistor values** which have to be used the following circuits.

1. A resistor R_1 shall have the same absolute value of the impedance like a capacitor $C_1=40$ nF at $f_1=4$ MHz.

Solution

$$R_1 = \frac{|X_{C1}|}{1} = \frac{1}{2\pi \cdot f \cdot C_1} = \frac{1}{2\pi \cdot 4 \text{ MHz} \cdot 40 \text{ nF}}$$

Final result

$$R_1 = 1.00 \text{ } \Omega$$

2. A RL series circuit with $L_2=4.7$ μ H, where an AC voltage source of $U_2=1.0$ V with $f_2=450$ kHz generates a current $I_2=60$ mA.

Solution

Series circuit means that the current is constant on every component.

The equivalent impedance for R and L combined is given by
$$\frac{U}{I} = R_2 + j \cdot \omega L$$
 Since $j \cdot \omega L$ is perpendicular to R_2 this can be simplified to:
$$\left| \frac{U}{I} \right|^2 = |R_2|^2 + |X_{L2}|^2 \implies \left(\frac{U}{I} \right)^2 = R_2^2 + X_{L2}^2$$

This can be rearranged to get R_2 :
$$R_2 = \sqrt{\left(\frac{U}{I} \right)^2 - X_{L2}^2} = \sqrt{\left(\frac{1V}{60mA} \right)^2 - (2\pi \cdot 450kHz \cdot 4.7 \mu H)^2}$$

Final result

$$R_2 = 10.0 \text{ } \Omega$$

3. A $\$RC\$$ parallel circuit with $\$C_3=4.7\text{ nF}\$$ on an AC current source ($\$I_{3S}=1.3\text{ A}\$, \$f_3=200\text{ kHz}\$$), which generates a current of $\$I_{3R}=1.0\text{ A}\$$ through $\$R_3\$$.

Solution

Parallel circuit means that the voltage is the same on $\$R_3\$$ and $\$C_3\$$:

$$\underline{U}_3 = R_3 \cdot \underline{I}_{3R} = -j \cdot X_{3C} \cdot \underline{I}_{3C}$$
 So it gets clear, that \underline{I}_{3R} is perpendicular to \underline{I}_{3C} (It has to, since R_3 is perpendicular to $-j \cdot X_{3C}$, too). Therefore, the resulting current of the parallel circuit is given as:

$$\underline{I}_3 = \underline{I}_{3R} + \underline{I}_{3C} \quad || \quad |\underline{I}_3|^2 = |\underline{I}_{3R}|^2 + |\underline{I}_{3C}|^2 \quad || \quad \underline{I}_3 = \sqrt{|\underline{I}_{3R}|^2 + |\underline{I}_{3C}|^2}$$

Back on the first formula:

$$R_3 \cdot \underline{I}_{3R} = X_{3C} \cdot \underline{I}_{3C} \quad || \quad R_3 = X_{3C} \cdot \frac{|\underline{I}_{3C}|}{|\underline{I}_{3R}|} \quad || \quad = \frac{1}{2\pi \cdot f \cdot C_3} \cdot \frac{|\underline{I}_{3C}|}{|\underline{I}_{3R}|}$$

Final result

$$R_3 = 70.0 \text{ } \Omega$$

From:
<https://wiki.mexle.org/> - MEXLE Wiki

Permanent link:
https://wiki.mexle.org/electrical_engineering_1/task_pdkggyexxy1ktu3_with_calculation?rev=1676177854

Last update: 2023/02/12 05:57

