

# task\_rj0r6j4apumukrj6\_with\_calculation

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

resistivity, power, exam ee1 WS2022

## Exercise 1.1 : Resistance of a Wire by Resistivity

(written test, approx. 6 % of a 60-minute written test, WS2022)

A heating element made of a Nichrome wire with a round cross-section is used in an electric oven.

Nichrome is a common Nickel Chromium alloy for heating elements.

The Nichrome wire has a resistivity of  $1.10 \cdot 10^{-6} \text{ } \Omega \cdot \text{m}$ .

The heating element is  $3 \text{ m}$  long and has a diameter of  $3.57 \text{ mm}$ .

1. Calculate the resistance  $R$  of the heating element.

Solution

$$\begin{aligned} R &= \rho \cdot \frac{l}{A} \quad | \quad \text{with } A = r^2 \cdot \pi = \\ &= \frac{1}{4} d^2 \cdot \pi \quad || \quad R = \rho \cdot \frac{l}{\frac{1}{4} d^2 \cdot \pi} \quad || \quad R = \\ &= 1.10 \cdot 10^{-6} \text{ } \Omega \cdot \text{m} \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi} \quad || \quad \end{aligned}$$

Final result

$$R = 0.33 \text{ } \Omega$$

2. The heating element is used to heat the oven to a temperature of  $180 \text{ } ^\circ\text{C}$ . For this, a power dissipation (= heat flow) of  $P=40 \text{ W}$  is necessary. Calculate the current  $I$  needed to operate it.

Solution

$$\begin{aligned} P &= U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \\ &= \sqrt{\frac{P}{R}} = \sqrt{\frac{40 \text{ W}}{0.33 \text{ } \Omega}} \quad \end{aligned}$$

Final result

```
\begin{align*} I = 11 \sim \rm{A} \end{align*}
```

From:

<https://wiki.mexle.org/> - MEXLE Wiki

Permanent link:

[https://wiki.mexle.org/electrical\\_engineering\\_1/task\\_rj0r6j4apumukrj6\\_with\\_calculation?rev=1678465861](https://wiki.mexle.org/electrical_engineering_1/task_rj0r6j4apumukrj6_with_calculation?rev=1678465861)

Last update: **2023/03/10 17:31**

