

# task\_rj0r6j4apumukrj6\_with\_calculation

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

Exercise E1.1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022) ..... 2

resistivity, power, exam ee1 WS2022

include\_1\_100

### Exercise E1.1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)

A heating element made of nichrome wire with a temperature coefficient of  $1.80 \times 10^{-4} \text{ } ^\circ\text{C}^{-1}$  is electrically connected to a  $230 \text{ V}$  AC power source. The electric power dissipation (= heat flow) of  $P=40 \text{ W}$  is necessary.

Calculate the current  $I$  in the heating element.

The Nichrome wire has a resistivity of  $1.10 \times 10^{-6} \text{ } \Omega \cdot \text{m}$ .

The heating element is  $3 \text{ m}$  long and has a diameter of  $3.57 \text{ mm}$ .

Solution:  $R = \rho \cdot \frac{l}{A}$

1. Calculate the resistance  $R$  of the heating element.

$$P = U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \sqrt{\frac{P}{R}} = \sqrt{\frac{40 \text{ W}}{0.33 \text{ } \Omega}} \quad \rightarrow \quad I \approx 10.9 \text{ A}$$

$$R = \rho \cdot \frac{l}{A} \quad | \quad A = r^2 \cdot \pi = \frac{1}{4} d^2 \cdot \pi \quad \Rightarrow \quad R = \rho \cdot \frac{l}{\frac{1}{4} d^2 \cdot \pi} \quad \Rightarrow \quad R = 1.10 \times 10^{-6} \text{ } \Omega \cdot \text{m} \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \times 10^{-3} \text{ m})^2 \cdot \pi} \quad \Rightarrow \quad R \approx 0.33 \text{ } \Omega$$

From: <https://wiki.mexle.org/> - MEXLE Wiki

Permanent link: [https://wiki.mexle.org/electrical\\_engineering\\_1/task\\_rj0r6j4apumukrj6\\_with\\_calculation?rev=1680241904](https://wiki.mexle.org/electrical_engineering_1/task_rj0r6j4apumukrj6_with_calculation?rev=1680241904)

Last update: 2023/03/31 07:51

