

# Exam Winter Semester 2022

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

- Exercise E5 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022) ..... 3
- Exercise E2 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022) ..... 6
- Exercise E7 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022) ..... 7
- Exercise E10 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022) ..... 7
- Exercise E8 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022) ..... 11
- Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022) ..... 11
- Exercise E6 Charging Capacitors (written test, approx. 16 % of a 60-minute written test, WS2022) ..... 12
- Exercise E4 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022) ..... 13
- Exercise E2 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022) ..... 15
- Exercise E3 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022) ..... 19
- Exercise E1 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022) ..... 20
- Exercise E1 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022) ..... 20
- Exercise E9 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022) ..... 24
- Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022) ..... 24
- Exercise E1 Charging Capacitors (written test, approx. 16 % of a 60-minute written test,

---


WS2022) .....	25
Exercise E1 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022) .....	26

d

**Exercise E5 Equivalent linear Source  
(written test, approx. 14 % of a 60-minute written test, WS2022)**

The circuit in the following has to be simplified.  
Result


$$\begin{aligned} U_{\text{rs}} &= U_{\text{AB}} = 4.5 \text{ V} \\ R_{\text{i}} &= R_{\text{AB}} = 6 \text{ } \Omega \end{aligned}$$




Calculated the internal resistance  $R_{\text{i}}$  and the source voltage  $U_{\text{rs}}$  of an equivalent linear voltage source on the connectors  $\text{A}$  and  $\text{B}$ . 
$$R_1=5.0 \text{ } \Omega, \quad U_2=6.0 \text{ V}, \quad R_3= 10 \text{ } \Omega, \quad I_4=4.2 \text{ A}, \quad R_5=10 \text{ } \Omega, \quad R_6=7.5 \text{ } \Omega, \quad R_7=15 \text{ } \Omega$$
 Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of  $U_2$  and  $R_1$  can be transformed into a current source  $I_2 = \frac{U_2}{R_1}$  and  $R_1$ :



Now a lot of them can be combined. The resistors  $R_1$ ,  $R_3$ ,  $R_5$  are in parallel, like also  $I_2$  and  $I_4$ : 
$$R_{135} = R_1 || R_3 || R_5$$
 
$$I_{24} = I_2 - I_4$$
 The resulting circuit can again be transformed:



Here, the  $U_{24}$  is calculated by  $I_{24}$  as the following: 
$$U_{24}$$

$$U_{AB} = U_{24} \cdot \left( \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) - I_4 \cdot R_1 || R_3 || R_5$$

On the right side of the last circuit, there is a voltage divider given by  $R_{135}$ ,  $R_6$ , and  $R_7$ .

Therefore the voltage between  $A$  and  $B$  is given as:

$$U_{AB} = U_{24} \cdot \left( \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) - \left( \frac{U_2}{R_1} - I_4 \right) \cdot \left( R_1 || R_3 || R_5 \right)$$

For the internal resistance  $R_i$  the ideal voltage source is substituted by its resistance ( $=0 \Omega$ , so a short-circuit):

$$R_{AB} = R_7 || (R_6 + R_1 || R_3 || R_5)$$

with  $R_1 || R_3 || R_5 = 5 \Omega || 10 \Omega || 10 \Omega = 5 \Omega || 5 \Omega = 2.5 \Omega$ :

$$U_{AB} = \left( \frac{6.0 \text{ V}}{5.0 \Omega} - 4.2 \text{ A} \right) \cdot \left( \frac{15 \Omega \cdot 2.5 \Omega}{7.5 \Omega + 15 \Omega + 2.5 \Omega} \right)$$

$$R_{AB} = 15 \Omega || (7.5 \Omega + 2.5 \Omega)$$

d

**Exercise E2 Temperature-dependent Resistance**  
**(written test, approx. 6 % of a 60-minute written test, WS2022)**

2. The graph shows the temperature dependence of the resistance of a resistor. The resistor has a resistance of  $10 \text{ k}\Omega$  at  $25^\circ\text{C}$ . Calculate the resistance of the thermistor at  $-40^\circ\text{C}$ .

Its temperature coefficients are:  $\alpha = 0.01 \text{ K}^{-1}$  and  $\beta = 71 \cdot 10^{-6} \text{ K}^{-2}$ .

The temperature inside the refrigeration system can reach down to  $-40^\circ\text{C}$ .

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2)$$

Resistance of the resistor  $R$  depends on the temperature  $T$  and the heat  $Q$ . Therefore, a solution is to use a heat pump to heat up the refrigeration system.

Therefore, with constant  $U$  and increasing  $R$  the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2)$$

with  $\Delta T = T_{\text{end}} - T_{\text{start}}$

$$R = 10 \text{ k}\Omega \cdot \left( 1 + 0.01 \text{ K}^{-1} \cdot (-40^\circ\text{C} - 25^\circ\text{C}) + 71 \cdot 10^{-6} \text{ K}^{-2} \cdot (-40^\circ\text{C} - 25^\circ\text{C})^2 \right)$$

d

### Exercise E7 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)

2. Calculate the phasor voltage  $\underline{u}(t)$  of the  $30 \mu\text{H}$  inductor in the circuit. The components  $R$  and  $X_L$  shall be given.

After analysis, the following phasor voltage  $\underline{u}(t)$  is extracted:  $\underline{u}(t) = 10 \cos(\omega t + \varphi)$  in  $\text{V}$ .

Solution  
.. Calculate the physical values of the components.  
Solution  $R = 10 \Omega$ ,  $X_L = 30 \mu\text{H} \cdot \omega = 1.88 \Omega$

Solution  
$$\underline{I} = \frac{\underline{U}}{\underline{Z}} = \frac{50 \angle 0^\circ}{4.68 \angle -20.9^\circ} = 10.68 \angle 20.9^\circ \text{ A}$$
  
The current  $i(t) = 10.68 \cos(\omega t + 20.9^\circ) \text{ A}$  is the result of the superposition of the current through the resistor and the current through the inductor. The voltage across the resistor is  $\underline{u}_R = R \cdot \underline{I} = 106.8 \angle 20.9^\circ \text{ V}$  and the voltage across the inductor is  $\underline{u}_L = jX_L \cdot \underline{I} = 20.3 \angle 110.9^\circ \text{ V}$ . The total voltage is  $\underline{u} = \underline{u}_R + \underline{u}_L = 127.1 \angle 20.9^\circ \text{ V}$ .  
With the complex part comes the magnitude  $|\underline{u}| = 127.1 \text{ V}$  and the phase  $\varphi = 20.9^\circ$ .  
The phase  $\varphi$  can be calculated as  $\varphi = \arctan\left(\frac{\text{Im}(\underline{u})}{\text{Re}(\underline{u})}\right) = \arctan\left(\frac{-4.68}{0.24}\right) = -10.9^\circ$ .

d

### Exercise E10 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022)

2. Calculate the resulting phasor voltage  $\underline{u}(t)$  of the  $30 \mu\text{H}$  inductor in the circuit. The components  $R$  and  $X_L$  shall be given. The voltage source is  $u(t) = 3.0 \cos(2\pi \cdot 15 \cdot t) \text{ V}$ .  
Solution  
Result  
.. Draw the circuit diagram of the given circuit. Label all components, voltages, and currents.

```

\begin{align*} Z &= \frac{\hat{U}}{\hat{I}} \quad \hat{I} = \frac{\hat{U}}{Z} \\
\end{align*}
\begin{align*} Z_C &= \frac{1}{2\pi f C} \quad \omega = 2\pi f = 2\pi \cdot 15 \\
\omega &= 2\pi \cdot 15 = 94.2 \text{ rad/s} \\
\end{align*}
\begin{align*} Z_L &= 2\pi f L = 2\pi \cdot 15 \cdot 330 \cdot 10^{-6} \\
&= 3.11 \text{ } \Omega \\
\end{align*}
\begin{align*} Z_C &= \frac{1}{2\pi f C} = \frac{1}{2\pi \cdot 15 \cdot 330 \cdot 10^{-6}} \\
&= 160.7 \text{ } \Omega \\
\end{align*}
\underline{Z} = R + j\underline{Z}_L - j\underline{Z}_C \quad \underline{Z} = R + j(\underline{Z}_L - \underline{Z}_C) \\
|\underline{Z}| = \sqrt{R^2 + (\underline{Z}_L - \underline{Z}_C)^2}

```

□□□□□□□□ □510...





d

### Exercise E8 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)

A series circuit means that the current is constant on every component.  
 The equivalent impedance for  $R_1$  and  $R_2$  combined is given by  $Z_{eq} = R_1 + R_2$   
 Parallel circuit means that the voltage is the same on  $R_1$  and  $R_2$   
 The equivalent impedance for  $R_1$  and  $R_2$  combined is given by  $Z_{eq} = \frac{R_1 R_2}{R_1 + R_2}$   
 A series circuit means that the current is constant on every component.  
 The equivalent impedance for  $R_1$  and  $R_2$  combined is given by  $Z_{eq} = R_1 + R_2$   
 Parallel circuit means that the voltage is the same on  $R_1$  and  $R_2$   
 The equivalent impedance for  $R_1$  and  $R_2$  combined is given by  $Z_{eq} = \frac{R_1 R_2}{R_1 + R_2}$

Solution

$R_1 = 1.00 \Omega$

$R_2 = 10.0 \Omega$

A series circuit means that the current is constant on every component.  
 The equivalent impedance for  $R_1$  and  $R_2$  combined is given by  $Z_{eq} = R_1 + R_2$   
 Parallel circuit means that the voltage is the same on  $R_1$  and  $R_2$   
 The equivalent impedance for  $R_1$  and  $R_2$  combined is given by  $Z_{eq} = \frac{R_1 R_2}{R_1 + R_2}$   
 A series circuit means that the current is constant on every component.  
 The equivalent impedance for  $R_1$  and  $R_2$  combined is given by  $Z_{eq} = R_1 + R_2$   
 Parallel circuit means that the voltage is the same on  $R_1$  and  $R_2$   
 The equivalent impedance for  $R_1$  and  $R_2$  combined is given by  $Z_{eq} = \frac{R_1 R_2}{R_1 + R_2}$   
 A series circuit means that the current is constant on every component.  
 The equivalent impedance for  $R_1$  and  $R_2$  combined is given by  $Z_{eq} = R_1 + R_2$   
 Parallel circuit means that the voltage is the same on  $R_1$  and  $R_2$   
 The equivalent impedance for  $R_1$  and  $R_2$  combined is given by  $Z_{eq} = \frac{R_1 R_2}{R_1 + R_2}$

d

### Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)

The heating element is used to heat the wire with a temperature of  $1800^\circ\text{C}$ .  
 Result: power dissipation (= heat flow) of  $P=40 \text{ W}$  is necessary.  
 Calculate the current  $I$  needed to operate for heating elements.  
 The Nichrome wire has a resistivity of  $1.10 \cdot 10^{-6} \Omega \cdot \text{m}$ .  
 The heating element is  $3 \text{ m}$  long and has a diameter of  $3.57 \text{ mm}$ .  
 Calculate the resistance  $R$  of the heating element.

Solution

$$\begin{aligned} P &= U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \sqrt{\frac{P}{R}} = \sqrt{\frac{40 \text{ W}}{0.33 \text{ } \Omega}} \end{aligned}$$

$$\begin{aligned} R &= \rho \cdot \frac{l}{A} \quad | \quad A = r^2 \cdot \pi \\ \frac{1}{4} d^2 \cdot \pi \quad | \quad R &= \rho \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad | \quad R = 1.10 \cdot 10^{-6} \text{ } \Omega \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi} \end{aligned}$$

d

**Exercise E6 Charging Capacitors**  
(written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit (with the real battery) also takes into account the internal resistance  $R_1$  of the battery. The capacitor  $C$  is initially uncharged. The switch  $S_1$  is open. The voltage across the capacitor is again  $U_C = 0 \text{ V}$  at the moment  $t_0 = 0 \text{ s}$  when the switch  $S_1$  is closed. Calculate the voltage  $u_C(t_2)$  across the capacitor at  $t_2 = 1 \text{ ms}$  after closing the switch.

**Solution**  
Hint: To solve this, first create an equivalent linear voltage source from  $U$ ,  $R_1$ , and  $R_2$ .

**Solution**  
The ideal voltage source  $U$  is in series with the internal resistance  $R_1$  and the external resistance  $R_2$ . The voltage across the capacitor is  $u_C(t) = U \cdot (1 - e^{-t/\tau})$ , where  $\tau = (R_1 + R_2) \cdot C$ .  
On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting  $R_2$ .




The circuit contains a voltage source  $U = 12 \text{ V}$ , a switch  $S_1$ , a resistor of  $R_1 = 20 \text{ } \Omega$  and a capacitor of  $C = 100 \text{ } \mu\text{F}$ .

The switch  $S_2$  to an additional consumer  $R_2$  will be considered to be open for the first asks. At the moment  $t_0 = 0 \text{ s}$  the switch  $S_1$  is closed, the voltage across the capacitor is  $u_C(t_0) = 0 \text{ V}$ .

- 1. First do not consider the light bulb - it is not connected to the RC circuit.
- 2. Calculate the point of time  $t_1$  when  $u_C(t_1) = 0.5 \cdot U$ .

Solution



So, here only  $R_1$  and  $C$  gives the time constant:  $\tau = R_1 \cdot C$

The following formula describes the time course of  $u_C(t)$  which has to be  $u_C(t_1) = 0.5 \cdot U$ :  

$$u_C(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$$
 It has to be rearranged to  $(1 - e^{-t/\tau}) = 0.5$   

$$e^{-t/\tau} = 0.5 \implies -t/\tau = \ln(0.5) \implies t = \tau \cdot \ln(0.5)$$



An equivalent linear voltage source can be given with  $U$ ,  $R_1$ , and  $R_B$  as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is:  $U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U$   
 The internal resistance is given by substituting the ideal voltage source with its resistance ( $R_i = 0 \Omega$ , short-circuit).  

$$R_i = R_1 \parallel R_B = 10 \Omega$$

$$u_C(t_2) = U_s \cdot (1 - e^{-t_2/(R_i \cdot C)}) = \frac{1}{2} \cdot U \cdot (1 - e^{-1 \text{ms} / (10 \Omega \cdot 100 \mu\text{F})})$$


d

**Exercise E4 Pure Resistor Network Simplification**  
 (written test, approx. 13 % of a 60-minute written test, WS2022)

The following shall be solved at 0°C. On the left,  $R_1 = R_2 = R_3 = 10 \Omega$  and the voltage source  $U = 10 \text{V}$ . The current  $i$  is given through  $R_B$ .

Solution

$R_2 = R_3 = 100 \Omega$



Since  $R_2 = R_3$  and based on the equations for the transformation, the transformed  $R_Y$  is given as:


$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2} = \frac{(100 \Omega)^2}{3 \cdot 100 \Omega} = \frac{1}{3} \cdot 100 \Omega = 33.33 \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{eq} = R_Y + (R_Y + R_1) \parallel (R_Y + R_2) = 33.33 \Omega + (33.33 \Omega + 400 \Omega) \parallel (33.33 \Omega + 100 \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance  $R_{eq}$  between A and B.

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:


$$R_{\text{eq}} = (R_2 + R_1 + R_1) \parallel (R_2 + R_2) \parallel R_{\text{eq}} = (100 \Omega + 200 \Omega + 200 \Omega) \parallel (100 \Omega + 100 \Omega) \parallel R_{\text{eq}} = (500 \Omega) \parallel (200 \Omega) \parallel R_{\text{eq}} = \frac{500 \Omega \cdot 200 \Omega}{500 \Omega + 200 \Omega} \parallel$$

d

**Exercise E2 Equivalent linear Source  
(written test, approx. 14 % of a 60-minute written test, WS2022)**

The circuit in the following has to be simplified.  
Result

$$U_{\text{s}} = U_{\text{AB}} = 4.5 \text{ V} \quad R_{\text{i}} = R_{\text{AB}} = 6 \Omega$$




Calculate the internal resistance  $R_i$  and the source voltage  $U_s$  of an equivalent linear voltage source on the connectors  $A$  and  $B$ .  $R_1=5.0 \Omega$ ,  $U_2=6.0 \text{ V}$ ,  $R_3= 10 \Omega$ ,  $I_4=4.2 \text{ A}$ ,  $R_5=10 \Omega$ ,  $R_6=7.5 \Omega$ ,  $R_7=15 \Omega$  Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of  $U_2$  and  $R_1$  can be transformed into a current source  $I_2 = \frac{U_2}{R_1}$  and  $R_1$ :



Now a lot of them can be combined. The resistors  $R_1$ ,  $R_3$ ,  $R_5$  are in parallel, like also  $I_2$  and  $I_4$ :

$$R_{135} = R_1 || R_3 || R_5$$

$$I_{24} = I_2 - I_4 = \frac{U_{24}}{R_1} - I_4$$

The resulting circuit can again be transformed:



Here, the  $U_{24}$  is calculated by  $I_{24}$  as the following:

$$U_{24}$$

$$U_{AB} = U_{24} \cdot \left( \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) - I_4 \cdot R_1 || R_3 || R_5$$

On the right side of the last circuit, there is a voltage divider given by  $R_{135}$ ,  $R_6$ , and  $R_7$ .

Therefore the voltage between  $A$  and  $B$  is given as:

$$U_{AB} = U_{24} \cdot \left( \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) - \left( \frac{U_2}{R_1} - I_4 \right) \cdot \left( \frac{R_7 \cdot R_1 || R_3 || R_5}{R_6 + R_7 + R_1 || R_3 || R_5} \right)$$

For the internal resistance  $R_i$  the ideal voltage source is substituted by its resistance ( $=0 \Omega$ , so a short-circuit):

$$R_{AB} = R_7 || (R_6 + R_1 || R_3 || R_5)$$

with  $R_1 || R_3 || R_5 = 5 \Omega || 10 \Omega || 10 \Omega = 5 \Omega || 5 \Omega = 2.5 \Omega$ :

$$U_{AB} = \left( \frac{6.0 \text{ V}}{5.0 \Omega} - 4.2 \text{ A} \right) \cdot \left( \frac{15 \Omega \cdot 2.5 \Omega}{7.5 \Omega + 15 \Omega + 2.5 \Omega} \right)$$

$$R_{AB} = 15 \Omega || (7.5 \Omega + 2.5 \Omega)$$

d

**Exercise E3 Temperature-dependent Resistance**  
**(written test, approx. 6 % of a 60-minute written test, WS2022)**

2. The graph shows the temperature dependence of the resistance of a resistor. The resistor has a resistance of  $10 \text{ k}\Omega$  at  $25^\circ\text{C}$ . Calculate the resistance of the thermistor at  $-40^\circ\text{C}$ .

Its temperature coefficients are:  $\alpha = 0.01 \text{ K}^{-1}$  and  $\beta = 71 \cdot 10^{-6} \text{ K}^{-2}$ .

The temperature inside the refrigeration system can reach down to  $-40^\circ\text{C}$ .

$$R = 10 \text{ k}\Omega \cdot \left( 1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2 \right)$$

Resistance of the resistor  $R$  depends on the temperature  $T$  and the heat  $Q$ . Therefore, a solution is to use a heat pump to heat up the refrigeration system.

Therefore, with constant  $U$  and increasing  $R$  the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 \cdot \left( 1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2 \right)$$

with  $\Delta T = T_{\text{end}} - T_{\text{start}}$

$$R = 10 \text{ k}\Omega \cdot \left( 1 + 0.01 \text{ K}^{-1} \cdot (-40^\circ\text{C} - 25^\circ\text{C}) + 71 \cdot 10^{-6} \text{ K}^{-2} \cdot (-40^\circ\text{C} - 25^\circ\text{C})^2 \right)$$

d

### Exercise E1 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)

2. Calculate the phasor voltage  $\underline{u}$  and the phasor current  $\underline{i}$  in the circuit shown in the figure. The components  $R$  and  $X_L$  shall be given.

After analysis, the following phasors shall be determined:  $\underline{u}$  and  $\underline{i}$  in the circuit. The voltage  $\underline{u}$  shall be given in the form  $\underline{u} = \hat{u} \cdot e^{j(\omega t + \varphi)}$  and the current  $\underline{i}$  in the form  $\underline{i} = \hat{i} \cdot e^{j(\omega t + \varphi)}$ .

Solution  
.. Calculation of the phasor voltage  $\underline{u}$  and the phasor current  $\underline{i}$  in the circuit. The voltage  $\underline{u}$  shall be given in the form  $\underline{u} = \hat{u} \cdot e^{j(\omega t + \varphi)}$  and the current  $\underline{i}$  in the form  $\underline{i} = \hat{i} \cdot e^{j(\omega t + \varphi)}$ .

Solution  
$$\underline{u} = \underline{U} \cdot e^{j(\omega t + \varphi)} \quad \underline{i} = \underline{I} \cdot e^{j(\omega t + \varphi)}$$
  
The current  $\underline{i}$  and voltage  $\underline{u}$  are in phase with the source voltage  $\underline{u}_s = 3.0 \cdot e^{j(2\pi \cdot 15 \cdot t)}$  (pure real) resulting in  $\underline{u} = 3.0 \cdot e^{j(2\pi \cdot 15 \cdot t)}$  and  $\underline{i} = 0.24 \cdot e^{j(2\pi \cdot 15 \cdot t)}$ .  
The voltage  $\underline{u}$  across the capacitor is  $\underline{u}_C = \underline{I} \cdot \underline{Z}_C = 0.24 \cdot (-j30) = -j7.2$  V and the voltage across the inductor is  $\underline{u}_L = \underline{I} \cdot \underline{Z}_L = 0.24 \cdot (j48.2) = j11.57$  V.  
The phasor voltage  $\underline{u}$  is the sum of the voltages across the capacitor and the inductor:  $\underline{u} = \underline{u}_C + \underline{u}_L = -j7.2 + j11.57 = j4.37$  V.  
The phasor current  $\underline{i}$  is  $\underline{i} = 0.24 \cdot e^{j(2\pi \cdot 15 \cdot t)}$  A.  
With the complex power  $\underline{S} = \underline{U} \cdot \underline{I}^* = 3.0 \cdot 0.24 = 0.72$  VA, the real power  $P = \text{Re}\{\underline{S}\} = 0.72$  W and the reactive power  $Q = \text{Im}\{\underline{S}\} = 0$  VAR.  
The phase  $\varphi$  can be calculated as  $\varphi = \arctan\left(\frac{\text{Im}\{\underline{u}\}}{\text{Re}\{\underline{u}\}}\right) = \arctan\left(\frac{4.37}{0}\right) = 90^\circ$ .

d

### Exercise E1 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022)

2. Calculate the resulting phasor voltage  $\underline{u}$  and the phasor current  $\underline{i}$  in the circuit shown in the figure. The voltage source  $u(t) = 3.0 \cdot \sin(2\pi \cdot 15 \cdot t)$  V and the current source  $i(t) = 0.22 \cdot \sin(2\pi \cdot 15 \cdot t)$  A are given. The components  $R$  and  $X_L$  shall be given.

Solution  
The linear source is connected with an inductor of  $330 \mu\text{H}$  and a capacitor of  $30.22 \mu\text{F}$ , all in series.

Result  
.. Draw the circuit diagram of the given circuit. Label all components, voltages, and currents.

```

\begin{align*} Z &= \frac{\hat{U}}{\hat{I}} \quad \hat{I} = \frac{\hat{U}}{Z} \\
\end{align*}
\begin{align*} Z_C &= \frac{1}{2\pi f C} \quad \omega = 2\pi f = 2\pi \cdot 15 \\
\omega &= 94.2 \text{ rad/s} \\
\end{align*}
\begin{align*} I &= \frac{U}{Z} = \frac{100}{\sqrt{R^2 + \left(\frac{1}{\omega C}\right)^2}} \\
\end{align*}
\begin{align*} Z_C &= \frac{1}{2\pi \cdot 15 \cdot 330 \cdot 10^{-6}} \\
\end{align*}
\begin{align*} \underline{Z} &= R + j\underline{Z}_L + \underline{Z}_C \quad \underline{Z} = R + j \\
&\quad \cdot \underline{Z}_L - j \cdot \underline{Z}_C \quad \underline{Z} = R + j(\underline{Z}_L - \underline{Z}_C) \\
|\underline{Z}| &= \sqrt{R^2 + (\underline{Z}_L - \underline{Z}_C)^2} \\
\end{align*}

```

□□□□□□□□ □510...





d

### Exercise E9 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)

A series circuit with a resistor  $R_1 = 1.00 \text{ k}\Omega$  and a capacitor  $C_1 = 40 \text{ nF}$  is connected to an AC voltage source of  $U = 10 \text{ V}$  at a frequency  $f = 4 \text{ MHz}$ . A resistor  $R_2 = 10.0 \text{ }\Omega$  and a capacitor  $C_2 = 4.7 \text{ }\mu\text{F}$  are connected in parallel to the same source. Calculate the current  $I$  through the parallel combination and the voltage  $U_{R_2}$  across the resistor  $R_2$ .

Solution

$$R_1 = 1.00 \text{ k}\Omega$$

$$R_2 = 10.0 \text{ }\Omega$$

A series circuit means that the current is constant on every component.

The equivalent impedance for  $R_2$  and  $C_2$  combined is given by

$$Z_{R_2C_2} = \frac{R_2 \cdot (-jX_{C_2})}{R_2 - jX_{C_2}}$$

Parallel circuit means that the voltage is the same on  $R_2$  and  $C_2$ .

Since  $X_{C_2} \ll R_2$ , the impedance can be simplified to  $Z_{R_2C_2} \approx -jX_{C_2}$ .

The resulting current of the parallel circuit is given as:

$$I_{R_2C_2} = \frac{U}{Z_{R_2C_2}} = \frac{U}{-jX_{C_2}} = j \frac{U}{X_{C_2}}$$

Back to the first formula:

$$I = \frac{U}{R_1 + Z_{R_2C_2}} = \frac{U}{R_1 - jX_{C_2}}$$

$$I = \frac{U}{R_1} \cdot \frac{1}{1 - j \frac{X_{C_2}}{R_1}} = \frac{U}{R_1} \cdot \frac{1 + j \frac{X_{C_2}}{R_1}}{1 + \left(\frac{X_{C_2}}{R_1}\right)^2}$$

d

### Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)

A heating element made of nichrome wire with a cross-section of  $A = 1.80 \text{ mm}^2$  and a length of  $l = 3.57 \text{ m}$  is connected to a power supply of  $U = 10 \text{ V}$ . Calculate the resistance  $R$  of the heating element.

Solution

$$R = \frac{\rho \cdot l}{A}$$

Solution

$$\begin{aligned} P &= U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \sqrt{\frac{P}{R}} = \sqrt{\frac{40 \text{ W}}{0.33 \text{ } \Omega}} \end{aligned}$$

$$\begin{aligned} R &= \rho \cdot \frac{l}{A} \quad | \quad A = r^2 \cdot \pi \\ \frac{1}{4} d^2 \cdot \pi \quad R &= \rho \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad | \quad R = 1.10 \cdot 10^{-6} \text{ } \Omega \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi} \end{aligned}$$

d

**Exercise E1 Charging Capacitors**  
(written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit (with the real battery) also takes into account the internal resistance  $R_1$  of the battery. The capacitor  $C$  is initially uncharged. The switch  $S_1$  is closed at  $t_0 = 0 \text{ s}$  and the voltage across the capacitor is again  $U_C$  at the moment  $t_2 = 1 \text{ ms}$  after closing the switch. Calculate the voltage  $u_C(t_2)$  across the capacitor at  $t_2 = 1 \text{ ms}$  after closing the switch.

**Solution**  
Hint: To solve this, first create an equivalent linear voltage source from  $U$ ,  $R_1$ , and  $R_2$ .

**Solution**  
The ideal voltage source  $U$  is in series with the internal resistance  $R_1$  and the external resistor  $R_2$ . The voltage across the capacitor is again  $U_C$  at the moment  $t_2 = 1 \text{ ms}$  after closing the switch. On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting  $R_2$ .




The circuit contains a voltage source  $U = 12 \text{ V}$ , a switch  $S_1$ , a resistor of  $R_1 = 20 \text{ } \Omega$  and a capacitor of  $C = 100 \text{ } \mu\text{F}$ .

The switch  $S_2$  to an additional consumer  $R_2$  will be considered to be open for the first asks. At the moment  $t_0 = 0 \text{ s}$  the switch  $S_1$  is closed, the voltage across the capacitor is  $u_C(t_0) = 0 \text{ V}$ .

... First do not consider the light bulb - it is not connected to the RC circuit. Calculate the point of time  $t_1$  when  $u_C(t_1) = 0.5 \cdot U$ .

Solution



So, here only  $R_1$  and  $C$  gives the time constant:  $\tau = R_1 \cdot C$

The following formula describes the time course of  $u_C(t)$  which has to be  $u_C(t_1) = 0.5 \cdot U$ :  

$$u_C(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$$
 It has to be rearranged to  $(1 - e^{-t/\tau}) = 0.5 \Rightarrow e^{-t/\tau} = 0.5 \Rightarrow -t/\tau = \ln(0.5) \Rightarrow t = \tau \cdot \ln(0.5)$



An equivalent linear voltage source can be given with  $U_s$ ,  $R_1$ , and  $R_B$  as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is:  $U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U$  The internal resistance is given by substituting the ideal voltage source with its resistance ( $R_i = 0 \Omega$ , short-circuit).  
 $R_i = R_1 \parallel R_B = 10 \Omega$

$$u_C(t_2) = U_s \cdot (1 - e^{-t_2/(R_i \cdot C)}) = \frac{1}{2} \cdot U \cdot (1 - e^{-1 \text{ms}/(10 \Omega \cdot 100 \mu\text{F})})$$


d

**Exercise E1 Pure Resistor Network Simplification**  
 (written test, approx. 13 % of a 60-minute written test, WS2022)

The following shall be solved at a rate of  $R_1 = R_2 = R_3 = 10 \Omega$  and the source  $U = 10 \text{V}$ .  
 Result:  $I = 0.5 \text{A}$

Solution

$R_{eq}$  between A and B



Since  $R_2=R_3$  and based on the equations for the transformation, the transformed  $R_Y$  is given as:


$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2} = \frac{(100 \Omega)^2}{3 \cdot 100 \Omega} = \frac{1}{3} \cdot 100 \Omega = 33.33 \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{eq} = R_Y + (R_Y + R_1) \parallel (R_Y + R_2) \parallel R_{eq} = 33.33 \Omega + (33.33 \Omega + 400 \Omega) \parallel (33.33 \Omega + 100 \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance  $R_{eq}$  between A and B.

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = (R_2 + R_1 + R_1) \parallel (R_2 + R_2) \parallel R_{\text{eq}} = (100 \sim \Omega + 200 \sim \Omega + 200 \sim \Omega) \parallel (100 \sim \Omega + 100 \sim \Omega) \parallel R_{\text{eq}} = (500 \sim \Omega) \parallel (200 \sim \Omega) \parallel R_{\text{eq}} = \frac{500 \sim \Omega \cdot 200 \sim \Omega}{500 \sim \Omega + 200 \sim \Omega}$$

From:

<https://wiki.mexle.org/> - MEXLE Wiki

Permanent link:

[https://wiki.mexle.org/electrical\\_engineering\\_1/ws2022\\_exam?rev=1680087384](https://wiki.mexle.org/electrical_engineering_1/ws2022_exam?rev=1680087384)

Last update: **2023/03/29 12:56**

