

# task\_1.9.3\_with\_calculation


## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

Aufgabe 1.9.3: layered plate capacitor (exam task, ca 6% of a 60 minute exam, WS2020)  
..... 2

**Aufgabe 1.9.3: layered plate capacitor (exam task, ca 6% of a 60 minute exam, WS2020)**



Determine the capacitance  $C$  for the plate capacitor drawn on the right with the following data:

- rectangular electrodes with edge length of  $6\text{ cm}$  and  $8\text{ cm}$ .
- distance between the plates:  $2\text{ mm}$
- dielectric A:
  - $\epsilon_{r,A} = 1$  (air)
  - thickness  $d_A = 1.5\text{ mm}$
- Dielectric B:
  - $\epsilon_{r,B} = 100$  (ice)
  - thickness  $d_B = 0.5\text{ mm}$

$\epsilon_0 = 8.854 \cdot 10^{-12}\text{ F/m}$

Tips for the solution

- Which circuit can be used to replace a layered structure with different dielectrics?

Solution

The total capacitance  $C$  can be divided into a partial capacitance  $C_A$  and a  $C_B$ . These are connected in series.

This results in:  $C = \frac{C_A \cdot C_B}{C_A + C_B}$

The partial capacitance  $C_A$  can be calculated by 
$$C_A = \epsilon_0 \epsilon_{r,A} \cdot \frac{A}{d_A} \quad | \quad \text{with } A = 3\text{ cm} \cdot 5\text{ cm} = 6 \cdot 10^{-2} \cdot 8 \cdot 10^{-2}\text{ m}^2 = 48 \cdot 10^{-4}\text{ m}^2$$
  

$$C_A = 8.854 \cdot 10^{-12}\text{ F/m} \cdot \frac{48 \cdot 10^{-4}\text{ m}^2}{1.5 \cdot 10^{-3}\text{ m}} \quad || \quad C_A = 28.33 \cdot 10^{-12}\text{ F}$$

The partial capacitance  $C_B$  can be calculated by 
$$C_B = \epsilon_0 \epsilon_{r,B} \cdot \frac{A}{d_B} \quad || \quad C_B = 100 \cdot 8.854 \cdot 10^{-12}\text{ F/m} \cdot \frac{48 \cdot 10^{-4}\text{ m}^2}{0.5 \cdot 10^{-3}\text{ m}}$$

$$\frac{48 \cdot 10^{-4} \text{ m}^2}{0,5 \cdot 10^{-3} \text{ m}} \parallel C_B \text{ \&= } 8.500 \cdot 10^{-9} \text{ F} \parallel$$

Result

$$C = 28.24 \cdot 10^{-12} \text{ F} \rightarrow 28 \text{ pF}$$

From:

<https://wiki.mexle.org/> - **MEXLE Wiki**

Permanent link:

[https://wiki.mexle.org/electrical\\_engineering\\_2/task\\_1.9.3\\_with\\_calculation?rev=1646911893](https://wiki.mexle.org/electrical_engineering_2/task_1.9.3_with_calculation?rev=1646911893)

Last update: **2022/03/10 12:31**

