

task_k4wrrhf8v46gct49_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E5 Capacitor (written test, approx. 12 % of a 120-minute written test, SS2024) 2

electrostatic, capacitor, plate capacitor, capacity, exam ee2 SS2024

Exercise E5 Capacitor

(written test, approx. 12 % of a 120-minute written test, SS2024)

0. Calculate the change of capacitance if the insulator is replaced by paper (dielectric constant $\epsilon_r = 3$). Results are applied.

The contaminant has $\epsilon_{r,c} > \epsilon_{r,air}$, while the distance between the plates remains the same. Give a generalized formula

Path

$$C = f(A, d, x, \epsilon_{r,c}, \epsilon_{r,air})$$

$$Q = \frac{U}{\frac{1}{\epsilon_0 \epsilon_{r,c}} \frac{A}{d-x} + \frac{1}{\epsilon_0 \epsilon_{r,air}} \frac{x}{d}}$$

Path

Here are two ways now. Either: $Q = C \cdot U = 1.1 \cdot 10^{-6} \text{ C}$ Or: $Q = D \cdot A = 146 \cdot 10^{-6} \text{ C}$

The displacement field is given by: $D = \epsilon_0 \epsilon_r E$

Send $\epsilon_{r,c} = \frac{U}{d-x}$ and $\epsilon_{r,air} = \frac{U}{x}$

The resulting capacity C is now a series circuit of C_{air} and C_c .

Therefore: $C = \frac{1}{\frac{1}{C_{air}} + \frac{1}{C_c}}$

$$C_{air} = \epsilon_0 \epsilon_{r,air} \frac{A}{d-x}$$

$$C_c = \epsilon_0 \epsilon_{r,c} \frac{A}{x}$$

- In the following such a sensor is given with:
- Plate area: $A = 25 \text{ mm}^2$
 - Distance between both plates: $d = 200 \text{ }\mu\text{m}$
 - Air between the plates: $\epsilon_{r,air} = 1$
 - Supply voltage: $U = 3.3 \text{ V}$
 - Boundary effects on the end of the layers shall be ignored in the following calculations.

$$\epsilon_0 = 8.854 \cdot 10^{-12} \text{ F/m}$$

1. Calculate the capacity C .

Path

$$C = \frac{1}{\frac{1}{\epsilon_0 \epsilon_{r,c} \frac{A}{x}} + \frac{1}{\epsilon_0 \epsilon_{r,air} \frac{A}{d-x}}}$$

From:

<https://wiki.mexle.org/> - **MEXLE Wiki**

Permanent link:

https://wiki.mexle.org/electrical_engineering_and_electronics/task_k4wrrhf8v46gct49_with_calculation

Last update: **2024/07/15 16:27**

