

# task\_unkkahm3u0v9azny\_with\_calculation

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

Exercise E12 Self Induction (written test, approx. 8 % of a 120-minute written test, SS2022)  
..... 2

self induction, induction, exam ee2 SS2022

**Exercise E12 Self Induction**  
**(written test, approx. 8 % of a 120-minute written test, SS2022)**

2. A motor with a maximum current of  $I = 63 \text{ A}$ , which the circuit breaker has a DC voltage source and which is fused with a circuit breaker.

Sketch the diagram of the circuit with the current  $i(t) = 63 \text{ A}$  at  $t = 0$ . The induced current is reduced linearly down to  $0 \text{ A}$  within  $1 \text{ } \mu\text{s}$ .

(The inner resistance of the motor shall be neglected.)

$$u_{\text{ind}}(t) = 3150 \text{ V}$$

Path

.. Draw the circuit (the circuit breaker can be drawn as a switch), with all voltage and current arrows.

For the maximum voltage on the circuit breaker one has to consider the following:


Result

- external voltage of the voltage source  $U_{\text{ext}}$
- voltage  $u_{\text{ind}}(t)$  induced by the change of the current

The first one is not given in the exercise, and therefore not considered here.

The induced voltage can be calculated by linearizing the following: 
$$u_{\text{ind}}(t) = -L \frac{di}{dt} \rightarrow u_{\text{ind}}(t) = -L \frac{\Delta i}{\Delta t}$$

With the given details: 
$$u_{\text{ind}}(t) = -L \frac{0 - I}{t_1 - t_0} = 50 \cdot 10^{-6} \text{ H} \cdot \frac{63 \text{ A}}{1 \cdot 10^{-6} \text{ s}} = 3150 \frac{\text{Vs}}{\text{A}} \cdot \frac{\text{A}}{\text{s}}$$



From:

<https://wiki.mexle.org/> - **MEXLE Wiki**

Permanent link:

[https://wiki.mexle.org/electrical\\_engineering\\_and\\_electronics/task\\_unkkahm3u0v9azny\\_with\\_calculation](https://wiki.mexle.org/electrical_engineering_and_electronics/task_unkkahm3u0v9azny_with_calculation)

Last update: **2024/07/05 03:25**

