

rechnung_signalzeitverlauf_umkehrintegrator

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

\$I.\quad\$ Am Punkt \$t_1\$

$$U_A(t_1) = -\frac{1}{\tau} \int_{t_0}^{t_1} U_E \, dt + U_A(t_0)$$

$$U_A(t_1) = -\frac{1}{5 \text{ k}\Omega \cdot 1 \text{ }\mu\text{F}} \int_{t_0}^{10\text{ms}} 1\text{V} \, dt + 0\text{V}$$

$$U_A(t_1) = -\frac{1}{5 \text{ ms}} \int_{t_0}^{10\text{ms}} 1\text{V} \, dt$$

$$U_A(t_1) = -\frac{1}{5 \text{ ms}} \int_{t_0}^{10\text{ms}} 1\text{V} \, dt = -2\text{V}$$

\$I.\quad\$ Am Punkt \$t_2\$

$$U_A(t_1) = -\frac{1}{\tau} \int_{t_0}^{t_1} U_E \, dt + U_A(t_0)$$

$$U_A(t_1) = -\frac{1}{5 \text{ ms}} \int_{10\text{ms}}^{20\text{ms}} (-1\text{V}) \, dt + 2\text{V} = 0\text{V}$$

\$I.\quad\$ Am Punkt \$t_3\$

$$U_A(t_1) = -\frac{1}{\tau} \int_{t_0}^{t_1} U_E \, dt + U_A(t_0)$$

$$U_A(t_1) = -\frac{1}{5 \text{ ms}} \int_{10\text{ms}}^{20\text{ms}} (-2\text{V}) \, dt + 0\text{V} = -2\text{V}$$

From:

<https://wiki.mexle.org/> - MEXLE Wiki

Permanent link:

https://wiki.mexle.org/elektronische_schaltungstechnik/rechnung_signalzeitverlauf_umkehrintegrator?rev=1590079917

Last update: 2021/05/09 09:53

