

rechnung_umkehrintegrator

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

$U_A = f(U_E)$	mit III.	
$\square\square\square\square\square\square\square\square\square\square$	$\square\square\square\square\square\square\square\square\square\square$	$\square\square\square\square\square\square\square\square\square\square$
$U_A = \text{color}\{blue\}\{-U_D\} - U_C$	mit II. und I.	$\text{color}\{blue\}\{U_D\} = \{1 \over A_D\} \cdot U_A \overset{A_D}{\rightarrow \infty} \rightarrow 0$
$\square\square\square\square\square\square\square\square\square\square$	$\square\square\square\square\square\square\square\square\square\square$	$\square\square\square\square\square\square\square\square\square\square$
$U_A = \square 0 \square - \text{color}\{blue\}\{U_C\}$	mit V.	$\text{color}\{blue\}\{U_C\} = \{1 \over C\} \cdot \int_{t_0}^{t_1} I_C \ dt + Q_0(t_0)$
$\square\square\square\square\square\square\square\square\square\square$	$\square\square\square\square\square\square\square\square\square\square$	$\square\square\square\square\square\square\square\square\square\square$
$U_A = \{-\{1 \over C\} \cdot \int_{t_0}^{t_1} \text{color}\{blue\}\{I_C\} \ dt + Q_0(t_0)\}$	mit IV.	$\text{color}\{blue\}\{I_C\} = I_R$
$\square\square\square\square\square\square\square\square\square\square$	$\square\square\square\square\square\square\square\square\square\square$	$\square\square\square\square\square\square\square\square\square\square$
$U_A = \text{color}\{blue\}\{-\{1 \over C\} \cdot \int_{t_0}^{t_1} I_R \ dt + Q_0(t_0)\}$	Ausklammern	
$\square\square\square\square\square\square\square\square\square\square$	$\square\square\square\square\square\square\square\square\square\square$	$\square\square\square\square\square\square\square\square\square\square$
$U_A = -\{1 \over C\} \cdot \int_{t_0}^{t_1} I_R \ dt - \text{color}\{blue\}\{Q_0(t_0) \over C\}$	Integrationskonstante betrachten	$\text{color}\{blue\}\{Q_0(t_0) \over C\} = U_C(t_0) = -U_{A0}$
$\square\square\square\square\square\square\square\square\square\square$	$\square\square\square\square\square\square\square\square\square\square$	$\square\square\square\square\square\square\square\square\square\square$
$U_A = -\{1 \over C\} \cdot \int_{t_0}^{t_1} \text{color}\{blue\}\{I_R\} \ dt + U_{A0}$	mit VI. und II.	$\text{color}\{blue\}\{I_R\} = \{U_R \over R\} = \{U_E \over R\}$
$\square\square\square\square\square\square\square\square\square\square$	$\square\square\square\square\square\square\square\square\square\square$	$\square\square\square\square\square\square\square\square\square\square$
$U_A = -\{1 \over C\} \cdot \int_{t_0}^{t_1} \text{color}\{blue\}\{1 \over R\} \cdot U_E \ dt + U_{A0}$	Konstante vorziehen	
$\square\square\square\square\square\square\square\square\square\square$	$\square\square\square\square\square\square\square\square\square\square$	$\square\square\square\square\square\square\square\square\square\square$
$U_A = -\{1 \over R\} \cdot \int_{t_0}^{t_1} U_E \ dt + U_{A0}$	Zeitkonstante $\tau = R \cdot C$ einfügen	
$\square\square\square\square\square\square\square\square\square\square$	$\square\square\square\square\square\square\square\square\square\square$	$\square\square\square\square\square\square\square\square\square\square$
$U_A = -\{1 \over \tau\} \cdot \int_{t_0}^{t_1} U_E \ dt + U_{A0}$		
$\square\square\square\square\square\square\square\square\square\square$	$\square\square\square\square\square\square\square\square\square\square$	$\square\square\square\square\square\square\square\square\square\square$

From: <https://wiki.mexle.org/> - MEXLE Wiki

Permanent link: https://wiki.mexle.org/elektronische_schaltungstechnik/rechnung_umkehrintegrator?rev=1623894980

Last update: 2021/06/17 03:56

