

rechnung_umkehrintegrator

Student Group

| First Name | Surname | Matrikel Nr. |
|------------|---------|--------------|
| | | |
| | | |
| | | |

Table of Contents

| | | |
|---|--|---|
| $U_A = f(U_E)$ | mit III. | |
| $\square\square\square\square\square\square\square\square\square\square$ | $\square\square\square\square\square\square\square\square\square\square$ | $\square\square\square\square\square\square\square\square\square\square$ |
| $U_A = \text{color}\{blue\}\{-U_D\} - U_C$ | mit II. und I. | $\text{color}\{blue\}\{U_D\} = \{1 \over A_D\} \cdot U_A \overset{A_D}{\rightarrow \infty} \rightarrow 0$ |
| $\square\square\square\square\square\square\square\square\square\square$ | $\square\square\square\square\square\square\square\square\square\square$ | $\square\square\square\square\square\square\square\square\square\square$ |
| $U_A = \square 0 \square - \text{color}\{blue\}\{U_C\}$ | mit V. | $\text{color}\{blue\}\{U_C\} = \{1 \over C\} \cdot \int_{t_0}^{t_1} I_C \ dt + Q_0(t_0)$ |
| $\square\square\square\square\square\square\square\square\square\square$ | $\square\square\square\square\square\square\square\square\square\square$ | $\square\square\square\square\square\square\square\square\square\square$ |
| $U_A = \{-\{1 \over C\} \cdot \int_{t_0}^{t_1} \text{color}\{blue\}\{I_C\} \ dt + Q_0(t_0)\}$ | mit IV. | $\text{color}\{blue\}\{I_C\} = I_R$ |
| $\square\square\square\square\square\square\square\square\square\square$ | $\square\square\square\square\square\square\square\square\square\square$ | $\square\square\square\square\square\square\square\square\square\square$ |
| $U_A = \text{color}\{blue\}\{-\{1 \over C\} \cdot \int_{t_0}^{t_1} I_R \ dt + Q_0(t_0)\}$ | Ausklammern | |
| $\square\square\square\square\square\square\square\square\square\square$ | $\square\square\square\square\square\square\square\square\square\square$ | $\square\square\square\square\square\square\square\square\square\square$ |
| $U_A = -\{1 \over C\} \cdot \int_{t_0}^{t_1} I_R \ dt - \text{color}\{blue\}\{Q_0(t_0) \over C\}$ | Integrationskonstante betrachten | $\text{color}\{blue\}\{Q_0(t_0) \over C\} = U_C(t_0) = -U_{A0}$ |
| $\square\square\square\square\square\square\square\square\square\square$ | $\square\square\square\square\square\square\square\square\square\square$ | $\square\square\square\square\square\square\square\square\square\square$ |
| $U_A = -\{1 \over C\} \cdot \int_{t_0}^{t_1} \text{color}\{blue\}\{I_R\} \ dt + U_{A0}$ | mit VI. und II. | $\text{color}\{blue\}\{I_R\} = \{U_R \over R\} = \{U_E \over R\}$ |
| $\square\square\square\square\square\square\square\square\square\square$ | $\square\square\square\square\square\square\square\square\square\square$ | $\square\square\square\square\square\square\square\square\square\square$ |
| $U_A = -\{1 \over C\} \cdot \int_{t_0}^{t_1} \text{color}\{blue\}\{1 \over R\} \cdot U_E \ dt + U_{A0}$ | Konstante vorziehen | |
| $\square\square\square\square\square\square\square\square\square\square$ | $\square\square\square\square\square\square\square\square\square\square$ | $\square\square\square\square\square\square\square\square\square\square$ |
| $U_A = -\{1 \over R\} \cdot \int_{t_0}^{t_1} U_E \ dt + U_{A0}$ | Zeitkonstante $\tau = R \cdot C$ einfügen | |
| $\square\square\square\square\square\square\square\square\square\square$ | $\square\square\square\square\square\square\square\square\square\square$ | $\square\square\square\square\square\square\square\square\square\square$ |
| $U_A = -\{1 \over \tau\} \cdot \int_{t_0}^{t_1} U_E \ dt + U_{A0}$ | | |
| $\square\square\square\square\square\square\square\square\square\square$ | $\square\square\square\square\square\square\square\square\square\square$ | $\square\square\square\square\square\square\square\square\square\square$ |

From: <https://wiki.mexle.org/> - MEXLE Wiki

Permanent link: https://wiki.mexle.org/elektronische_schaltungstechnik/rechnung_umkehrintegrator?rev=1623895674

Last update: 2021/06/17 04:07

