

calc_decimal_example

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

$(10) \quad U_2 = U_A \cdot \frac{R_2}{R_1 + R_2}$	Spannungsteilerformel
--	-----------------------

II. Betrachtung der Spannungsverstärkung

aus (0)	$A_V = \frac{U_A}{U_E}$	
	$A_V = \frac{U_A}{U_2 + U_D}$	mit (4): $U_E = U_2 + U_D$
	$A_V = \frac{U_A}{U_2 + U_D}$	
	$A_V = \frac{U_A}{U_2 + U_D}$	mit (10): $U_2 = U_A \cdot \frac{R_2}{R_1 + R_2}$
	$A_V = \frac{U_A}{U_A \cdot \frac{R_2}{R_1 + R_2} + U_D}$	
	$A_V = \frac{U_A}{U_A \cdot \frac{R_2}{R_1 + R_2} + U_D}$	mit (1)
	$A_V = \frac{U_A}{U_A \cdot \frac{R_2}{R_1 + R_2} + \frac{U_A}{A_D}}$	
	$A_V = \frac{U_A}{U_A \cdot \frac{R_2}{R_1 + R_2} + \frac{U_A}{A_D}}$	Erweitern mit $\frac{1}{U_A}$
	$A_V = \frac{1}{\frac{R_2}{R_1 + R_2} + \frac{1}{A_D}}$	Bruch umformen
	$A_V = \frac{1}{\frac{R_2}{R_1 + R_2} + \frac{1}{A_D}}$	

From:
<https://wiki.mexle.org/> - MEXLE Wiki

Permanent link:
https://wiki.mexle.org/introduction_to_digital_systems/calc_decimal_example?rev=1631665365

Last update: 2021/09/15 02:22

