

Inverting Operational Amplifier

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Inverting Operational Amplifier

Gain of Op-Amp

Investigation of inverting input

2

2

3

Inverting Operational Amplifier

Gain of Op-Amp

Build the following circuit in [figure 1](#) with the power supply and a multimeter.




Fig. 1: Inverting Op-Amp

$$U_{DD} = 10\text{ V}, U_{SS} = -10\text{ V}, R_1 = 10\text{ k}\Omega$$

Calculate the necessary value for R_2 , so that the Output U_{OUT} is +5 V. Use the supply voltage of the operational amplifier for U_{IN} .

$$U_{IN} =$$

R_2

Investigation of inverting input




Fig. 2: Inverting Op-Amp: Investigate inverting input

$U_{DD} = 10\text{V}$, $U_{SS} = -10\text{V}$, $R_1 = 10\text{k}\Omega$

For U_{IN} , U_{OUT} , R_2 use the values from [figure 1](#).

Complete the arrows in the schematic of the circuit.

Determine the currents I_1 and I_2 indirectly through a voltage measurement.

Calculate the sum of the currents at node N_{12} .

I_1

I_2

ΣI

- Virt masse messen
- r2 kurzschluss

From:

<https://wiki.mexle.org/> - MEXLE Wiki

Permanent link:

https://wiki.mexle.org/lab05_en/inverting_op-amp_basics_amplification?rev=1775057225

Last update: **2026/04/01 17:27**

