

Inverting Operational Amplifier

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Inverting Operational Amplifier 2
Gain of Op-Amp 2
Investigation of inverting input 3

Inverting Operational Amplifier

Gain of Op-Amp

Build the following circuit in [figure 1](#) with the power supply and a multimeter.



Fig. 1: Inverting Op-Amp

$U_{DD} = 10\text{ V}$, $U_{SS} = -10\text{ V}$, $R_1 = 10\text{ k}\Omega$

Calculate the necessary value for R_2 , so that the Output U_{OUT} is +5 V. Use the supply voltage of the operational amplifier for U_{IN} .

$U_{IN} =$

$$R_2$$

Investigation of inverting input



Fig. 2: Inverting Op-Amp: Investigate currents of the inverting input

$$U_{DD} = 10V, U_{SS} = -10V, R_1 = 10k\Omega$$

Use the values from figure 1 for U_{IN}, U_{OUT}, R_2 .

Complete the arrows in the scematic of the circuit.

Determine the the currents I_1 and I_2 indirectly through a voltage measurement.

Calculate the sum of the currents at node N_{12} .

$$U_1$$

$$U_2$$

$$I_1$$

$$I_2$$

$$I_{N12}$$

-NEW-



Fig. 3: Inverting Op-Amp: Investigate the virtual GND of the inverting input

$$U_{DD} = 10V, U_{SS} = -10V, R_1 = 10k\Omega$$

Use the values from figure 1 for U_{IN}, U_{OUT}, R_2 .

Complete the arrows in the scematic of the circuit.

Determine the the currents I_1 and I_2 indirectly through a voltage measurement. Calculate the sum of the currents at node N_{12} .

$$U_1$$

$$U_2$$

$I_{\text{1}} \approx I_{\text{2}}$

$I_{\text{2}} \approx I_{\text{N12}}$

$I_{\text{N12}} \approx I_{\text{2}}$

- Virt masse messen
- r2 kurzschluss

From:

<https://wiki.mexle.org/> - MEXLE Wiki

Permanent link:

https://wiki.mexle.org/lab05_en/inverting_op-amp_basics_amplification?rev=1775121959

Last update: **2026/04/02 11:25**

