

# Inverting Operational Amplifier

## Student Group

| First Name | Surname | Matrikel Nr. |
|------------|---------|--------------|
|            |         |              |
|            |         |              |
|            |         |              |

## Table of Contents

Inverting Operational Amplifier ..... 2  
Gain of Op-Amp ..... 2  
Investigation of inverting input ..... 3

## Inverting Operational Amplifier

### Gain of Op-Amp

Build the following circuit in [figure 1](#) with the power supply and a multimeter.



Fig. 1: Inverting Op-Amp

$U_{DD} = 10\text{ V}$ ,  $U_{SS} = -10\text{ V}$ ,  $R_1 = 10\text{ k}\Omega$

Calculate the necessary value for  $R_2$ , so that the Output  $U_{OUT}$  is +5 V. Use the supply voltage of the operational amplifier for  $U_{IN}$ .

$U_{IN} =$

$$R_2$$

**Investigation of inverting input**



Fig. 2: Inverting Op-Amp: Investigate currents of the inverting input

$$U_{DD} = 10\text{V}, U_{SS} = -10\text{V}, R_1 = 10\text{k}\Omega$$

Use the values from figure 1 for  $U_{IN}$ ,  $U_{OUT}$ ,  $R_2$ .

Complete the arrows in the schematic of the circuit.

Determine the the currents  $I_1$  and  $I_2$  indirectly by measuring the voltage.

Calculate the sum of the currents at node  $N_{12}$ .

$$U_1$$

$$U_2$$

$$I_1$$

$$I_2$$

$$I_{N12}$$



Fig. 3: Inverting Op-Amp: Investigate the virtual GND of the inverting input

$$U_{DD} = 10V, U_{SS} = -10V, R_1 = 10k\Omega$$

Use the values from figure 1 for  $U_{IN}, U_{OUT}, R_2$ .

Complete the arrows in the scematic of the circuit.

Determine the the currents  $I_1$  and  $I_2$  indirectly through a voltage measurement. Calculate the sum of the currents at node  $N_{12}$ .

$$U_1$$

$$U_2$$

$$I_{\text{1}} \approx I_{\text{2}}$$
$$I_{\text{2}} \approx I_{\text{N12}}$$
$$I_{\text{N12}} \approx I_{\text{2}}$$

- Virt masse messen
- r2 kurzschluss

From:

<https://wiki.mexle.org/> - MEXLE Wiki

Permanent link:

[https://wiki.mexle.org/lab05\\_en/inverting\\_op-amp\\_basics\\_amplification?rev=1775122828](https://wiki.mexle.org/lab05_en/inverting_op-amp_basics_amplification?rev=1775122828)

Last update: **2026/04/02 11:40**

