

# Inverting Operational Amplifier

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

Inverting Operational Amplifier .....	2
Gain of Op-Amp .....	2
Investigation of inverting input .....	3

## Inverting Operational Amplifier

### Gain of Op-Amp

Build the following circuit in [figure 1](#) with the power supply and a multimeter.




Fig. 1: Inverting Op-Amp

$U_{DD} = 10\text{ V}$ ,  $U_{SS} = -10\text{ V}$ ,  $R_1 = 10\text{ k}\Omega$

Calculate the necessary value for  $R_2$ , so that the Output  $U_{OUT}$  is +5 V. Use the supply voltage of the operational amplifier for  $U_{IN}$ .

$U_{IN} =$

$$R_2$$

### Investigation of inverting input



Fig. 2: Inverting Op-Amp: Investigate currents of the inverting input

$$U_{DD} = 10\text{V}, U_{SS} = -10\text{V}, R_1 = 10\text{k}\Omega$$

Use the values from [figure 1](#) for  $U_{IN}$ ,  $U_{OUT}$ ,  $R_2$ .

Complete the arrows in the schematic of the circuit.

Determine the the currents  $I_1$  and  $I_2$  indirectly by measuring the voltage.

Calculate the sum of the currents at node  $N_{12}$ .

$$U_1$$

$$U_2$$

$I_{1}$

$I_{2}$

$I_{N12}$



Fig. 3: Inverting Op-Amp: Investigate the virtual GND of the inverting input

$U_{DD} = 10V, U_{SS} = -10V, R_1 = 10k\Omega$

Use the values from figure 1 for  $U_{IN}, U_{OUT}, R_2$ .

Complete the arrows in the scematic of the circuit.

Take the values for  $U_1, U_2$  from the mesurments from figure 2 .

Calculate the sum of the voltages at node  $N_{12}$  and compare it to measurement. What are your results?

$U_1$

$U_2$

Calculated  $U_{12}$

Measured  $U_{12}$

$\{ \dots \}$

$\{\rm \dots\dots\dots\}$

$\{\rm \dots\dots\dots\}$

- Virt masse messen
- r2 kurzschluss

From:  
<https://wiki.mexle.org/> - **MEXLE Wiki**

Permanent link:  
[https://wiki.mexle.org/lab05\\_en/inverting\\_op-amp\\_basics\\_amplification?rev=1775123686](https://wiki.mexle.org/lab05_en/inverting_op-amp_basics_amplification?rev=1775123686)

Last update: **2026/04/02 11:54**

