

# Inverting Operational Amplifier

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

Inverting Operational Amplifier ..... 2  
Gain of Op-Amp ..... 2  
Investigation of inverting input ..... 3

## Inverting Operational Amplifier

### Gain of Op-Amp

Build the following circuit in [figure 1](#) with the power supply and a multimeter.



Fig. 1: Inverting Op-Amp

$U_{DD} = 10\text{ V}$ ,  $U_{SS} = -10\text{ V}$ ,  $R_1 = 10\text{ k}\Omega$

Calculate the necessary value for  $R_2$ , so that the Output  $U_{OUT}$  is +5 V. Use the supply voltage of the operational amplifier for  $U_{IN}$ .

$U_{IN} =$

$$R_2$$

**Investigation of inverting input**



Fig. 2: Inverting Op-Amp: Investigate currents of the inverting input

$$U_{DD} = 10\text{V}, U_{SS} = -10\text{V}, R_1 = 10\text{k}\Omega$$

Use the values from figure 1 for  $U_{IN}, U_{OUT}, R_2$ .

Complete the arrows in the schematic of the circuit.

Determine the the currents  $I_1$  and  $I_2$  indirectly by measuring the voltage.

Calculate the sum of the currents at node  $N_{12}$ .

$$U_1$$

$$U_2$$

$I_{\text{1}} \approx$

$I_{\text{2}} \approx$

$I_{\text{N12}} \approx$




Fig. 3: Inverting Op-Amp: Investigate the virtual GND of the inverting input

$U_{\text{DD}} = 10\text{V}, U_{\text{SS}} = -10\text{V}, R_{\text{1}} = 10\text{k}\Omega$

Use the values from figure 1 for  $U_{\text{IN}}, U_{\text{OUT}}, R_{\text{2}}$ .

Complete the arrows in the schematic of the circuit.

Take the values for  $U_{\text{1}}, U_{\text{2}}, U_{\text{OUT}}$  from figure 2.

Use these values to calculate the sum of the voltages at node  $N_{\text{12}}$ .

Compare your result by measurement.

$U_{\text{1}} \approx$

$U_{\text{2}} \approx$

$U_{\text{OUT}} \approx$

Calculated  $U_{\text{N12}} \approx$

Measured  $U_{\text{N12}} \approx$

What are your results?

$\{\rm \dots\}$

$\{\rm \dots\}$

$\{\rm \dots\}$

What will happen if you short-circuit  $R_2$ ?

Try it and explain your results.

$\{\rm \dots\}$

$\{\rm \dots\}$

$\{\rm \dots\}$

$\{\rm \dots\}$

$\{\rm \dots\}$

$\{\rm \dots\}$

$\{\rm \dots\}$

$\{\rm \dots\}$

$\{\rm \dots\}$

$\{\rm \dots\}$

$\{\rm \dots\}$

From:  
<https://wiki.mexle.org/> - **MEXLE Wiki**

Permanent link:  
[https://wiki.mexle.org/lab05\\_en/inverting\\_op-amp\\_basics\\_amplification?rev=1775125128](https://wiki.mexle.org/lab05_en/inverting_op-amp_basics_amplification?rev=1775125128)

Last update: **2026/04/02 12:18**

