

Inverting Operational Amplifier

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

- Inverting Operational Amplifier 2
- Gain of Op-Amp 2
- Analysis of inverting input currents 3
- Analysis of inverting input voltages 4

Inverting Operational Amplifier

Gain of Op-Amp

Build the following circuit in [figure 1](#) with the power supply and a multimeter.



Fig. 1: Inverting Op-Amp

$U_{DD} = 10\text{ V}$, $U_{SS} = -10\text{ V}$, $R_1 = 100\text{ k}\Omega$

Calculate the necessary value for R_2 , so that the output U_{OUT} is $+1.5\text{ V}$. Use the supply voltage of the operational amplifier for U_{IN} .

$U_{IN} =$

$$R_2$$

Analysis of inverting input currents



Fig. 2: Inverting Op-Amp: Analysis of currents of the inverting input

$U_{DD} = 10\text{V}$, $U_{SS} = -10\text{V}$, $R_1 = 100\text{k}\Omega$ Use the values from [figure 1](#) for U_{IN} , U_{OUT} , R_2 .

Complete the reference arrows in the schematic of the circuit. Determine the the currents I_1 and I_2 indirectly by measuring the voltage across known resistors and calculate the algebraic sum of the currents at node N_{12} using Kirchhoff's Current Law (KCL).

$$U_1$$

$$U_2$$

$$I_1$$

$$I_2$$

V_{N12}

Analysis of inverting input voltages




Fig. 3: Inverting Op-Amp: Analysis of virtual GND of the inverting input

$V_{DD} = 10V, V_{SS} = -10V, R_1 = 100k\Omega$

Use the values from figure 1 for V_{IN}, V_{OUT}, R_2 .

Complete the reference arrows in the schematic of the circuit.

Take the values for V_1, V_2, V_{OUT} from figure 2.

Calculate the voltage V_{12} using Kirchhoff's Voltage Law (KVL) within one of the possible circuit loops. Mark the chosen loop in the circuit.

Verify your calculated result by measuring V_{12} .

$V_1 =$

$V_2 =$

$V_{OUT} =$

$V_{OUT} =$

Calculated $V_{12} =$

Measured $V_{12} =$

Analyse the physical significance of the potential at N_{12} relative to GND (defined as U_{12}) in the context of the operational amplifier's input configuration. What do you observe?

- $\{\text{rm} \dots\}$
- $\{\text{rm} \dots\}$
- $\{\text{rm} \dots\}$
- $\{\text{rm} \dots\}$
- $\{\text{rm} \dots\}$
- $\{\text{rm} \dots\}$
- $\{\text{rm} \dots\}$
- $\{\text{rm} \dots\}$
- $\{\text{rm} \dots\}$
- $\{\text{rm} \dots\}$
- $\{\text{rm} \dots\}$

What happens if you short-circuit R_2 (the feedback resistor)? Experimentally verify this effect and explain the observed behavior regarding the output voltage.

- $\{\text{rm} \dots\}$
- $\{\text{rm} \dots\}$
- $\{\text{rm} \dots\}$
- $\{\text{rm} \dots\}$
- $\{\text{rm} \dots\}$
- $\{\text{rm} \dots\}$
- $\{\text{rm} \dots\}$
- $\{\text{rm} \dots\}$
- $\{\text{rm} \dots\}$
- $\{\text{rm} \dots\}$
- $\{\text{rm} \dots\}$

$\{\rm \dots\dots\dots\}$

From:
<https://wiki.mexle.org/> - **MEXLE Wiki**

Permanent link:
https://wiki.mexle.org/lab05_en/inverting_op-amp_basics_amplification?rev=1778149868

Last update: **2026/05/07 12:31**

